



TEST DATA
MODEL 6000, 6000A
6000B & 6005
TUBE TESTERS

THE HICKOK ELECTRICAL INSTRUMENT CO.
10514 DUPONT AVENUE • CLEVELAND, OHIO 44108
PHONE—(216) 541-8060 **TWX—810-421-8286**
PRINTED IN U.S.A.

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS	TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS	
1A3	1.4	HR-0203-0	0	0	C	Diode	2DS4†	2.0	DR-4208-0	22	79	A	2600	USE ADAPTER SA-3, 105B-127, NOTE 3
1AD2†	1.4	B3-0X00-0	0	42	F	OK ABOVE DIODES OK	Model 6000 A:							
1AD4	1.1	DV-4120-0	17	62	B	1400	2DS4	2.0	13-4208-0	22	79	A	2600	
1AG4	1.1	DV-4120-0	27	48	B	1000	2DV4†	2.0	13-6107-0	27	88	A	4600	
1AH4	1.1	FT-4120-0	17	0	B	500	2DX4	2.5	ET-2105-0	29	85	A	3800	
1AK4	1.1	FT-4120-0	17	0	B	500	2EA5	2.5	ET-1562-0	11	86	A	4000	
1AU2	1.1	EV-0900-0	0	81	F		2EG4†	2.0	DR-4208-0	22	72	A	2500	MAKE "LINE TEST" AT 1425 ON 300 SCALE. USE ADAPTER SA-3, 105B-127, NOTE 3
1AY2	1.1	CX-0X00-0	0	86	F		Model 6000A:							
1B3	1.1	HS-0X00-0	0	80	F		2EG4	2.0	13-4208-0	22	72	A	2500	Diode No. 1
1BC2	1.1	BV-0X00-0	0	73	F		2EN5	2.0	ET-0705-6	0	80	C		Diode No. 2
1BH2	1.1	DW-0X00-0	0	73	F		2EN5	2.0	ET-0205-6	0	80	C		
1BK2	1.4	BS-0X00-0	0	85	F		2ER5	2.0	ET-2567-0	10	89	A	5000	
1BX2	1.4	BS-0X00-0	0	80	F		2ES5	2.5	ET-2501-0	10	87	A	4600	
1BY2†	1.1	B3-0X00-0	0	42	F		2EV5	2.5	ET-1562-0	21	87	A	4000	
1DG3	1.1	DY-0X00-0	0	42	F		2FH5	2.5	ET-2507-0	14	87	A	4600	
1D-K29	1.1	BS-0X00-0	0	0	D		2FQ5	2.5	ET-2507-0	19	87	A	4500	
1G3	1.1	HS-0X00-0	0	80	F		2FQ5A	2.5	ET-2507-6	19	89	A	5200	
1H2	1.4	BS-0X00-0	0	76	F		2FS5	2.5	ET-1567-0	10	85	A	3500	
1K3	1.1	HS-0X00-0	0	42	F		2FV6	2.5	ET-1567-2	12	85	A	3800	
1N2	1.1	HS-0X00-0	0	80	F		2GK5	2.5	ET-2507-6	19	89	A	5200	
1R5	1.4	BX-4306-2	55	63	A	1100	2GU5	2.5	ET-1562-0	13	89	A	5500	
1R-K23	1.4	ES-0X00-0	0	85	F		2GW5	2.5	ET-2105-0	20	88	A	5000	
1S2A	1.4	ES-0X00-0	0	85	F		2HA5	2.0	ET-1507-6	20	87	A	4600	
1S4	1.4	BX-3240-0	29	65	B	1500	2HK5	2.5	ET-1502-0	19	88	A	5000	
1S5	1.4	BX-6510-0	11	0	B	500	2HM5	2.5	ET-1507-6	20	87	A	4400	
1S5	1.4	BX-0300-0	0	0	C		2HU5	2.5	ET-1507-6	20	87	A	4400	
1U4	1.4	BX-6230-0	14	42	A	900	2T4	2.5	ET-2105-0	36	88	A	5000	
1V2	1.1	EV-0900-0	0	78	F		3A2	3.0	BS-0X00-0	0	85	F		
1W5	1.1	EV-2780-0	11	73	B	400	3A3	3.0	HS-0X00-0	0	75	F		
1X2	1.1	BS-0X00-0	0	80	F		3AF4	3.0	ET-2105-0	36	85	A	4000	
2AF4	2.5	ET-2105-0	36	85	A	4000	3AL5	3.0	ET-0701-6	0	78	C		Diode No. 1
2AH2†	2.5	B3-0X00-0	0	79	F		3AL5	3.0	ET-0205-6	0	78	C		Diode No. 2
2AS2†	2.5	B3-0X00-0	0	80	F		3AT2†	3.0	B3-0X00-0	0	84	F		OK ABOVE DIODES OK
2AV2	2.0	EV-0900-0	0	69	F		3AU6	3.0	ET-1567-2	11	76	A	2300	
2AZ2	2.0	BS-0X00-0	0	88	F		3AV6	3.0	ET-1702-5	12	58	A	1250	Triode Sect.
2BA2	2.0	EV-0100-0	0	90	F		3AV6	3.0	ET-0602-0	0	26	C		Diode No. 1
2BJ2	2.5	BS-0X00-0	0	78	F		3AV6	3.0	ET-0502-0	0	26	C		Diode No. 2
2BN4	2.0	ET-2501-0	19	88	A	5000	3AW2†	3.0	C3-0X00-0	0	87	F		OK ABOVE DIODES OK
2BN4A	2.0	ET-2501-0	19	86	A	3200	3AW3	3.0	HS-0X00-0	0	75	F		
2BU2†	2.5	B3-0X00-0	0	85	F		3B2	3.0	HS-0X00-0	0	70	F		
2C51	6.3	KR-7608-2	16	86	A	4000	3B4	2.5	EV-3710-0	50	69	A	1700	
2C51	6.3	KR-3402-8	16	86	A	4000	3BA6	3.0	ET-1567-2	11	72	A	1900	
2CN3A	2.0	HS-0X00-0	0	87	F		3BC5	3.0	ET-1562-0	11	78	A	2500	
2CW4†	2.0	DR-4208-0	23	79	A	2600	3BE6	3.0	ET-7562-1	0	35	B	800	AMPL. SECT. MAKE NO GAS TEST
Model 6000 A:							3BE6	3.0	ET-1602-7	20	90	A	6500	AMPL. SECT. MAKE GAS TEST
2CW4	2.0	13-4208-0	23	79	A	2600	3BL2†	3.0	B3-0X00-0	0	85	F		OK ABOVE DIODES OK
2CY5	2.5	ET-1562-0	11	81	B	3000	3BM2†	3.0	B3-0X00-0	0	85	F		OK ABOVE DIODES OK
2D2†	6.3	ET-1602-5	*	94	F		3BN2†	3.0	B3-0X00-0	0	68	F		
2DF4	2.5	EV-8310-0	21	88	A	3800	3BN4	3.0	ET-2501-0	19	68	A	5000	
						Strikes at about 24	3BN4A	3.0	ET-2501-0	19	86	A	3200	

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS	TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS
4HC7†	4.3	B3-9X04-0	12	84	A 3500	Triode No. 1	5B07A	5.0	EV-7608-9	13	90	A 6400	Triode No. 1
4HC7	4.3	B3-A203-0	19	27	A 700	Triode No. 2	5B07A	5.0	EV-2103-9	13	90	A 6400	Triode No. 2
4HK5	4.3	ET-1502-0	19	90	A 5900		5BR8	5.0	EV-9678-0	11	73	A 2000	Pent. Sect.
4HM5	4.3	ET-1507-6	20	87	A 4600		5BR8	5.0	EV-1203-0	12	90	A 6200	Triode Sect.
4HM6	4.3	EV-2781-9	11	87	A 4700		5BT8	5.0	EV-8679-0	19	75	A 2200	Pent. Sect.
4HQ5	4.3	ET-1507-6	20	87	A 4400		5BT8	5.0	EV-0103-0	0	63	C	Diode No. 1
4HS8	4.3	EV-7821-9	10	15	A 600	Pent. No. 1	5BT8	5.0	EV-0203-0	0	63	C	Diode No. 2
4HS8	4.3	EV-7321-6	10	15	A 600	Pent. No. 2	5BW8	5.0	EV-6987-0	11	73	A 2000	Pent. Sect.
4HT6	4.3	EV-2781-9	10	87	A 4600		5BW8	5.0	EV-0302-0	0	77	C	Diode No. 1
4JC6	4.3	EV-2781-9	10	89	A 5600		5BW8	5.0	EV-0102-0	0	77	C	Diode No. 2
4JD6	4.3	EV-2783-9	10	83	B 2600		5CQ8	5.0	EV-9678-0	12	81	A 3000	Pent. Sect.
4JH6	4.3	ET-1562-7	11	84	A 3700		5CQ8	5.0	EV-1203-0	20	84	A 3500	Triode Sect.
4JK6	4.3	ET-1562-7	10	86	A 4800		5CL8	5.0	EV-9678-0	10	84	A 3500	Tetrode Sect.
4JL6	4.3	ET-1562-7	16	85	A 4200		5CL8	5.0	EV-1203-0	12	89	A 6000	Triode Sect.
4JW8	4.3	EV-2367-0	17	87	A 2200	Pent. Sect.	5CM8	5.0	EV-2673-0	11	81	A 3000	Pent. Sect.
4JW8	4.3	EV-9108-0	19	66	A 1600	Triode Sect.	5CM8	5.0	EV-9108-0	12	65	A 1500	Triode Sect.
4KE8	4.3	EV-2637-0	11	85	A 3700	Pent. Sect.	5CQ8	5.0	EV-2637-0	10	79	A 2600	Tetrode Sect.
4KE8	4.3	EV-9108-0	20	87	A 4500	Triode Sect.	5CQ8	5.0	EV-9108-0	11	87	A 4300	Triode Sect.
4KF8	4.3	EV-7821-9	10	17	A 700	Pent. No. 1	5CZ5	5.0	EV-3917-0	10	87	A 4500	
4KF8	4.3	EV-7321-6	10	17	A 700	Pent. No. 2	5DH8	5.0	EV-9678-0	10	83	A 3400	Pent. Sect.
4KT6	4.3	EV-2781-9	15	81	A 2350		5DH8	5.0	EV-1203-0	15	78	A 2500	Triode Sect.
4LJ8	4.3	EV-9678-0	15	75	A 2800	Pent. Sect.	5DJ4	5.0	JS-0600-0	0	70	D	Plate No. 1
4LJ8	4.3	EV-1203-0	24	75	A 2600	Triode Sect.	5DJ4	5.0	JS-0400-0	0	65	D	Plate No. 2
4LU6	4.3	ET-1562-7	11	86	A 4200		5EA8	5.0	EV-2637-0	11	79	A 2600	Pent. Sect.
4MK8	4.3	EV-7821-9	11	30	F	Pent. No. 1	5EA8	5.0	EV-9108-0	11	89	A 5000	Triode Sect.
4MK8	4.3	EV-7321-6	11	30	F	Pent. No. 2	5ES8	5.0	EV-7608-0	22	92	A 7500	Triode No. 1
5AM8	5.0	EV-2631-9	11	79	A 2700	Pent. Sect.	5ES8	5.0	EV-2103-0	22	92	A 7500	Triode No. 2
5AM8	5.0	EV-0807-0	0	78	C	Diode Sect.	5EU8	5.0	EV-7198-0	11	79	A 2600	Pent. Sect.
5AN8	5.0	EV-8679-1	11	81	A 3000	Pent. Sect.	5EU8	5.0	EV-2306-0	11	89	A 5000	Triode Sect.
5AN8	5.0	EV-2173-6	24	83	A 3300	Triode Sect.	5EW6	5.0	ET-1562-7	11	84	A 3700	
5AQ5	5.0	ET-1562-0	11	86	A 4100		5FG7	5.0	EV-9678-0	10	82	A 3000	Pent. Sect.
5AR4	5.0	JS-0600-0	0	90	D	Plate No. 1	5FG7	5.0	EV-1203-0	18	88	A 4750	Triode Sect.
5AR4	5.0	JS-0400-0	0	90	D	Plate No. 2	5FV8	5.0	EV-9678-0	10	80	A 2750	Pent. Sect.
5AS8	5.0	EV-2913-7	11	81	A 3000	Pent. Sect.	5FV8	5.0	EV-1203-0	15	89	A 5500	Triode Sect.
5AS8	5.0	EV-0608-0	0	78	C	Diode Sect.	5GH8	5.0	EV-2637-0	11	82	A 3000	Pent. Sect.
5AT8	5.0	EV-9673-8	12	81	A 3000	Pent. Sect.	5GH8	5.0	EV-9108-0	21	85	A 3900	Triode Sect.
5AT8	5.0	EV-1203-8	20	84	A 3500	Triode Sect.	5GM6	5.0	ET-1562-7	10	86	A 5000	
5AU4	7.5	JS-0600-0	0	83	D	Plate No. 1	5GS7	5.0	EV-9678-0	10	85	A 3500	Pent. Sect.
5AU4	7.5	JS-0400-0	0	75	D	Plate No. 2	5GS7	5.0	EV-1203-0	31	85	A 3750	Triode Sect.
5AV8	5.0	EV-6987-0	11	81	A 3000	Pent. Sect.	5GX6	5.0	ET-1562-7	12	67	A 1600	
5AV8	5.0	EV-2301-0	24	83	A 3300	Triode Sect.	5GX7	5.0	EV-2671-0	11	84	A 3200	Pent. Sect.
5B8	5.0	EV-6987-1	11	81	A 3000	Pent. Sect.	5GX7	5.0	EV-9801-0	18	89	A 4800	Triode Sect.
5B8	5.0	EV-2301-9	24	83	A 3300	Triode Sect.	5HA7†	5.0	B3-9X04-0	20	76	A 2500	Triode No. 1
5BC3†	5.0	BT-0900-0	0	74	D	PLATE/USE ADAPTER NO. 1 5A-4 1928-144	5HA7	5.0	B3-A203-0	16	16	A 750	Triode No. 2
5BC3	5.0	BT-0500-0	0	82	D	PLATE/NOTES VOL. 2	5HB7	5.0	EV-2671-0	10	79	A 3100	Pent. Sect.
(Model 6000 A: No Adapter Required.)							5HB7	5.0	EV-9801-0	11	89	A 4500	Triode Sect.
5BE8	5.0	EV-9678-3	11	73	A 2000	Pent. Sect.	5HC7†	5.0	B3-9X04-0	12	84	A 3500	Triode No. 1
5BE8	5.0	EV-1203-0	12	90	A 6200	Triode Sect.	5HC7	5.0	B3-A203-0	19	27	A 700	Triode No. 2
5BK7A	5.0	EV-7608-9	20	85	A 4000	Triode No. 1	5HG8	5.0	EV-2893-0	10	84	A 3600	Pent. Sect.
5BK7A	5.0	EV-2103-9	20	85	A 4000	Triode No. 2	5HG8	5.0	EV-6703-0	32	82	A 3200	Triode Sect.
							5HZ6	5.0	ET-1562-7	10	65	A 1400	

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS	TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS
5J6	5.0	ET-5207-0	21	81	A 3000	Triode No. 1	6AB9†	6.3	FW-978X-0	15	81	A 3000	Tetrode No. 2
5J6	5.0	ET-6107-0	21	81	A 3000	Triode No. 2	6AB9	6.3	FW-3124-0	15	81	A 3000	Tetrode No. 2
5JK6	5.0	ET-1562-7	10	86	A 4800		6AC7	6.3	HS-4865-3	11	81	A 3000	
5JL6	5.0	ET-1562-7	16	85	A 4200		6AC9†	6.3	B3-9AX8-7	10	87	A 4200	Pent. Sect.
5JW8	5.0	EV-2637-0	17	87	A 2200	Pent. Sect.	6AC9	6.3	B3-0304-0	0	85	C	Diode No. 1
5JW8	5.0	EV-9108-0	19	66	A 1600	Triode Sect.	6AC9	6.3	B3-0203-0	0	85	C	Diode No. 2
5KD8	5.0	EV-2637-0	10	79	A 2600	Pent. Sect.	6AC10†	6.3	B3-9X04-0	14	85	A 3700	Triode No. 1
5KD8	5.0	EV-9108-0	19	89	A 5200	Triode Sect.	6AC10	6.3	B3-7506-0	14	85	A 3700	Triode No. 2
5KE8	5.0	EV-2637-0	11	85	A 3700	Pentode Sect.	6AC10	6.3	B3-A203-0	14	85	A 3700	Triode No. 3
5KE8	5.0	EV-9108-0	20	87	A 4500	Triode Sect.	6AD10†	6.3	B3-3762-5	17	62	A 1900	Pent. No. 1
5KZ8	5.0	EV-2673-0	12	82	A 3200	Pent. Sect.	6AD10	6.3	B3-8AX9-0	7	89	A 3800	Pent. No. 2
5KZ8	5.0	EV-9108-0	22	84	A 3600	Triode Sect.	6AF3	6.3	EV-020X-0	0	86	D	
5LJ8	5.0	EV-9678-0	15	75	A 2800	Pent. Sect.	6AF4	6.3	ET-2105-0	36	85	A 4000	
5LJ8	5.0	EV-1203-0	24	75	A 2500	Triode Sect.	6AF9†	6.3	FW-8X97-0	13	88	A 5000	
5MB8	5.0	EV-9678-0	8	84	A 4000	Pent. Sect.	6AF9	6.3	FW-1432-0	13	83	A 3300	Pent. No. 2
5MB8	5.0	EV-1203-0	13	88	A 4800	Triode Sect.	6AF11†	6.3	B3-A2X9-0	10	88	A 4900	Pent. Sect.
5MQ8	5.0	EV-2637-0	15	80	A 3000	Pent. Sect.	6AF11	6.3	B3-6805-0	18	77	A 2400	Triode No. 1
5MQ8	5.0	EV-9108-0	20	83	A 3300	Triode Sect.	6AF11	6.3	B3-3407-0	10	80	A 2800	Triode No. 2
5R4	5.0	JS-0600-0	0	45	D	Plate No. 1	6AG5	6.3	ET-1562-0	11	78	A 2500	
5R4	5.0	JS-0400-0	0	35	D	Plate No. 2	6AG7	6.3	HS-4865-1	11	88	A 5000	
5T8	5.0	EV-8907-0	11	56	A 1200	Triode Sect.	6AG9†	6.3	B3-A2X9-4	19	78	A 2500	Pent. Sect.
5T8	5.0	EV-0607-0	0	77	C	Diode No. 1	6AG9	6.3	B3-5706-0	14	87	A 4600	Triode Sect.
5T8	5.0	EV-0203-0	0	77	C	Diode No. 2	6AG11†	6.3	B3-8709-0	16	86	A 4000	Triode No. 1
5T8	5.0	EV-0107-0	0	77	C	Diode No. 3	6AG11	6.3	B3-5604-0	16	86	A 4000	Triode No. 2
5U4G	5.0	JS-0600-0	0	45	D	Plate No. 1	6AG11	6.3	B3-0X0A-0	0	80	C	Diode No. 1
5U4G	5.0	JS-0400-0	0	35	D	Plate No. 2	6AG11	6.3	B3-0302-0	0	80	C	Diode No. 2
5U4GA,B	5.0	JS-0600-0	0	70	D	Plate No. 1	6AH9†	6.3	B3-5A87-9	10	87	A 5200	Pentode Sect.
5U4GA,B	5.0	JS-0400-0	0	66	D	Plate No. 2	6AH9	6.3	B3-2304-0	27	77	A 2350	Triode Sect.
5U8	5.0	EV-2637-0	11	73	A 2800	Pent. Sect.	6AK5	6.3	ET-1562-0	24	65	A 1500	
5U8	5.0	EV-9108-0	12	90	A 6200	Triode Sect.	6AK6	6.3	ET-1567-2	20	74	A 2100	
5U9†	6.3	FW-3782-4	10	83	A 3300	PENT. SECT. USE ADAPTER SA-11, 1099-177 MODEL 600, 605 NOTE 1	6AK9†	6.3	B3-8597-0	30	85	A 4150	Pent. Sect.
5U9	6.3	FW-X901-0	29	81	A 3000	Triode Sect.	6AK9	6.3	B3-XA07-0	18	75	A 2400	Triode No. 1
5V3	6.3	JS-0600-4	0	80	D	Plate No. 1	6AK9	6.3	B3-3207-0	26	59	A 1750	Triode No. 2
5V3	6.3	JS-0400-6	0	70	D	Plate No. 2	6AK10†	6.3	B3-9X04-0	14	85	A 4500	Triode No. 1
5V4	5.0	JS-0600-0	0	85	D	Plate No. 1	6AK10	6.3	B3-7506-0	14	85	A 4500	Triode No. 2
5V4	5.0	JS-0400-0	0	85	D	Plate No. 2	6AK10	6.3	B3-A203-0	14	85	A 4500	Triode No. 3
5V6	5.0	HS-5348-0	13	86	A 4100		6AL3	6.3	EV-090X-0	0	93	D	
5V9†	5.0	FW-3741-2	10	48	B 1000	HEPT. SECT. USE ADAPTER SA-11, 1099-177 MODEL 600, 605 NOTE 1	6AL5	6.3	ET-0701-6	0	78	C	Diode No. 1
5V9	5.0	FW-8X09-0	22	81	A 3000	Triode Sect.	6AL5	6.3	ET-0205-6	0	78	C	Diode No. 2
5X8	5.0	EV-7986-1	12	81	A 3000	Pent. Sect.	6AL9†	6.3	B3-A2X9-4	5	91	A 9000	Pent. Sect.
5X8	5.0	EV-2306-1	20	84	A 3500	Triode Sect.	6AL9	6.3	B3-5706-0	9	88	A 6300	Triode Sect.
5X9†	6.3	FW-3782-4	10	84	A 3600	PENT. SECT. USE ADAPTER SA-11, 1099-177 MODEL 600, 605 NOTE 1	6AL11†	6.3	B3-8AX9-0	14	87	A 4300	Pent. No. 1
5X9	6.3	FW-X901-0	12	81	A 3000	Triode Sect.	6AL11	6.3	B3-3672-4	20	21	A 620	Pent. No. 2
5Y3	5.0	JS-0600-0	0	22	D	Plate No. 1	6AM8	6.3	EV-2631-9	11	79	A 2700	Pent. Sect.
5Y3	5.0	JS-0400-0	0	18	D	Plate No. 2	6AM8	6.3	EV-0807-0	0	78	C	Diode Sect.
6AB4	6.3	ET-6107-0	10	85	A 4000		6AN4	6.3	ET-2105-0	13	89	A 5500	
							6AN5	6.3	ET-1567-0	13	85	B 4000	
							6AN8	6.3	EV-8679-1	11	81	A 3000	Pent. Sect.
							6AN8	6.3	EV-2173-6	24	83	A 3300	Triode Sect.

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS	TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS
6AQ5	6.3	ET-1562-0	11	86	A 4100		6BA8	6.3	EV-7986-0	11	88	A 5000	Pent. Sect.
6AR11†	6.3	B3-X89A-7	10	81	A 2700	Pent. No. 1	6BA8	6.3	EV-2301-0	30	79	A 2700	Triode Sect.
6AR11	6.3	B3-5236-4	10	81	A 2700	Pent. No. 2	6BA11†	6.3	B3-4638-7	10	15	A 600	Pent. No. 1
6AS6	6.3	ET-1562-7	11	48	B 1000		6BA11	6.3	B3-4238-5	10	15	A 600	Pent. No. 2
6AS7	7.5	HY-4506-2	100	79	A 2500	Triode No. 1	6BA11	6.3	B3-9A0X-0	30	62	A 1600	Triode Sect.
6AS7	7.5	HY-1203-5	100	79	A 2500	Triode No. 2	6BC4	6.3	EV-2106-0	12	91	A 7000	
6AS8	6.3	EV-2913-7	11	81	A 3000	Pent. Sect.	6BC5	6.3	ET-1562-0	11	78	A 2500	
6AS8	6.3	EV-0608-0	0	78	C	Diode Sect.	6BC7	6.3	EV-0809-3	0	80	C	Diode No. 1
6AS11†	6.3	B3-A2X9-0	10	88	A 5000	Pent. Sect.	6BC7	6.3	EV-0607-3	0	80	C	Diode No. 2
6AS11	6.3	B3-6805-0	14	85	A 3800	Triode No. 1	6BC7	6.3	EV-0201-3	0	80	C	Diode No. 3
6AS11	6.3	B3-3407-0	16	83	A 3300	Triode No. 2	6BC8	6.3	EV-7608-9	16	90	A 6200	Triode No. 1
6AT6	6.3	ET-1702-0	10	60	A 1300	Triode Sect.	6BC8	6.3	EV-2103-9	16	90	A 6200	Triode No. 2
6AT6	6.3	ET-0602-0	0	26	C	Diode No. 1	6BD11†	6.3	B3-A2X9-0	13	87	A 4500	Pent. Sect.
6AT6	6.3	ET-0502-0	0	26	C	Diode No. 2	6BD11	6.3	B3-6805-0	17	78	A 2500	Triode No. 1
6AT8	6.3	EV-9673-8	12	81	A 3000	Pent. Sect.	6BD11	6.3	B3-3407-0	11	80	A 2750	Triode No. 2
6AT8	6.3	EV-1203-8	20	84	A 3500	Triode Sect.	6BE3†	6.3	B3-0X07-0	0	89	D	
6AU4	6.3	HY-0503-0	0	89	D		6BE6	6.3	ET-7562-1	0	35	B 800	AMPL. SECT. MAKE NO GAS TEST
6AU5	6.3	HS-1583-0	25	88	A 5200		6BE6	6.3	ET-1602-7	20	90	A 6500	OSC. SECT. MAKE GAS TEST
6AU6	6.3	ET-1567-2	11	76	A 2300		6BF11†	6.3	B3-8AX9-0	25	88	A 5000	Pent. No. 1
6AU8	6.3	EV-7986-0	11	86	A 4200	Pent. Sect.	6BF11	6.3	B3-3762-5	13	7	A 550	Pent. No. 2
6AU8	6.3	EV-2301-0	15	86	A 4000	Triode Sect.	6BH3†	6.3	EV-0209-0	0	87	D	USE ADAPTER SA-4, 105B-144, NOTE 3
6AV6	6.3	ET-1702-6	12	58	A 1250	Triode Sect.	Model 6000 A:	No Adapter Required.					
6AV6	6.3	ET-0602-0	0	26	C	Diode No. 1	6BH6	6.3	ET-1562-7	12	73	A 2000	
6AV6	6.3	ET-0502-0	0	26	C	Diode No. 2	6BH8	6.3	EV-7986-0	7	88	A 5000	Pent. Sect.
6AV11†	6.3	B3-9X04-0	22	78	A 2500	Triode No. 1	6BH8	6.3	EV-2301-0	27	83	A 3300	Triode Sect.
6AV11	6.3	B3-7506-0	22	78	A 2500	Triode No. 2	6BH11†	6.3	B3-8X9A-0	10	84	A 3500	Pent. Sect.
6AV11	6.3	B3-A203-0	22	78	A 2500	Triode No. 3	6BH11	6.3	B3-6705-0	18	89	A 5100	Triode No. 1
6AW8	6.3	EV-7986-0	10	88	A 5000	Pent. Sect.	6BH11	6.3	B3-4302-0	18	89	A 5100	Triode No. 2
6AW8	6.3	EV-2301-0	15	78	A 2500	Triode Sect.	6BJ3†	6.3	B3-0X07-0	0	88	D	
6AX3†	6.3	B3-0407-0	0	82	D		6BJ7	6.3	EV-0809-3	0	80	C	Diode No. 1
6AX4	6.3	HY-0503-0	0	82	D		6BJ7	6.3	EV-0607-3	0	80	C	Diode No. 2
6AX5	6.3	HS-0508-3	0	20	D	Plate No. 1	6BJ7	6.3	EV-0201-3	0	80	C	Diode No. 3
6AX5	6.3	HS-0308-5	0	20	D	Plate No. 2	6BJ8	6.3	EV-8709-0	27	80	A 2800	Triode Sect.
6AY3†	6.3	EV-0209-0	0	87	D	USE ADAPTER SA-4, 105B-144, NOTE 3	6BJ8	6.3	EV-0603-0	0	78	C	Diode No. 1
Model 6000 A:	No Adapter Required.						6BJ8	6.3	EV-0102-0	0	78	C	Diode No. 2
6AY11†	6.3	B3-8709-0	20	22	A 660	Triode No. 1	6BK4	6.3	HS-0501-X	0	45	C	
6AY11	6.3	B3-5604-0	20	22	A 660	Triode No. 2	6BK7	6.3	EV-7608-9	20	85	A 4000	Triode No. 1
6AY11	6.3	B3-0X0A-0	0	77	C	Diode No. 1	6BK7	6.3	EV-2103-9	20	85	A 4000	Triode No. 2
6AY11	6.3	B3-0302-0	0	77	C	Diode No. 2	6BK11†	6.3	B3-9X04-0	20	39	A 850	Triode No. 1
6AZ8	6.3	EV-6123-0	11	81	A 3000	Pent. Sect.	6BK11	6.3	B3-7506-0	19	7	A 550	Triode No. 2
6AZ8	6.3	EV-9807-0	24	83	A 3300	Triode Sect.	6BK11	6.3	B3-A203-0	19	7	A 550	Triode No. 3
6B10†	6.3	B3-5607-0	24	78	A 2500	Triode No. 1	6BL7	6.3	HY-4506-0	24	88	A 5000	Triode No. 1
6B10	6.3	B3-3402-0	24	78	A 2500	Triode No. 2	6BL7	6.3	HY-1203-0	24	88	A 5000	Triode No. 2
6B10	6.3	B3-0X09-0	0	78	C	Diode No. 1	6BL8	6.3	EV-2637-1	12	81	A 3000	Pent. Sect.
6B10	6.3	B3-0809-0	0	78	C	Diode No. 2	6BL8	6.3	EV-9108-6	26	85	A 4000	Triode Sect.
6BA3†	6.3	EV-0209-0	0	84	D	USE ADAPTER SA-4, 105B-144, NOTE 3	6BM8	6.3	EV-3672-0	24	86	A 4300	Pent. Sect.
Model 6000 A:	No Adapter Required.						6BM8	6.3	EV-1908-0	11	71	A 1900	Triode Sect.
6BA5	6.3	DW-1578-0	19	75	A 2150		6BN4	6.3	ET-2501-0	19	88	A 5000	
6BA6	6.3	ET-1567-2	11	72	A 1900		6BN4A	6.3	ET-2501-0	19	86	A 3200	
6BA7	6.3	EV-7913-2	0	31	B 750	Ampl. Sect.	6BN6	6.3	ET-2751-6	6	27	B 700	Limiter Grid
6BA7	6.3	EV-2103-7	16	88	A 5000	Osc. Sect.	6BN6	6.3	ET-6751-2	13	0	B 500	Quadrature Grid

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS	TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS	
6DA4	6.3	HY-0503-0	0	86	D		6EA7	6.3	JX-4506-0	11	65	A	1500	Triode No. 1
6DA5	6.3	EV-19X2-0	Vary	100	F	Connect a 1 megohm resistor from cap lead to Loctal Test Socket Pin No. 7.	6EA7	6.3	JX-1203-0	51	90	A	6500	Triode No. 2
						Vary Bias to vary beam angle.	6EA8	6.3	EV-2637-0	11	79	A	2600	Pent. Sect.
6DB5	6.3	EV-3912-0	11	91	B	7500	6EA8	6.3	EV-9108-0	11	89	A	5000	Triode Sect.
6DC6	6.3	ET-1562-7	10	84	A	3500	6EB5	6.3	ET-0205-6	0	71	C		Diode No. 1
6DE4	6.3	HY-0503-0	0	89	D		6EB5	6.3	ET-0701-6	0	71	C		Diode No. 2
6DE6	6.3	ET-1562-7	11	81	A	3000	6EB8	6.3	EV-7986-0	11	87	A	5100	Pent. Sect.
6DE7	6.3	EV-7608-0	27	73	A	2000	6EB8	6.3	EV-2301-0	11	70	A	2000	Triode Sect.
6DE7	6.3	EV-2109-0	54	89	A	6500	6EF4‡	6.3	B3-06X5-9	0	45	C		
6DG6	6.3	HS-5348-0	11	91	B	7500	6EH4‡	6.3	B3-0605-X	0	45	C		
6DJ8	6.3	EV-7608-0	22	91	A	7000	6EH5	6.3	ET-2761-0	13	88	A	10000	
6DJ8	6.3	EV-2103-0	22	91	A	7000	6EH7	6.3	EV-2781-9	15	87	A	3300	
6DK3	6.3	EV-020X-0	0	86	C		6EH8	6.3	EV-7986-0	15	75	A	2300	Pent. Sect.
6DK6	6.3	ET-1562-7	12	83	A	3300	6EH8	6.3	EV-2301-0	20	87	A	4600	Triode Sect.
6DL3‡	6.3	EV-070X-0	0	86	C		6EJ4‡	6.3	B3-9605-X	0	45	C		
Model 6000 A:	No Adapter Required.						6EJ7	6.3	EV-2781-9	10	87	A	4000	
6DM4	6.3	HY-0503-0	0	89	D		6EL4	6.3	HS-0501-X	0	45	C		
6DN3‡	6.3	EV-0709-0	0	86	C		6EM5	6.3	EV-3917-0	12	89	A	4300	
Model 6000 A:	No Adapter Required.						6EM7	6.3	HY-4506-0	10	66	A	1500	Triode No. 1
6DN7	6.3	HY-4506-0	24	73	A	2000	6EM7	6.3	HY-1203-0	53	91	A	5250	Triode No. 2
6DN7	6.3	HY-1203-0	20	91	A	7500	6EN4	6.3	HS-0501-X	0	45	C		
6DQ3‡	6.3	B3-0407-0	0	86	C		6EQ7	6.3	EV-2763-1	17	60	A	2400	Pent. Sect.
6DQ4	6.3	JX-0503-0	0	86	D		6EQ7	6.3	EV-0803-0	0	26	C		Diode Sect.
6DQ5	6.3	HS-1X43-0	43	92	A	7800	6ER5	6.3	ET-2567-0	10	89	A	5000	
6DQ6	6.3	HS-5X48-0	25	90	B	6000	6ES5	6.3	ET-2501-0	10	87	A	4600	
6DR4	6.3	ET-6507-0	12	58	A	1250	6ES8	6.3	EV-7608-0	22	92	A	7500	Triode No. 1
6DR7	6.3	EV-7608-0	17	36	A	800	6ES8	6.3	EV-2103-0	22	92	A	7500	Triode No. 2
6DR7	6.3	EV-2109-0	56	88	A	3600	6ET7	6.3	EV-7986-0	10	89	A	4750	Pent. Sect.
6DS4‡	6.3	DR-4208-0	22	79	A	2600	6ET7	6.3	EV-0301-0	0	21	C		Diode No. 1
Model 6000 A:	No Adapter Required.						6ET7	6.3	EV-0201-0	0	21	C		Diode No. 2
6DS4	6.3	13-4208-0	22	79	A	2600	6EU7	6.3	BS-8709-0	12	58	A	1250	Triode No. 1
6DS5	6.3	ET-1562-0	13	87	A	4800	6EU7	6.3	BS-5604-0	12	58	A	1250	Triode No. 2
6DT3‡	6.3	B3-0407-0	0	86	C		6EU8	6.3	EV-7198-0	11	79	A	2600	Pent. Sect.
6DT4	6.3	HY-0503-0	0	92	D		6EU8	6.3	EV-2306-0	11	89	A	5000	Triode Sect.
6DT5	6.3	EV-3917-0	21	87	A	4400	6EV5	6.3	ET-1562-0	19	86	A	4000	
6DT6	6.3	ET-1562-7	23	15	A	600	6EV7	6.3	EV-7608-0	10	84	A	3600	Triode No. 1
6DT6	6.3	ET-7562-1	16	0	B	500	6EV7	6.3	EV-2103-0	10	84	A	3600	Triode No. 2
6DT8	6.3	EV-7608-9	11	81	A	3000	6EW6	6.3	ET-1562-7	11	84	A	3700	
6DT8	6.3	EV-2103-9	11	81	A	3000	6EW7	6.3	EV-7608-0	27	72	A	2000	Triode No. 1
6DV4‡	6.3	13-6107-0	27	88	A	4600	6EW7	6.3	EV-2109-0	54	88	A	6000	Triode No. 2
6DW4‡	6.3	EV-0209-0	0	89	D		6EX6	6.3	HS-5X83-0	48	91	A	7500	
Model 6000 A:	No Adapter Required.							Tubes indicating shorts: Re-test using HS-5X13-0						
6DX8	6.3	EV-8697-0	10	90	A	6000	6EY6	6.3	HS-5348-0	28	87	A	4400	
6DX8	6.3	EV-1203-0	18	73	A	2100	6EZ5	6.3	HS-5348-0	51	71	A	1800	
6DZ4	6.3	ET-2105-0	35	87	A	4000	6EZ8	6.3	EV-9800-0	28	78	A	2500	Triode No. 1
6DZ8	6.3	EV-3672-0	23	88	A	5500	6EZ8	6.3	EV-7600-0	28	78	A	2500	Triode No. 2
6DZ8	6.3	EV-1908-0	19	39	A	850	6EZ8	6.3	EV-2301-0	18	78	A	2500	Triode No. 3
6EA4‡	6.3	B3-0605-X	0	45	C			If no reading is obtained, use selector setting FU- in place of EV-						
6EA5	6.3	ET-1562-0	11	86	A	4000	6FA7	6.3	EV-7986-1	10	58	A	1250	Tetrode No. 1
							6FA7	6.3	EV-7186-9	10	58	A	1250	Tetrode No. 2
							6FA7	6.3	EV-9306-1	0	26	C		Diode Sect.
							6FD6	6.3	ET-1657-2	18	45	C		

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS	TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS	
6DA4	6.3	HY-0503-0	0	86	D	---	6EA7	6.3	JX-4506-0	11	65	A	1500	Triode No. 1
{ 6DA5	6.3	EV-19X2-0	Vary	100	F	---	6EA7	6.3	JX-1203-0	51	90	A	6500	Triode No. 2
megohm resistor from cap lead to Loctal Test Socket Pin No. 7.							6EA8	6.3	EV-2637-0	11	79	A	2600	Pent. Sect.
Vary Bias to vary beam angle.							6EA8	6.3	EV-9108-0	11	89	A	5000	Triode Sect.
6DB5	6.3	EV-3912-0	11	91	B	7500	6EB5	6.3	ET-0205-6	0	71	C	---	Diode No. 1
6DC6	6.3	ET-1562-7	10	84	A	3500	6EB5	6.3	ET-0701-6	0	71	C	---	Diode No. 2
6DE4	6.3	HY-0503-0	0	89	D	---	6EB8	6.3	EV-7986-0	11	87	A	5100	Pent. Sect.
6DE6	6.3	ET-1562-7	11	81	A	3000	6EB8	6.3	EV-2301-0	11	70	A	2000	Triode Sect.
{ 6DE7	6.3	EV-7608-0	27	73	A	2000	6EF4†	6.3	B3-06X5-9	0	45	C	---	---
{ 6DE7	6.3	EV-2109-0	54	89	A	6500	6EH4†	6.3	B3-0605-X	0	45	C	---	---
6DG6	6.3	HS-5348-0	11	91	B	7500	6EH5	6.3	ET-2761-0	13	88	A	10000	---
{ 6DJ8	6.3	EV-7608-0	22	91	A	7000	6EH7	6.3	EV-2781-9	15	87	A	3300	---
{ 6DJ8	6.3	EV-2103-0	22	91	A	7000	{ 6EH8	6.3	EV-7986-0	15	75	A	2300	Pent. Sect.
6DK3	6.3	EV-020X-0	0	86	C	---	{ 6EH8	6.3	EV-2301-0	20	87	A	4600	Triode Sect.
6DK6	6.3	ET-1562-7	12	83	A	3300	6EJ4†	6.3	B3-9605-X	0	45	C	---	---
{ 6DL3†	6.3	EV-070X-0	0	86	C	---	6EJ7	6.3	EV-2781-9	10	87	A	4000	---
Model 6000 A: No Adapter Required.							6EL4	6.3	HS-0501-X	0	45	C	---	---
6DM4	6.3	HY-0503-0	0	89	D	---	6EM5	6.3	EV-3917-0	12	89	A	4300	---
{ 6DN3†	6.3	EV-0709-0	0	86	C	---	{ 6EM7	6.3	HY-4506-0	10	66	A	1500	Triode No. 1
Model 6000 A: No Adapter Required.							{ 6EM7	6.3	HY-1203-0	53	91	A	5250	Triode No. 2
6DN7	6.3	HY-4506-0	24	73	A	2000	6EN4	6.3	HS-0501-X	0	45	C	---	---
{ 6DN7	6.3	HY-1203-0	20	91	A	7500	{ 6EO7	6.3	EV-2763-1	17	60	A	2400	Pent. Sect.
6DQ3†	6.3	B3-0407-0	0	86	C	---	{ 6EO7	6.3	EV-0803-0	0	26	C	---	Diode Sect.
6DQ4	6.3	JX-0503-0	0	86	D	---	6ER5	6.3	ET-2567-0	10	89	A	5000	---
6DQ5	6.3	HS-1X43-0	43	92	A	7800	6ES5	6.3	ET-2501-0	10	87	A	4600	---
6DQ6	6.3	HS-5X48-0	25	90	B	6000	{ 6ES8	6.3	EV-7608-0	22	92	A	7500	Triode No. 1
6DR4	6.3	ET-6507-0	12	58	A	1250	{ 6ES8	6.3	EV-2103-0	22	92	A	7500	Triode No. 2
{ 6DR7	6.3	EV-7608-0	17	36	A	800	6ET7	6.3	EV-7986-0	10	89	A	4750	Pent. Sect.
{ 6DR7	6.3	EV-2109-0	56	88	A	3600	6ET7	6.3	EV-0301-0	0	21	C	---	Diode No. 1
{ 6DS4†	6.3	DR-4208-0	22	79	A	2600	6ET7	6.3	EV-0201-0	0	21	C	---	Diode No. 2
Model 6000 A:							{ 6EU7	6.3	BS-8709-0	12	58	A	1250	Triode No. 1
6DS4	6.3	13-4208-0	22	79	A	2600	{ 6EU7	6.3	BS-5604-0	12	58	A	1250	Triode No. 2
6DS5	6.3	ET-1562-0	13	87	A	4800	6EU8	6.3	EV-7198-0	11	79	A	2600	Pent. Sect.
6DT3†	6.3	B3-0407-0	0	86	C	---	6EU8	6.3	EV-2306-0	11	89	A	5000	Triode Sect.
6DT4	6.3	HY-0503-0	0	92	D	---	6EV5	6.3	ET-1562-0	19	86	A	4000	---
6DT5	6.3	EV-3917-0	21	87	A	4400	{ 6EV7	6.3	EV-7608-0	10	84	A	3600	Triode No. 1
{ 6DT6	6.3	ET-1562-7	23	15	A	600	{ 6EV7	6.3	EV-2103-0	10	84	A	3600	Triode No. 2
{ 6DT6	6.3	ET-7562-1	16	0	B	500	6EW6	6.3	ET-1562-7	11	84	A	3700	---
{ 6DT8	6.3	EV-7608-9	11	81	A	3000	{ 6EW7	6.3	EV-7608-0	27	72	A	2000	Triode No. 1
{ 6DT8	6.3	EV-2103-9	11	81	A	3000	{ 6EW7	6.3	EV-2109-0	54	88	A	6000	Triode No. 2
6DV4†	6.3	13-6107-0	27	88	A	4600	6EX6	6.3	HS-5X83-0	48	91	A	7500	---
{ 6DW4†	6.3	EV-0209-0	0	89	D	---	Tubes indicating shorts: Re-test using HS-6X13-0							
Model 6000 A: No Adapter Required.							6EY6	6.3	HS-5348-0	28	87	A	4400	---
{ 6DX8	6.3	EV-8697-0	10	90	A	6000	6EZ5	6.3	HS-5348-0	51	71	A	1800	---
{ 6DX8	6.3	EV-1203-0	18	73	A	2100	{ 6EZ8	6.3	EV-9800-0	28	78	A	2500	Triode No. 1
6DZ4	6.3	ET-2105-0	35	87	A	4000	{ 6EZ8	6.3	EV-7600-0	28	78	A	2500	Triode No. 2
{ 6DZ8	6.3	EV-3672-0	23	88	A	5500	{ 6EZ8	6.3	EV-2301-0	18	78	A	2500	Triode No. 3
{ 6DZ8	6.3	EV-1908-0	19	39	A	850	If no reading is obtained, use selector setting FU- in place of EV-.							
6EA4†	6.3	B3-0605-X	0	45	C	---	6FA7	6.3	EV-7986-1	10	58	A	1250	Tetrode No. 1
6EA5	6.3	ET-1562-0	11	86	A	4000	6FA7	6.3	EV-7186-9	10	58	A	1250	Tetrode No. 2
							6FA7	6.3	EV-9306-1	0	26	C	---	Diode Sect.
							6FD6	6.3	ET-1657-2	18	45	C	---	OK ABOVE DIODES OK

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS	TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS
{6FD7	6.3	EV-7608-0	10	68	A 1600	Triode No. 1	{6GJ7	6.3	EV-2671-0	11	86	A 3500	Pent. Sect.
{6FO7	6.3	EV-2109-0	58	89	A 4500	Triode No. 2	{6GJ7	6.3	EV-9803-0	30	90	A 4250	Triode Sect.
6FE6	6.3	HS-5348-0	30	92	A 8300		{6GJ8	6.3	EV-2637-0	10	83	A 3000	Pent. Sect.
6FG5	6.3	ET-1567-0	10	82	A 2500		{6GJ8	6.3	EV-9108-0	10	84	A 3200	Triode Sect.
{6FG7	6.3	EV-9678-0	10	82	A 3000	Pent. Sect.	6GK5	6.3	ET-2507-6	19	89	A 5200	
{6FG7	6.3	EV-1203-0	18	88	A 4750	Triode Sect.	6GK6	6.3	EV-2781-3	10	90	A 5750	
6FH5	6.3	ET-2507-0	14	87	A 4600		{6GL7	6.3	JX-4506-0	23	23	A 600	Triode No. 1
{6FH8	6.3	EV-6970-0	25	78	A 2500	TETRODE PLATE NO. 1	{6GL7	6.3	JX-1203-0	57	90	A 6400	Triode No. 2
6FH8	6.3	EV-6870-0	22	60	A 1300	TETRODE PLATE NO. 2	6GM5	6.3	EV-6917-0	10	89	A 5100	
{6FH8	6.3	EV-6170-0	22	60	A 1300	TETRODE PLATE NO. 3	6GM6	6.3	ET-1562-7	10	86	A 5000	
6FH8	6.3	EV-2300-0	23	90	A 5400	Triode Sect.	{6GN8	6.3	EV-7986-0	10	90	A 6000	Pent. Sect.
If no reading is obtained, use selector setting FU- in place of Ev-							{6GN8	6.3	EV-2301-0	16	60	A 1300	Triode Sect.
{6FJ7†	6.3	B3-XA09-0	20	78	A 2300	Triode No. 1	{6GQ7	6.3	EV-0809-0	0	80	C	Diode No. 1
{6FJ7	6.3	B3-3507-0	16	91	A 7000	Triode No. 2	{6GQ7	6.3	EV-0607-0	0	80	C	Diode No. 2
{6FM7†	6.3	B3-XA09-0	20	46	A 950	Triode No. 1	{6GQ7	6.3	EV-0201-0	0	80	C	Diode No. 3
{6FM7	6.3	B3-8507-0	62	88	A 5250	Triode No. 2	{6GT5†	6.3	EV-6973-0	28	91	B 6600	SEE ADAPTER SA-4, 1059-144, NOTE 3
{6FM8	6.3	EV-8907-0	11	56	A 1200	Triode Sect.	Model 6000 A: No Adapter Required.						
{6FM8	6.3	EV-0601-0	0	77	C	Diode No. 1	6GU5	6.3	ET-1562-0	13	89	A 5500	
{6FM8	6.3	EV-0203-0	0	77	C	Diode No. 2	{6GU7	6.3	EV-7608-0	30	75	A 2050	Triode No. 1
6FO5	6.3	ET-2507-0	19	87	A 4500		{6GU7	6.3	EV-2103-0	30	75	A 2050	Triode No. 2
6FO5A	6.3	ET-2507-6	19	89	A 5200		6GV5†	6.3	B3-92A4-0	42	86	A 4500	DO NOT USE TESTER CAP CONNECTOR. JUMPER CAP TO PIN 2 OF THE OCTAL SOCKET
{6FO7	6.3	EV-7608-0	23	79	A 2600	Triode No. 1	6GW6	6.3	HS-5X48-0	28	91	B 6800	
{6FO7	6.3	EV-2103-0	23	79	A 2600	Triode No. 2	{6GW8	6.3	EV-8637-0	10	89	A 5500	Pent. Sect.
6FS5	6.3	ET-1567-0	10	85	A 3500		{6GW8	6.3	EV-1902-0	10	45	A 950	Triode Sect.
6FV6	6.3	ET-1567-2	12	85	A 3800		6GX6	6.3	ET-1562-7	12	67	A 1600	
{6FV8	6.3	EV-9678-0	10	80	A 2750	Pent. Sect.	{6GX7	6.3	EV-2671-0	11	84	A 3200	Pent. Sect.
{6FV8	6.3	EV-1203-0	15	89	A 5500	Triode Sect.	{6GX7	6.3	EV-9801-0	18	89	A 4800	Triode Sect.
6FW5	6.3	HS-1583-0	48	90	A 6200		6GY5†	6.3	B3-527X-0	30	92	B 9000	DO NOT USE TESTER CAP CONNECTOR. JUMPER CAP TO PIN 2 OF THE OCTAL SOCKET.
{6FY7†	6.3	B3-XA09-0	20	32	A 800	Triode No. 1	6GY6	6.3	ET-1562-7	14	61	A 1350	
{6FY7	6.3	B3-3507-0	54	92	A 6500	Triode No. 2	{6GY8	6.3	EV-0607-0	0	79	C	Triode No. 1
{6FY8	6.3	EV-3672-0	22	89	A 5700	Pent. Sect.	{6GY8	6.3	FU-3908-0	20	75	A 2250	Triode No. 2
{6FY8	6.3	EV-1908-0	21	62	A 1400	Triode Sect.	{6GY8	6.3	FU-1200-0	29	75	A 2250	Triode No. 3
{6G11†	6.3	B3-8AX9-0	19	89	A 5500	Pent. No. 1	6GZ5	6.3	ET-2761-0	20	86	A 4000	
6G11	6.3	B3-3672-4	10	8	A 700	Pent. No. 2	6HA5	6.3	ET-1507-6	20	87	A 4600	
{6GA7†	6.3	B3-4735-0	58	89	A 4500	Pent. Sect.	6HA6	6.3	EV-2761-3	10	90	A 6500	
6GA7	6.3	B3-0A08-0	0	85	D	Diode Sect.	6HB5†	6.3	B3-A72X-0	57	89	A 5600	
6GB5	6.3	EV-2X78-0	64	89	A 5000	SEE ADAPTER SA-4, 1059-144	6HB6	6.3	EV-2781-9	10	92	A 7500	
6GC5	6.3	EV-6917-0	11	91	B 7500		{6HB7	6.3	EV-2671-0	10	79	A 3100	Pent. Sect.
6GE5†	6.3	B3-A72X-0	48	90	A 6000		{6HB7	6.3	EV-9801-0	11	89	A 4500	Triode Sect.
{6GE8	6.3	EV-8917-0	14	72	A 1850	Pent. Sect.	6H-B25	6.3	EV-2X79-8	50	87	A 4500	USE ADAPTER SA-4, 1059-144
{6GE8	6.3	EV-3602-0	64	86	A 4700	Triode Sect.	{6HC8	6.3	EV-3672-0	15	88	A 5100	Pent. Sect.
6GF5†	6.3	B3-A72X-0	54	88	A 4800		{6HC8	6.3	EV-1908-0	9	73	A 2000	Triode Sect.
{6GF7†	6.3	EV-9801-0	19	35	A 700	TRIODE NO. 1 USE ADAPTER SA-4, 1059-144, NOTE 3	6HD5†	6.3	B3-A79X-0	54	89	A 6000	
6GF7	6.3	EV-2603-0	63	86	A 4200	Triode No. 2	{6HD7	6.3	EV-2671-0	10	79	A 2800	Pent. Sect.
Model 6000 A: No Adapter Required.							{6HD7	6.3	EV-9803-0	15	90	A 7000	Triode Sect.
{6GH8	6.3	EV-2637-0	11	82	A 3000	Pent. Sect.	6HE5†	6.3	B3-96XA-0	23	87	A 4500	
{6GH8	6.3	EV-9108-0	21	85	A 3900	Triode Sect.	{6HE7†	6.3	B3-95A8-0	54	91	A 7000	Pent. Sect.
{6GJ5†	6.3	EV-6X73-0	28	91	B 6600	USE ADAPTER SA-4, 1059-144, NOTE 3	Model 6000 A: No Adapter Required.						
Model 6000 A: No Adapter Required.							{6HE7	6.3	B3-0204-0	0	86	C	Diode Sect.

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS	TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS
6HF5†	6.3	B3-92A4-0	75	88	A 4300	DO NOT USE TESTER CAP CONNECTOR. JUMPER CAP TO PIN 2 OF THE OCTAL SOCKET.	6JC6	6.3	EV-2781-9	11	88	A 5000	
{6HF8	6.3	EV-7986-0	10	88	A 4800	Pent. Sect.	{6JC8	6.3	EV-2637-0	10	82	A 3000	Pent. Sect.
{6HF8	6.3	EV-2301-0	20	69	A 1700	Triode Sect.	{6JC8	6.3	EV-8901-0	10	89	A 5000	Triode Sect.
6HG5	6.3	ET-1562-0	11	86	A 4100		6JD5†	6.3	B3-2704-3	0	88	A 4500	
{6HG8	6.3	EV-2893-0	10	84	A 3600	Pent. Sect.	6JD6	6.3	EV-2781-9	10	83	A 3200	
{6HG8	6.3	EV-6703-0	32	82	A 3200	Triode Sect.	{6JE6†	6.3	EV-2X73-8	39	92	B 8100	USE ADAPTER SA-4, 1000-144, NOTE 3
6HJ5†	6.3	B3-A792-X	54	90	A 6500		Model 6000 A:	No Adapter Required.					
{6HJ7	6.3	EV-2671-0	10	89	A 4000	Pent. Sect.	{6JE8	6.3	EV-7986-0	11	89	A 5000	Pent. Sect.
{6HJ7	6.3	EV-9803-0	20	91	A 4500	Triode Sect.	{6JE8	6.3	EV-2301-0	12	75	A 2200	Triode Sect.
{6HJ8	6.3	EV-2631-9	10	85	A 3500	Pent. Sect.	{6JF6†	6.3	EV-2X73-8	32	92	B 7800	USE ADAPTER SA-4, 1000-144, NOTE 3
{6HJ8	6.3	EV-0807-0	0	79	C	Diode Sect.	Model 6000 A:	No Adapter Required.					
6HK5	6.3	ET-1502-0	19	88	A 5000		{6JF8	6.3	HR-5X46-0	25	90	B 6050	Pent. Sect.
6HL5	6.3	EV-2793-0	15	93	A 9500		{6JFB	6.3	HR-0802-0	0	85	D	Diode Sect.
{6HL8	6.3	EV-2637-0	10	87	A 4400	Pent. Sect.	6JG5	6.3	EV-7986-0	10	90	A 6000	
{6HL8	6.3	EV-9108-0	18	87	A 4400	Triode Sect.	{6JG6†	6.3	EV-2973-6	32	92	B 7800	USE ADAPTER SA-4, 1000-144, NOTE 3
6HM5	6.3	ET-1507-6	20	87	A 4600		Model 6000 A:	No Adapter Required.					
6HM6	6.3	EV-2781-9	11	87	A 4700		6JH5†	6.3	B3-2704-3	0	88	A 4500	
6HO5	6.3	ET-1507-6	20	87	A 4400		6JH6	6.3	ET-1562-7	11	84	A 3700	
6HR5	6.3	ET-1562-0	10	87	A 4500		{6JH8	6.3	EV-6937-1	23	57	A 1200	PLATE NO. 1. DISREGARD NEON FLASH IN SHORT TESTING.
6HR6	6.3	ET-1567-2	10	84	A 3600		{6JH8	6.3	EV-6837-1	23	57	A 1200	PLATE NO. 2. DISREGARD NEON FLASH IN SHORT TESTING.
6HS5†	6.3	B3-2704-3	0	88	A 4500		6JK5†	6.3	B3-2704-3	0	88	A 4500	
6HS6	6.3	ET-1567-2	14	82	A 3200		6JK6	6.3	ET-1562-7	10	86	A 4800	
{6HS8	6.3	EV-7821-9	10	15	A 600	Pent. No. 1	{6JK8	6.3	EV-7608-9	23	78	A 2000	Triode No. 1
{6HS8	6.3	EV-7321-6	10	15	A 600	Pent. No. 2	6JK8	6.3	EV-2103-9	20	89	A 5000	Triode No. 2
6HT6	6.3	EV-2781-9	10	87	A 4600		6JL6	6.3	ET-1562-7	16	85	A 4200	
6HV5†	6.3	B3-7204-3	0	82	C		{6JL8	6.3	EV-7986-0	10	88	A 5200	Pent. Sect.
{6HW8	6.3	EV-6X37-9	13	72	A 1900		{6JL8	6.3	EV-2301-0	17	81	A 2900	Triode Sect.
Make external connection from Pin 2 and 8 of octal socket to plate cap lead. Connect Pin 1 to Pin 7 in octal socket.							6JM6†	6.3	B3-5632-4	43	88	A 7000	CONNECT JUMPER FROM TUBE CAP TO PIN NO. 6 ON OCTAL SOCKET.
6HZ5†	6.3	B3-2704-3	0	88	A 4500		6JN6†	6.3	B3-A732-4	43	88	A 7000	
6HZ6	6.3	ET-1562-7	10	65	A 1400		{6JN8	6.3	EV-9578-0	10	82	A 3200	Pent. Sect.
{6HZ8	6.3	EV-7986-0	16	88	A 5000	Pent. Sect.	{6JN8	6.3	EV-1203-0	17	89	A 5500	Triode Sect.
{6HZ8	6.3	EV-2301-0	18	76	A 2300	Triode Sect.	{6JO6	6.3	EV-7139-6	50	85	A 3800	Pent. Sect.
6J4	6.3	ET-1702-0	20	90	A 6000		{6JO6	6.3	EV-0609-0	0	70	C	Diode Sect.
{6J6	6.3	ET-5207-0	21	81	A 3000	Triode No. 1	{6JR6†	6.3	EV-2913-6	65	85	A 4200	USE ADAPTER SA-4, 1000-144, NOTE 3
{6J6	6.3	ET-6107-0	21	81	A 3000	Triode No. 2	Model 6000A:	No adapter required.					
{6J9†	6.3	EV-780X-0	17	81	A 3000	Triode No. 1	6JS6A†	6.3	B3-5632-4	53	88	A 4300	CONNECT JUMPER FROM TUBE CAP TO PIN NO. 6 ON OCTAL SOCKET. USE ADAPTER SA-4, 1000-144, NOTE 3
{6J9	6.3	EV-960X-0	17	81	A 3000	Triode No. 2	{6JT6†	6.3	EV-2973-6	44	91	A 7000	
{6J9	6.3	EV-2103-0	17	81	A 3000	Triode No. 3	Model 6000 A:	No Adapter Required.					
{6J10†	6.3	B3-7468-5	6	27	B 700	Pent. No. 1	{6JT8	6.3	EV-7986-0	12	90	A 6000	Pent. Sect.
{6J10	6.3	B3-A923-0	16	88	A 4350	Pent. No. 2	{6JT8	6.3	EV-2301-0	18	46	A 950	Triode Sect.
{6J11†	6.3	B3-A978-X	10	86	A 4000	Pent. No. 1	{6JU6†	6.3	EV-2X13-8	72	85	A 4200	USE ADAPTER SA-4, 1000-144, NOTE 3
{6J11	6.3	B3-5326-4	10	86	A 4000	Pent. No. 2	Model 6000 A:	No Adapter Required.					
6JA5†	6.3	B3-9634-0	55	88	A 5400		6JU8	6.3	EV-0809-0	0	78	C	Diode No. 1
6JB5†	6.3	B3-96XA-0	51	71	A 1800		6JU8	6.3	EV-0708-0	0	78	C	Diode No. 2
{6JB6†	6.3	EV-2X13-8	28	91	B 6600	USE ADAPTER SA-4, 1000-144, NOTE 3	6JU8	6.3	EV-0203-0	0	78	C	Diode No. 3
Model 6000 A:	No Adapter Required.						{6JU8	6.3	EV-0102-0	0	78	C	Diode No. 4
{6JB8	6.3	EV-2637-0	25	45	A 1000	Pent. Sect.							
{6JB8	6.3	EV-9108-0	19	77	A 2400	Triode Sect.							
6JC5†	6.3	B3-96XA-0	23	87	A 4500								

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS	TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS
6LU8†	6.3	B3-6489-0	40	87	A 4000	Pent. Sect.	6MV8	6.3	EV-7986-0	10	86	A 4600	Pent. Sect.
6LU8	6.3	B3-X20A-0	24	62	A 1400	Triode Sect.	6MV8	6.3	EV-2301-0	15	73	A 2200	Triode Sect.
6LV6†	6.3	B3-5632-4	69	85	A 4350	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET	6MY8†	6.3	B3-6489-0	40	87	A 4000	Pent. Sect.
6LW6	6.3	HY-5X32-0	75	88	A 5500		6MY8	6.3	B3-X20A-0	24	62	A 1400	Triode Sect.
6LX6†	6.3	B3-5632-4	70	90	A 7500	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET	6Q11†	6.3	B3-9X04-8	24	75	A 2200	Triode No. 1
6LY8	6.3	EV-7986-0	22	85	A 3400	Pent. Sect.	6Q11	6.3	B3-7506-8	12	58	A 1250	Triode No. 2
6LY8	6.3	EV-2301-0	17	48	A 1100	Triode Sect.	6Q11	6.3	B3-A203-8	12	58	A 1250	Triode No. 3
6LZ6†	6.3	EV-5X73-8	75	88	A 4500	USE ADAPTER SA-4, 1850-144, NOTE 3	6R4	6.3	EV-1803-0	24	85	A 4000	
Model 6000A: No Adapter Required.							6S4	6.3	EV-6902-0	22	86	A 4150	
6M3	6.3	JS-030X-0	0	91	D		6SN7	6.3	HY-4506-0	23	79	A 2600	Triode No. 1
6M11†	6.3	B3-2A3X-0	11	86	A 3750	Pent. Sect.	6SN7	6.3	HY-1203-0	23	79	A 2600	Triode No. 2
6M11	6.3	B3-8709-0	20	82	A 3000	Triode No. 1	6T4	6.3	ET-2105-0	36	88	A 5000	
6M11	6.3	B3-5604-0	20	82	A 3000	Triode No. 2	6T8	6.3	EV-8907-0	11	56	A 1200	Triode Sect.
6MA6	6.3	DY-4607-X	0	45	C		6T8	6.3	EV-0607-0	0	77	C	Diode No. 1
6MB6†	6.3	B3-5632-4	70	90	A 7500	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET	6T8	6.3	EV-0203-0	0	77	C	Diode No. 2
6MB8	6.3	EV-9678-0	8	84	A 4000	Pent. Sect.	6T8	6.3	EV-0107-0	0	77	C	Diode No. 3
6MB8	6.3	EV-1203-0	13	88	A 4800	Triode Sect.	6T9†	6.3	B3-8AX9-0	15	87	A 4500	Pent. Sect.
6MC6†	6.3	EV-2X73-8	70	90	A 7500	USE ADAPTER SA-4, 1850-144, NOTE 3	6T9	6.3	B3-4205-0	19	36	A 950	Triode Sect.
Model 6000A: No Adapter Required.							6T10†	6.3	B3-8AX9-0	19	88	A 4500	Pent. No. 1
6MD8†	6.3	EV-6307-0	20	85	A 3500	TRIODE NO. 1 USE ADAPTER SA-4, 1850-144, NOTE 3	6T10	6.3	B3-3762-5	14	21	B 625	Pent. No. 2
6MD8	6.3	EV-8207-0	20	85	A 3500	Triode No. 2	6U8	6.3	EV-2637-0	11	73	A 2000	Pent. Sect.
6MD8	6.3	EV-9107-0	20	86	A 3500	Triode No. 3	6U8	6.3	EV-9108-0	12	90	A 6200	Triode Sect.
Model 6000 A: No Adapter Required.							6U9†	6.3	FW-3782-4	10	83	A 3300	PENT. SECT. USE ADAPTER SA-11, 1850-177 MODEL 6000, 6005 NOTE 3
6ME6†	6.3	EV-2X73-8	39	92	B 8100	USE ADAPTER SA-4, 1850-144, NOTE 3	6U9	6.3	FW-X901-0	29	81	A 3000	Triode Sect.
Model 6000A: No Adapter Required.							6U10†	6.3	B3-9X04-0	26	74	A 1900	Triode No. 1
6ME8	6.3	EV-6937-2	24	25	A 700	Plate No. 1	6U10	6.3	B3-7506-0	19	14	A 575	Triode No. 2
6ME8	6.3	EV-6837-2	24	25	A 700	Plate No. 2	6U10	6.3	B3-A203-0	26	74	A 1900	Triode No. 3
6MF8†	6.3	B3-7489-0	30	84	A 4000	Pent. Sect.	6V3	6.3	EV-020X-0	0	88	D	
6MF8	6.3	B3-X20A-0	23	66	A 1900	Triode Sect.	6V5	6.3	HY-5340-0	40	86	A 4100	
6MG8	6.3	EV-2637-0	10	81	A 3000	Pent. Sect.	6V6	6.3	HS-5348-1	13	86	A 4100	
6MG8	6.3	EV-9108-0	10	88	A 5000	Triode Sect.	6V9†	6.3	FW-3741-2	10	48	B 1000	HEPT. SECT. USE ADAPTER SA-11, 1850-177 MODEL 6000, 6005 NOTE 3
6MH6†	6.3	B3-5632-4	70	90	A 7500	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET, NOTE 3	6V9	6.3	FW-8X09-0	22	81	A 3000	Triode Sect.
Model 6000A: No Adapter Required.							6W4	6.3	HY-0503-0	0	88	D	
6MJ8†	6.3	B3-A203-0	27	78	A 2800	Triode No. 1	6W6	6.3	HS-5348-0	11	91	B 7500	
6MJ8	6.3	B3-X403-0	27	78	A 2800	Triode No. 2	6X4	6.3	ET-0607-1	0	40	D	Plate No. 1
6MJ8	6.3	B3-8603-0	27	78	A 2800	Triode No. 3	6X4	6.3	ET-0107-6	0	40	D	Plate No. 2
6MK8	6.3	EV-7821-9	11	30	F	Pent. No. 1	6X5	6.3	HS-0508-1	0	50	D	Plate No. 1
6MK8	6.3	EV-7321-6	11	30	F	Pent. No. 2	6X5	6.3	HS-0308-1	0	50	D	Plate No. 2
6ML8	6.3	EV-6307-0	20	84	A 4000	Triode No. 1	6X8	6.3	EV-7986-1	12	81	A 3000	Pent. Sect.
6ML8	6.3	EV-8207-0	20	84	A 4000	Triode No. 3	6X8	6.3	EV-2306-1	20	84	A 3500	Triode Sect.
6ML8	6.3	EV-9107-0	20	84	A 4000	Triode No. 3	6X9†	6.3	FW-3782-4	10	84	A 3600	PENT. SECT. USE ADAPTER SA-11, 1850-177 MODEL 6000, 6005 NOTE 3
6MN8†	6.3	B3-8603-0	25	68	A 1850	Triode No. 1	6X9	6.3	FW-X901-0	12	81	A 3000	Triode Sect.
6MN8	6.3	B3-X403-0	25	68	A 1850	Triode No. 2	6Y9†	6.3	FW-8X97-0	13	88	A 5000	PENT. NO. 1, USE ADAPTER SA-11, 1850-177 MODEL 6000, 6005 NOTE 3
6MN8	6.3	B3-A203-0	25	68	A 1850	Triode No. 3	6Y9	6.3	FW-1432-0	13	83	A 3300	Pent. No. 2
6MQ8	6.3	EV-2637-0	15	80	A 3000	Pent. Sect.	6Y10†	6.3	B3-8AX9-0	20	86	A 4000	Pent. No. 1
6MQ8	6.3	EV-9108-0	20	83	A 3300	Triode Sect.	6Y10	6.3	B3-3762-5	12	67	A 1600	Pent. No. 2
6MU8	6.3	EV-2637-0	19	86	A 4900	Pent. Sect.							
6MU8	6.3	EV-9108-0	25	73	A 2400	Triode Sect.							

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS	TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS	
6Z4	6.3	FR-0304-0	0	60	D	Plate No. 1	8B8	7.5	EV-8709-0	22	48	A	1000	Triode Sect.
6Z4	6.3	FR-0204-0	0	60	D	Plate No. 2	8B8	7.5	EV-0603-0	0	78	C	---	Diode No. 1
6Z10†	6.3	B3-7468-5	6	27	B	700	8B8	7.5	EV-0102-0	0	78	C	---	Diode No. 2
6Z10	6.3	B3-A923-0	16	88	A	4350	8BN11†	7.5	B3-7A98-X	10	85	A	3800	Pent. No. 1
7AU7	6.3	EV-7608-0	24	75	A	2200	8BN11	7.5	B3-3542-6	10	85	A	3800	Pent. No. 2
7AU7	6.3	EV-2103-0	24	75	A	2200	8BQ5	7.5	EV-2793-0	12	90	A	7500	
7DJ8	7.5	EV-7608-0	22	91	A	7000	8BQ11†	7.5	B3-X89A-7	5	85	A	4000	Pent. No. 1
7DJ8	7.5	EV-2103-0	22	91	A	7000	8BQ11	7.5	B3-5236-4	5	89	A	5000	Pent. No. 2
7ES8	7.5	EV-7608-0	22	92	A	7500	8BU11†	7.5	B3-8X9A-0	10	85	A	3800	Pent. Sect.
7ES8	7.5	EV-2103-0	22	92	A	7500	8BU11	7.5	B3-6705-0	15	89	A	5000	Triode No. 1
7EY6	7.5	HS-5348-0	28	87	A	4400	8BU11	7.5	B3-4302-0	15	89	A	5000	Triode No. 2
7FC7	7.5	EV-9608-0	24	90	A	5500	8CB11†	7.5	B3-X89A-7	10	85	A	3700	Pent. No. 1
7FC7	7.5	EV-2301-0	24	90	A	5500	8CB11	7.5	B3-5236-4	10	85	A	3700	Pent. No. 2
7HG8	7.5	EV-2893-0	10	84	A	3600	8CG7	7.5	EV-7608-9	23	79	A	2600	Triode No. 1
7HG8	7.5	EV-6703-0	32	82	A	3200	8CG7	7.5	EV-2103-9	23	79	A	2600	Triode No. 2
7KY6	7.5	EV-2781-3	17	88	A	5000	8CM7	7.5	EV-7603-0	27	73	A	2000	Triode No. 1
7KZ6	7.5	EV-2781-3	17	88	A	5000	8CM7	7.5	EV-8109-0	24	87	A	4400	Triode No. 2
8AC9†	7.5	B3-9AX8-7	10	87	A	4200	8CN7	7.5	EV-7806-0	11	56	A	1200	Triode Sect.
8AC9	7.5	B3-0304-0	0	85	C	---	8CN7	7.5	EV-0203-0	0	77	C	---	Diode No. 1
8AC9	7.5	B3-0203-0	0	85	C	---	8CN7	7.5	EV-0103-0	0	77	C	---	Diode No. 2
8AC10†	10.0	B3-9X04-0	10	80	A	3000	8CS7	7.5	EV-7608-0	22	75	A	2200	Triode No. 1
						TRIODE NO. 1. MAKE "LINE TEST" AT 1240 ON 2000 SCALE.	8CS7	7.5	EV-3109-0	27	87	A	4500	Triode No. 2
8AC10	10.0	B3-7506-0	10	80	A	3000	8CW5	7.5	EV-2793-0	40	89	A	5500	
8AC10	10.0	B3-A203-0	10	80	A	3000	8CX8	7.5	EV-7986-0	16	83	A	3300	Pent. Sect.
8AL9†	7.5	B3-A2X9-4	5	91	A	9000	8CX8	7.5	EV-2301-0	15	81	A	2900	Triode Sect.
8AL9	7.5	B3-5706-0	9	88	A	6300	8E88	7.5	EV-7986-0	11	87	A	5100	Pent. Sect.
8AR11†	7.5	B3-X89A-7	10	81	A	2700	8E88	7.5	EV-2301-0	11	70	A	2000	Triode Sect.
8AR11	7.5	B3-5236-4	10	81	A	2700	8EM6	7.5	EV-3917-0	12	89	A	4300	
8AU8	7.5	EV-7986-0	11	86	A	4200	8ET7	7.5	EV-7986-0	10	89	A	4750	Pent. Sect.
8AU8	7.5	EV-2301-0	15	86	A	4000	8ET7	7.5	EV-0301-0	0	21	C	---	Diode No. 1
8AV11†	7.5	B3-9X04-0	22	78	A	2500	8ET7	7.5	EV-0201-0	0	21	C	---	Diode No. 2
8AV11	7.5	B3-7506-0	22	78	A	2500	8FQ7	7.5	EV-7608-0	23	79	A	2600	Triode No. 1
8AV11	7.5	B3-A203-0	22	78	A	2500	8FQ7	7.5	EV-2103-0	23	79	A	2600	Triode No. 2
8AW8A	7.5	EV-7986-0	10	88	A	5000	8GK6	7.5	EV-2781-3	10	90	A	5750	
8AW8A	7.5	EV-2301-0	15	78	A	2500	8GN8	7.5	EV-7986-0	10	90	A	6000	Pent. Sect.
8B10†	7.5	B3-5607-0	28	75	A	2000	8GN8	7.5	EV-2301-0	16	60	A	1300	Triode Sect.
						TRIODE NO. 1. MAKE "LINE TEST" AT 1790 ON 2000 SCALE.	8GU7	7.5	EV-7608-0	30	75	A	2050	Triode No. 1
8B10	7.5	B3-3402-0	28	75	A	2000	8GU7	7.5	EV-2103-0	30	75	A	2050	Triode No. 2
8B10	7.5	B3-0X09-0	0	76	C	---	8GX7	7.5	EV-2671-0	11	84	A	3200	Pent. Sect.
8B10	7.5	B3-0809-0	0	76	C	---	8GX7	7.5	EV-9801-0	18	89	A	4800	Triode Sect.
8BA8A	7.5	EV-7986-0	11	88	A	6000	8JL8	7.5	EV-7986-0	10	88	A	5200	Pent. Sect.
8BA8A	7.5	EV-2301-0	30	79	A	2700	8JL8	7.5	EV-2301-0	17	81	A	2900	Triode Sect.
8BA11†	7.5	B3-4638-7	10	15	A	600	8JU8	7.5	EV-0809-0	0	78	C	---	Diode No. 1
8BA11	7.5	B3-4238-5	10	15	A	600	8JU8	7.5	EV-0708-0	0	78	C	---	Diode No. 2
8BA11	7.5	B3-9A0X-0	30	62	A	1600	8JU8	7.5	EV-0203-0	0	78	C	---	Diode No. 3
							8JU8	7.5	EV-0102-0	0	78	C	---	Diode No. 4
8BH8	7.5	EV-7986-0	7	88	A	5000	8JV8	7.5	EV-7986-0	7	89	A	3700	Pent. Sect.
8BH8	7.5	EV-2301-0	27	83	A	3000	8JV8	7.5	EV-2301-0	20	69	A	1680	Triode Sect.
8BM11†	7.5	B3-A79X-8	10	85	A	3700	8K11†	7.5	B3-9X04-8	24	75	A	2200	Triode No. 1
8BM11	7.5	B3-6235-4	13	84	A	3500	8K11	7.5	B3-7506-8	12	58	A	1250	Triode No. 2
							8K11	7.5	B3-A203-8	12	58	A	1250	Triode No. 3

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS	TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS
8KA8	7.5	EV-6983-7	16	70	A 1800	Pent. Sect.	9V9†	10.0	FW-3741-2	10	48	B 1000	HEPT. SECT. USE ADAPTER SA-11, 100-177, MODEL 600, 605 NOTE 3
8KA8	7.5	EV-2103-0	19	73	A 2000	Triode Sect.	9V9	10.0	FW-8X09-0	22	81	A 3000	Triode Sect.
8KR8	7.5	EV-7986-0	14	91	A 4750	Pent. Sect.	10AL11†	10.0	B3-8AX9-0	14	87	A 4300	Pent. No. 1
8KR8	7.5	EV-2301-0	17	91	A 3900	Triode Sect.	10AL11	10.0	B3-3672-4	20	21	A 620	Pent. No. 2
8LC8	7.5	EV-6987-3	16	70	A 1800	Pent. Sect.	10BQ5	10.0	EV-2793-0	12	90	A 7500	
8LC8	7.5	EV-2103-0	19	73	A 2000	Triode Sect.	10CW5	10.0	EV-2793-0	40	89	A 5500	
8LR8†	7.5	EV-2673-0	40	87	A 4000	PENT. SECT. USE ADAPTER SA-4, 100-144 NOTE 3	10DE7	10.0	EV-7608-0	27	73	A 2000	Triode No. 1
8LR8	7.5	EV-9801-0	24	62	A 1400	Triode Sect.	10DE7	10.0	EV-2109-0	54	89	A 6500	Triode No. 2
Model 6000A: No Adapter Required.							10DR7	10.0	EV-7608-0	17	36	A 800	Triode No. 1
8LT8	7.5	EV-9321-6	10	85	A 3700	Pent. Sect.	10DR7	10.0	EV-2109-0	56	88	A 3600	Triode No. 2
8LT8	7.5	EV-0607-0	0	92	D	Diode No. 1	10EQ7	10.0	HY-4506-0	30	73	A 2000	Triode No. 1
8LT8	7.5	EV-0807-0	0	92	D	Diode No. 2	10EG7	10.0	HY-1203-0	50	92	A 7500	Triode No. 2
8MU8	7.5	EV-2637-0	19	86	A 4900	Pent. Sect.	10EM7	10.0	HY-4506-0	10	66	A 1500	Triode No. 1
8MU8	7.5	EV-9108-0	25	73	A 2400	Triode Sect.	10EM7	10.0	HY-1203-0	53	91	A 5250	Triode No. 2
8U9†	7.5	FW-3782-4	10	83	A 3300	PENT. SECT. USE ADAPTER SA-11, 100-177, MODEL 600, 605 NOTE 3	10GF7†	10.0	EV-9801-0	19	35	A 700	TRIODE NO. 1 USE ADAPTER SA-4, 100-144, NOTE 3
8U9	7.5	FW-X901-0	29	81	A 3000	Triode Sect.	10GF7	10.0	EV-2603-0	63	86	A 4200	Triode No. 2
8X9†	7.5	FW-3782-4	10	84	A 3600	PENT. SECT. USE ADAPTER SA-11, 100-177, MODEL 600, 605 NOTE 3	Model 6000 A: No Adapter Required.						
8X9	7.5	FW-X901-0	12	81	A 3000	Triode Sect.	10GK6	10.0	EV-2781-3	10	90	A 5750	
9AH9†	10.0	B3-5A87-9	10	87	A 5200	Pent. Sect.	10GN8	10.0	EV-7986-0	10	90	A 6000	Pent. Sect.
9AH9	10.0	B3-2304-0	27	77	A 2350	Triode Sect.	10GN8	10.0	EV-2301-0	16	60	A 1300	Triode Sect.
9AK10†	10.0	B3-9X04-0	14	85	A 4500	Triode No. 1	10GV8	10.0	EV-9678-0	28	91	A 6500	Pent. Sect.
9AK10	10.0	B3-7506-0	14	85	A 4500	Triode No. 2	10GV8	10.0	EV-2103-0	22	78	A 2200	Triode Sect.
9AK10	10.0	B3-A203-0	14	85	A 4500	Triode No. 3	10HF8	10.0	EV-7986-0	10	88	A 4800	Pent. Sect.
9AU7	10.0	EV-7608-0	24	75	A 2200	Triode No. 1	10HF8	10.0	EV-2301-0	20	69	A 1700	Triode Sect.
9AU7	10.0	EV-2103-0	24	75	A 2200	Triode No. 2	10J10†	10.0	B3-7468-5	6	27	B 700	Pent. No. 1
9BJ11†	10.0	B3-A79X-8	10	66	A 1600	Pent. No. 1	10J10	10.0	B3-A923-0	16	88	A 4350	Pent. No. 2
9BJ11	10.0	B3-6235-4	13	84	A 3300	Pent. No. 2	10JA5†	10.0	B3-9634-0	55	88	A 5400	
9EA8	10.0	EV-2637-0	11	79	A 2600	Pent. Sect.	10JA8	10.0	EV-7986-0	11	89	A 5200	Tetrode Sect.
9EA8	10.0	EV-9108-0	11	89	A 5000	Triode Sect.	10JA8	10.0	EV-2301-0	22	71	A 1850	Triode Sect.
9GH8	10.0	EV-2637-0	11	82	A 3000	Pent. Sect.	10JT8	10.0	EV-7986-0	12	90	A 6000	Pent. Sect.
9GH8	10.0	EV-9108-0	21	85	A 3900	Triode Sect.	10JT8	10.0	EV-2301-0	18	46	A 950	Triode Sect.
9JW8	10.0	EV-2637-0	17	87	A 2200	Pent. Sect.	10JY8	10.0	EV-7986-0	18	86	A 4500	Pent. Sect.
9JW8	10.0	EV-9108-0	19	66	A 1600	Triode Sect.	10JY8	10.0	EV-2301-0	18	86	A 5000	Triode Sect.
9KC6	7.5	EV-2791-6	10	85	A 3800		10KR8	10.0	EV-7986-0	14	91	A 4750	Pent. Sect.
9KX6	7.5	EV-2781-3	12	89	A 5500		10KR8	10.0	EV-2301-0	17	91	B 3900	Triode Sect.
9KZ8	10.0	EV-2673-0	12	82	A 3200	Pent. Sect.	10KU8	10.0	EV-7986-0	14	90	A 5500	Pent. Sect.
9KZ8	10.0	EV-9108-0	22	84	A 3600	Triode Sect.	10KU8	10.0	EV-0301-0	0	26	C	Diode No. 1
9LA6	7.5	EV-2781-3	12	88	A 5000		10KU8	10.0	EV-0201-0	0	26	C	Diode No. 2
9ML8	10.0	EV-5307-0	20	84	A 4000	Triode No. 1	10LB8	10.0	EV-7986-0	14	89	A 5300	Pent. Sect.
9ML8	10.0	EV-8207-0	20	84	A 4000	Triode No. 2	10LB8	10.0	EV-2301-0	17	84	A 3600	Triode Sect.
9ML8	10.0	EV-9107-0	20	84	A 4000	Triode No. 3	10LD6	10.0	EV-2781-3	12	86	B 4600	
9MN8†	10.0	B3-8603-0	25	68	A 1850	Triode No. 1	10LE8	10.0	EV-9683-7	10	65	A 1500	Pent. No. 1
9MN8	10.0	B3-X403-0	25	68	A 1850	Triode No. 2	10LE8	10.0	EV-9183-2	10	65	A 1500	Pent. No. 2
9MN8	10.0	B3-A203-0	25	68	A 1850	Triode No. 3	10LW8	10.0	EV-7986-0	14	89	A 5000	Pent. Sect.
9R-AL1	10.0	EV-7608-0	33	58	A 1500	Triode No. 1	10LW8	10.0	EV-2301-0	22	59	A 1300	Triode Sect.
9R-AL1	10.0	EV-3109-0	35	79	A 3200	Triode No. 2	10LY8	10.0	EV-7986-0	22	85	A 3400	Pent. Sect.
							10LY8	10.0	EV-2301-0	17	48	A 1100	Triode Sect.
							10LZ8	10.0	EV-7986-0	14	87	A 4000	Pent. Sect.
							10LZ8	10.0	EV-2301-0	21	0	A 500	Triode Sect.

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS	TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS
10T10†	10.0	B3-8AX9-0	19	88	A 4500	Pent. No. 1	12AL11†	12.6	B3-8AX9-0	14	87	A 4300	Pent. No. 1
10T10	10.0	B3-3762-5	14	21	B 625	Pent. No. 2	12AL11†	12.6	B3-3762-4	20	21	A 620	Pent. No. 2
10Z10†	10.0	B3-7468-5	6	27	B 700	Pent. No. 1	12A05	12.6	ET-1662-0	11	86	A 4100	
10Z10	10.0	B3-A923-0	16	88	A 4350	Pent. No. 2	12AT6	12.6	ET-1702-0	10	60	A 1300	Triode Sect.
11AF9†	12.6	FW-8X97-0	13	88	A 5000	PENT. NO. 1. USE ADAPTER SA-11, 1059-177 MODEL 6000, 6005 NOTE 3	12AT6	12.6	ET-0602-0	0	26	C	Diode No. 1
11AF9	12.6	FW-1432-0	13	83	A 3300	Pent. No. 2	12AT6	12.6	ET-0502-0	0	26	C	Diode No. 2
11AR11†	10.0	B3-X89A-7	10	81	A 2700	Pent. No. 1	12AT7	12.6	EV-7608-0	11	82	A 3000	Triode No. 1
11AR11	10.0	B3-5236-4	10	81	A 2700	Pent. No. 2	12AT7	12.6	EV-2103-0	11	82	A 3000	Triode No. 2
11BQ11†	12.6	B3-X89A-7	10	85	A 3500	PENT. NO. 1. MAKE "LINE TEST" AT 1400 OR 3000 SCALE	12AU6	12.6	ET-1567-2	11	76	A 2300	
11BQ11	12.6	B3-5236-4	10	87	A 4000	Pent. No. 2	12AU7	12.6	EV-7608-0	24	75	A 2200	Triode No. 1
11BT11†	10.0	B3-A2X8-6	13	89	A 6000	Pent. Sect.	12AU7	12.6	EV-2103-0	24	75	A 2200	Triode No. 2
11BT11	10.0	B3-5706-0	16	77	A 2800	Triode No. 1	12AV5	12.6	HS-1583-0	42	89	A 5600	
11BT11	10.0	B3-3904-0	23	78	A 3000	Triode No. 2	12AV6	12.6	ET-1702-5	12	58	A 1250	Triode Sect.
11CA11†	10.0	B3-8AX9-7	20	86	A 4250	Pent. Sect.	12AV6	12.6	ET-1602-0	0	26	C	Diode No. 1
11CA11	10.0	B3-6405-0	20	73	A 2350	Triode No. 1	12AV6	12.6	ET-1502-0	0	26	C	Diode No. 2
11CA11	10.0	B3-3207-0	20	75	A 2500	Triode No. 2	12AV7	12.6	EV-7608-2	20	85	A 4000	Triode No. 1
11CF11†	10.0	B3-5346-0	5	91	A 8000	Pent. Sect.	12AV7	12.6	EV-2103-7	20	85	A 4000	Triode No. 2
11CF11	10.0	B3-9X08-0	5	86	A 4300	Triode No. 1	12AX3†	12.6	B3-0407-0	0	82	D	
11CF11	10.0	B3-A207-0	5	89	A 5500	Triode No. 2	12AX7	12.6	EV-7608-0	12	58	A 1250	Triode No. 1
11CY7	10.0	EV-7608-0	10	53	A 1100	Triode No. 1	12AX7	12.6	EV-2103-0	12	58	A 1250	Triode No. 2
11CY7	10.0	EV-2109-0	60	86	A 4000	Triode No. 2	12AY3†	12.6	EV-0209-0	0	87	D	
11DS5	12.6	ET-1562-0	13	87	A 4800		Model 6000 A: No Adapter Required.						
11FY7†	10.0	B3-XA09-0	20	32	A 800	Triode No. 1	12AY7	12.6	EV-7608-0	18	58	A 1250	Triode No. 1
11FY7	10.0	B3-3507-0	54	92	A 6500	Triode No. 2	12AY7	12.6	EV-2103-0	18	58	A 1250	Triode No. 2
11HM7	10.0	EV-2781-9	12	90	A 6000		12AZ7	12.6	EV-7608-0	11	81	A 3000	Triode No. 1
11JE8	10.0	EV-7986-0	11	89	A 5000	Pent. Sect.	12AZ7	12.6	EV-2103-0	11	81	A 3000	Triode No. 2
11JE8	10.0	EV-2301-0	12	78	A 2200	Triode Sect.	12B4	12.6	EV-2901-0	50	90	A 6500	
11KV8	10.0	EV-7986-0	11	91	A 7400	Pent. Sect.	12BA6	12.6	ET-1567-2	11	72	A 1900	
11KV8	10.0	EV-2301-0	19	72	A 1900	Triode Sect.	12BA7	12.6	EV-7913-2	0	31	B 750	Ampl. Sect.
11LQ8	10.0	EV-7986-0	11	91	A 7400	Pent. Sect.	12BA7	12.6	EV-2103-7	16	88	A 5000	Osc. Sect.
11LQ8	10.0	EV-2301-0	17	90	A 6500	Triode Sect.	12BD6	12.6	ET-1567-2	11	73	A 2000	
11LT8	12.6	EV-9321-6	10	80	A 3200	PENT. SECT. MAKE "LINE TEST" AT 1400 OR 3000 SCALE	12BE3†	12.6	B3-0X07-0	0	89	D	
11LT8	12.6	EV-0607-0	0	81	D	Diode No. 1	12BE6	12.6	ET-7562-1	0	35	B 800	AMPL. SECT. MAKE NO GAS TEST
11LT8	12.6	EV-0807-0	0	81	D	Diode No. 2	12BE6	12.6	ET-1602-7	20	90	A 6500	OSC. SECT. MAKE GAS TEST
11LY6	10.0	EV-2781-3	11	87	A 4500		12BF6	12.6	ET-1702-0	19	72	A 1900	Triode Sect.
11MS8	12.6	EV-9678-0	54	84	A 4400	Pent. Sect.	12BF6	12.6	ET-0602-0	0	26	C	Diode No. 1
11MS8	12.6	EV-2103-0	22	74	A 2700	Triode Sect.	12BF6	12.6	ET-0502-0	0	26	C	Diode No. 2
11Y9†	10.0	FW-8X97-0	13	88	A 5000	PENT. NO. 1. USE ADAPTER SA-11, 1059-177 MODEL 6000, 6005 NOTE 3	12BF11†	12.6	B3-8AX9-0	25	88	A 5000	Pent. No. 1
11Y9	10.0	FW-1432-0	13	83	A 3300	Pent. No. 2	12BF11	12.6	B3-3762-5	13	7	A 550	Pent. No. 2
12AC10†	12.6	B3-9X04-0	14	85	A 3700	Triode No. 1	12BH7	12.6	EV-7608-2	32	77	A 2380	Triode No. 1
12AC10	12.6	B3-7506-0	14	85	A 3700	Triode No. 2	12BH7	12.3	EV-2103-7	32	77	A 2380	Triode No. 2
12AC10	12.6	B3-A203-0	14	85	A 3700	Triode No. 3	12BN6	12.6	ET-2751-6	6	27	B 700	Limiter Grid
12AE10†	12.6	B3-8AX9-0	23	82	A 3200	Pent. No. 1	12BN6	12.6	ET-6751-2	13	0	B 500	Quadrature Grid
12AE10	12.6	B3-3762-5	22	35	A 800	Pent. No. 2	12BQ6	12.6	HS-5X48-0	42	89	A 5500	
12AF3	12.6	EV-020X-0	0	80	D		12BS3†	12.6	EV-0209-0	0	83	D	
12AL5	12.6	ET-0701-6	0	78	C	Diode No. 1	Model 6000 A: No Adapter Required.						
12AL5	12.6	ET-0205-6	0	78	C	Diode No. 2	12BT3†	12.6	B3-0407-0	0	88	D	
							12BV11†	12.6	B3-7X98-A	10	73	A 2000	Pent. No. 1
							12BV11	12.6	B3-6345-2	10	73	A 2000	Pent. No. 2
							12BY3	12.6	EV-020X-0	0	88	D	

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS	TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS
12BY7	12.6	EV-2781-3	11	87	A 4500		12GW6	12.6	HS-5X48-0	28	91	B 6600	(OCTAL SOCKET.
12BZ6	12.6	ET-1562-7	11	81	A 3000		12H-B25	12.6	EV-2X79-8	50	87	A 4500	USE ADAPTER SA-4, 1050-104, NOTE 3
12C5	12.6	ET-2761-0	20	91	B 7500		{12HE7†	12.6	B3-95A8-0	54	91	A 7000	Pent. Sect.
12CA5	12.6	DU-2761-0	20	89	A 5500		{12HE7	12.6	B3-0204-0	0	86	C	Diode Sect.
{12CK3†	12.6	EV-0209-0	0	86	C	USE ADAPTER SA-4, 1050-104, NOTE 3	12HG7	12.6	EV-2781-3	10	91	A 7500	
Model 6000 A: No Adapter Required.							12HL5	12.6	EV-2793-0	15	93	A 9500	
{12CL3†	12.6	EV-0209-0	0	86	C	USE ADAPTER SA-4, 1050-104, NOTE 3	12HL7	12.6	EV-2781-3	15	89	A 5000	
Model 6000 A: No Adapter Required.							{12JB6†	12.6	EV-2X13-8	28	91	B 6600	USE ADAPTER SA-4, 1050-104, NOTE 3
{12CR6	12.6	ET-7561-2	14	74	A 2200	Pent. Sect.	Model 6000 A: No Adapter Required.						
{12CR6	12.6	ET-0201-0	0	45	C	Diode Sect.	12JF5†	12.6	B3-3724-0	25	90	B 6000	CONNECT JUMPER FROM TUBE CAP TO PIN 7 ON OCTAL SOCKET
{12CS6	12.6	ET-1562-7	11	15	B 600	GRID NO. 1 MAKE GAS TEST	12JN6†	12.6	B3-A732-4	43	88	A 7000	
{12CS6	12.6	ET-7562-1	0	31	B 750	GRID NO. 3 MAKE NO GAS TEST	{12JN8	12.6	EV-9678-0	10	82	A 3200	Pent. Sect.
12CT3	12.6	EV-0209-0	0	94	D	OK ABOVE DIODES	{12JN8	12.6	EV-1203-0	17	89	A 5500	Triode Sect.
12CU5	12.6	ET-2761-0	11	91	B 7000		{12JQ6	12.6	EV-7139-6	50	85	A 3800	Pent. Sect.
12CU6	12.6	HS-5X48-0	42	89	A 5500		{12JQ6	12.6	EV-0609-0	0	70	C	Diode Sect.
12D4	12.6	HY-0503-0	0	86	D		12JS6†	12.6	B3-5632-4	53	88	A 4300	CONNECT JUMPER FROM TUBE CAP TO PIN 8 ON OCTAL SOCKET
12DB5	12.6	EV-3912-0	11	91	B 7500		{12JT6†	12.6	EV-2973-6	44	91	A 7000	USE ADAPTER SA-4, 1050-104, NOTE 3
{12DJ8	12.6	EV-7608-0	22	91	A 7000	Triode No. 1	Model 6000 A: No Adapter Required.						
{12DJ8	12.6	EV-2103-0	22	91	A 7000	Triode No. 2	12K5	12.6	ET-2761-0	10	80	B 3000	
12DM4	12.6	HY-0503-0	0	89	D		{12MD8†	12.6	EV-6307-0	20	85	A 3500	TRIODE NO. 1 USE ADAPTER SA-4, 1050-104, NOTE 3
12DM5	12.6	ET-2761-0	20	91	B 7500		12MD8	12.6	EV-8207-0	20	85	A 3500	Triode No. 2
12DQ6	12.6	HS-5X48-0	25	90	B 6000		12MD8	12.6	EV-9107-0	20	85	A 3500	Triode No. 3
12DT5	12.6	EV-3917-0	21	87	A 4400		Model 6000 A: No Adapter Required.						
{12DT6	12.6	ET-1562-7	23	15	A 600	Grid No. 1	{12MN8†	12.6	B3-8603-0	25	68	A 1850	Triode No. 1
{12DT6	12.6	ET-7562-1	16	0	B 500	Grid No. 3	12MN8	12.6	B3-X403-0	25	68	A 1850	Triode No. 2
{12DT7	12.6	EV-7608-0	12	58	A 1250	Triode No. 1	12MN8	12.6	B3-A203-0	25	68	A 1850	Triode No. 3
{12DT7	12.6	EV-2103-0	12	58	A 1250	Triode No. 2	{12R-LL5	12.6	EV-7608-0	23	79	A 2600	Triode No. 1
{12DT8	12.6	EV-7608-9	11	81	A 3000	Triode No. 1	12R-LL5	12.6	EV-2103-0	23	79	A 2600	Triode No. 2
{12DT8	12.6	EV-2103-9	11	81	A 3000	Triode No. 2	12SN7	12.6	HY-4506-0	23	79	A 2600	Triode No. 1
{12DW4	12.6	EV-0209-0	0	89	D	USE ADAPTER SA-4, 1050-104, NOTE 3	12SN7	12.6	HY-1203-0	23	79	A 2600	Triode No. 2
Model 6000 A: No Adapter Required.							{12T10†	12.6	B3-8AX9-0	19	88	A 4500	Pent. No. 1
{12DW7	12.6	EV-7608-0	12	58	A 1250	Triode No.	12T10	12.6	B3-3762-5	14	21	B 625	Pent. No. 2
{12DW7	12.6	EV-2103-0	25	75	A 2200	Triode No.	12V6	12.6	HS-5348-0	13	86	A 4100	
{12FQ8	12.6	EV-7809-0	10	35	A 800	TRIODE NO. 1 PLATE NO. 1	12W6	12.6	HS-5348-0	11	91	B 7500	
{12FQ8	12.6	EV-7609-0	10	35	A 800	TRIODE NO. 1 PLATE NO. 2	{12X4	12.6	ET-0607-1	0	40	D	Plate No. 1
{12FQ8	12.6	EV-2309-0	10	35	A 800	TRIODE NO. 2 PLATE NO. 1	12X4	12.6	ET-0107-6	0	40	D	Plate No. 2
{12FQ8	12.6	EV-2109-0	10	35	A 800	TRIODE NO. 2 PLATE NO. 2	{13CW4†	12.6	DR-4208-0	23	79	A 2600	USE ADAPTER SA-3, 1050-101, NOTE 1
12FX5	12.6	ET-2761-0	10	90	A 5750		Model 6000 A:						
12G11†	12.6	B3-8AX9-0	19	89	A 5500	Pent. No. 1	13CW4	12.6	13-4208-0	23	79	A 2600	
12G11	12.6	B3-3672-4	10	8	A 700	Pent. No. 2	{13DE7	12.6	EV-7608-0	27	73	A 2000	Triode No. 1
12GC6	12.6	HS-5X83-0	45	90	A 8000		{13DE7	12.6	EV-2109-0	54	89	A 6500	Triode No. 2
12GE5†	12.6	B3-A72X-0	48	90	A 6000		{13DR7	12.6	EV-7608-0	17	36	A 800	Triode No. 1
{12GJ5†	12.6	EV-6X73-0	28	91	B 6600	USE ADAPTER SA-4, 1050-104, NOTE 3	{13DR7	12.6	EV-2109-0	56	88	A 3600	Triode No. 2
Model 6000 A: No Adapter Required.							13EM7	12.6	HY-4506-0	10	66	A 1500	Triode No. 1
12GN7	12.6	EV-2781-9	12	89	A 5550		{13EM7	12.6	HY-1203-0	53	91	A 5250	Triode No. 2
{12GT5†	12.6	EV-6973-0	28	91	B 6600	USE ADAPTER SA-4, 1050-104, NOTE 3	{13FD7	12.6	EV-7608-0	10	68	A 1600	Triode No. 1
Model 6000 A: No Adapter Required.							13FD7	12.6	EV-2109-0	58	89	A 4500	Triode No. 2
12GV5†	12.6	B3-92A4-0	42	86	A 4500	DO NOT USE TESTER CAP CONNECTOR. JUMPER CAP TO PIN 2 OF THE OCTAL SOCKET.							

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS	TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS
{13FM7†	12.6	B3-XA09-0	20	46	A 950	Triode No. 1	{15LE8	12.6	EV-9683-7	10	57	A 1300	PENT. NO. 1. MAKE "LINE TEST" AT 1000 ON 3000 SCALE
{13FM7	12.6	B3-8507-0	62	88	A 5250	Triode No. 2	{15LE8	12.6	EV-9183-2	10	57	A 1300	Pent. No. 2
{13GF7†	12.6	EV-9801-0	19	35	A 700	TRIODE NO. 1 USE ADAPTER SA-4, 1050-144, NOTE 3	{15MF8†	12.6	B3-7489-0	30	84	A 4000	PENT. SECT. MAKE "LINE TEST" AT 1000 ON 3000 SCALE
{13GF7	12.6	EV-2603-0	63	86	A 4200	Triode No. 2	{15MF8	12.6	B3-X20A-0	23	66	A 1900	Triode Sect.
Model 6000 A: No Adapter Required.							{15MX8†	17.0	EV-2673-0	42	80	A 2550	PENT. SECT. MAKE "LINE TEST" AT 1425 ON 3000 SCALE. USE ADAPTER SA-3 1050-144 NOTE 3
{13J10†	12.6	B3-7468-5	6	27	B 700	Pent. No. 1	{15MX8	17.0	EV-9801-0	19	27	A 700	Triode Sect.
{13J10	12.6	B3-A923-0	16	88	A 4350	Pent. No. 2	Model 6000A: No Adapter Required.						
{13JZ8†	12.6	B3-7489-0	25	88	A 3900	Pent. Sect.	{16AK9†	17.0	B3-8597-0	30	85	A 4150	Pent. Sect.
{13JZ8	12.6	B3-X20A-0	29	65	A 1350	Triode Sect.	{16AK9	17.0	B3-XA07-0	18	75	A 2400	Triode No. 1
{13V10†	12.6	B3-8AX9-0	21	87	A 4200	Pent. No. 1	{16AK9	17.0	B3-3207-0	26	59	A 1750	Triode No. 2
{13V10	12.6	B3-3762-5	24	0	A 500	Pent. No. 2	{16BQ11†	17.0	B3-X89A-7	10	85	A 3500	Pent. No. 1
{13Z10†	12.6	B3-7468-5	6	27	B 700	Pent. No. 1	{16BQ11	17.0	B3-5236-4	10	87	A 4000	Pent. No. 2
{13Z10	12.6	B3-A923-0	16	88	A 4350	Pent. No. 2	{16BX11†	17.0	B3-2A3X-0	5	88	A 4900	Pent. Sect.
{14BL11†	12.6	B3-A2X8-0	13	90	A 5500	Pent. Sect.	{16BX11	17.0	B3-8709-0	5	89	A 5500	Triode No. 1
{14BL11	12.6	B3-5706-0	14	82	A 3000	Triode No. 1	{16BX11	17.0	B3-5604-0	5	90	A 6000	Triode No. 2
{14BL11	12.6	B3-3904-0	22	82	A 3000	Triode No. 2	{16GK6	17.0	EV-2781-3	7	90	A 5900	
{14BR11†	12.6	B3-2A34-0	10	89	A 4750	Pent. Sect.	{16GY5†	17.0	B3-527X-0	30	92	B 9000	DO NOT USE TESTER CAP CONNECTOR. CONNECT CAP TO PIN 2 OF DIGITAL SOCKET
{14BR11	12.6	B3-8605-0	17	81	A 2600	Triode No. 1	{16HB5†	17.0	B3-A72X-0	57	89	A 5600	
{14BR11	12.6	B3-X907-0	14	82	A 3000	Triode No. 2	{16JV6†	17.0	B3-A732-X	55	91	A 7000	
{14GT8	12.6	EV-8907-0	10	15	A 600	Triode Sect.	{16KA6†	17.0	B3-523X-4	57	89	A 5500	DO NOT USE TESTER CAP CONNECTOR. CONNECT CAP TO PIN 2 OF N DIGITAL SOCKET
{14GT8	12.6	EV-0601-0	0	80	C	Diode No. 1	{16LU8†	17.0	B3-6489-0	40	87	A 4000	Pent. Sect.
{14GT8	12.6	EV-0203-0	0	80	C	Diode No. 2	{16LU8	17.0	B3-X20A-0	24	62	A 1400	Triode Sect.
{14JG8	12.6	EV-8907-0	10	65	A 1500	Triode Sect.	{16MY8†	17.0	B3-6489-0	40	87	A 4000	Pent. Sect.
{14JG8	12.6	EV-0601-0	0	77	C	Diode No. 1	{16MY8	17.0	B3-X20A-0	24	62	A 1400	Triode Sect.
{14JG8	12.6	EV-0203-0	0	77	C	Diode No. 2	{16Y9†	17.0	FW-8X97-0	13	88	A 5000	PENT. NO. 2. USE ADAPTER SA-11, 1050-177 MODEL 6000, 6005 NOTE 3
{15AF11†	17.0	B3-A2X9-0	8	90	A 5400	PENT. SECT. MAKE "LINE TEST" AT 1425 ON 3000 SCALE	{16Y9	17.0	FW-1432-0	13	83	A 3300	Pent. No. 2
{15AF11	17.0	B3-6805-0	17	81	A 2700	Triode No. 1	{17AB9†	17.0	FW-978X-0	15	81	A 3000	TETRODE NO. 1. USE ADAPTER SA-11, 1050-177 MODEL 6000, 6005 NOTE 3
{15AF11	17.0	B3-3407-0	13	82	A 2800	Triode No. 2	{17AB9	17.0	FW-3124-0	15	81	A 3000	Tetrode No. 2
{15BD11†	17.0	B3-A2X9-0	12	87	A 4500	PENT. SECT. MAKE "LINE TEST" AT 1400 ON 3000 SCALE	{17AB10†	17.0	B3-7468-5	6	27	B 700	Limiter Grid
{15BD11	17.0	B3-6805-0	13	78	A 2500	Triode No. 1	{17AB10	17.0	B3-5468-7	13	0	B 500	Quadrature Grid
{15BD11	17.0	B3-3407-0	10	80	A 2750	Triode No. 2	{17AB10	17.0	B3-A923-0	25	83	A 3100	Pent. No. 2
{15CW5	17.0	EV-2793-0	42	88	A 5000	MAKE "LINE TEST" AT 1400 ON 3000 SCALE.	{17AX3†	17.0	B3-0407-0	0	82	D	
{15EW7	17.0	EV-7608-0	30	63	A 1450	TRIODE NO. 1 MAKE "LINE TEST" AT 1400 ON 3000 SCALE	{17AX4	17.0	HY-0503-0	0	82	D	
{15EW7	17.0	EV-2109-0	56	91	A 4350	Triode No. 2	{17AY3†	17.0	EV-0209-0	0	87	D	USE ADAPTER SA-4, 1050-144, NOTE 3
{15FM7†	12.6	B3-XA09-0	20	46	A 950	Triode No. 1	Model 6000 A: No Adapter Required.						
{15FM7	12.6	B3-8507-0	59	88	A 5250	Triode No. 2	{17BE3†	17.0	B3-0X07-0	0	89	D	
{15FY7†	17.0	B3-XA09-0	18	33	A 750	TRIODE NO. 1 MAKE "LINE TEST" AT 1425 ON 3000 SCALE	{17BF11†	17.0	B3-8AX9-0	25	88	A 5000	Pent. No. 1
{15FY7	17.0	B3-3507-0	47	91	A 6500	Triode No. 2	{17BF11	17.0	B3-3762-5	13	7	A 540	Pent. No. 2
{15HA6	17.0	EV-2761-3	10	90	A 6500		{17BH3†	17.0	EV-0209-0	0	87	D	USE ADAPTER SA-4, 1050-144, NOTE 3
{15HB6	17.0	EV-2781-9	20	88	A 5000		Model 6000 A: No Adapter Required.						
{15KY8†	17.0	EV-2673-0	42	80	A 2550	PENT. SECT. MAKE "LINE TEST" AT 1425 ON 3000 SCALE USE ADAPTER SA-4, 1050-144, NOTE 3	{17BQ6	17.0	HS-5X48-0	42	89	A 5500	
{15KY8	17.0	EV-9801-0	19	27	A 700	Triode Sect.	{17BS3†	17.0	EV-0209-0	0	83	D	USE ADAPTER SA-4, 1050-144, NOTE 3
Model 6000 A: No Adapter Required.							Model 6000 A: No Adapter Required.						

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS	TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS	
17BW3†	17.0	B3-0407-0	0	89	D	OK ABOVE DIODES OK	17X10†	17.0	B3-7468-5	6	27	B	700	Limiter Grid
17BZ3†	17.0	B3-0X07-0	0	86	C		17X10	17.0	B3-5468-7	13	0	B	500	GRADUATED GRID
17C5	17.0	ET-2761-0	20	91	B	7500	17X10	17.0	B3-A923-0	25	83	A	3100	Pent. No. 2
17C9†	17.0	EV-7986-0	15	85	A	3200	18A5	17.0	HS-1583-0	40	88	A	4800	
17C9	17.0	EV-132X-0	15	85	A	3200	18AJ10†	17.0	B3-8AX9-0	29	72	B	2400	Pent. No. 1
17CK3†	17.0	EV-0209-0	0	86	C		18AJ10	17.0	B3-3762-5	10	60	A	900	Pent. No. 2
Model 6000 A: No Adapter Required.							18FW6	17.0	ET-1567-2	12	73	A	2000	
17CL3†	17.0	EV-0209-0	0	86	C		18FX6	17.0	ET-1562-7	11	43	A	900	Ampl. Sect.
Model 6000 A: No Adapter Required.							18FX6	17.0	ET-1602-7	19	88	A	5000	Osc. Sect.
17CT3	17.0	EV-0209-0	0	94	D	OK ABOVE DIODES OK	18FY6	17.0	ET-1702-0	21	0	A		TRIODE SECT. OK ABOVE ON 2ND SCALE.
17CU5	17.0	ET-2761-0	38	86	A	4300	18FY6	17.0	ET-0602-0	0	32	C		Diode No. 1
17D4	17.0	HY-0503-0	0	86	D		18FY6	17.0	ET-0502-0	0	32	C		Diode No. 2
17DE4	17.0	HY-0503-0	0	89	D		18GB5	17.0	EV-2X78-0	64	89	A	5000	USE ADAPTER SA-4 1056-144
17DM4	17.0	HY-0503-0	0	89	D		18GD6A	17.0	ET-1567-2	15	73	A	1750	
17DQ6	17.0	HS-5X48-0	25	90	B	6000	18AQ5	20.0	ET-1562-0	11	86	A	4100	
17DW4	17.0	EV-0209-0	0	89	D		18AU4	20.0	HY-0503-0	0	89	D		
Model 6000A: No Adapter Required.							19CG3†	20.0	B3-0407-0	0	91	D		
17GE5†	17.0	B3-A72X-0	48	90	A	6000	19CL8A	20.0	EV-9678-0	10	84	A	3300	Tetrode Sect.
17GJ5†	17.0	EV-6X73-0	28	91	B	6600	19CL8A	20.0	EV-1203-0	12	89	A	6000	Triode Sect.
Model 6000 A: No Adapter Required.							19DE3†	20.0	B3-0403-0	0	86	C		CONNECT JUMPER FROM TUBE CAP TO PIN 3 ON OCTAL SOCKET
17GT5†	17.0	EV-6973-0	28	91	B	6600	19DK3	20.0	EV-020X-0	0	86	C		
Model 6000 A: No Adapter Required.							19DQ3†	20.0	B3-0407-0	0	86	C		
17GV5†	17.0	B3-92A4-0	44	91	A	7000	19EA8	20.0	EV-2637-0	17	79	A	2600	Pent. Sect.
17GW6	17.0	HS-5X48-0	28	91	B	6600	19EA8	20.0	EV-9108-0	13	89	A	5000	Triode Sect.
17H3	17.0	EV-0301-0	0	80	D		19EZ8	20.0	EV-9800-0	19	69	A	1700	Triode No. 1
17H-B25	17.0	EV-2X79-8	50	87	A	4500	19EZ8	20.0	EV-7600-0	19	69	A	1700	Triode No. 2
17JB6†	17.0	EV-2X13-8	28	91	B	6600	19EZ8	20.0	EV-2301-0	20	71	A	1850	Triode No. 3
Model 6000 A: No Adapter Required.							If no reading is obtained, use selector setting FU- in place of EV-.							
17JF6†	17.0	EV-2X73-8	32	92	B	7800	19FX5	20.0	ET-2761-0	10	90	A	5750	
Model 6000 A: No Adapter Required.							19GQ7	20.0	EV-8809-0	0	80	C		Diode No. 1
17JG6A†	17.0	EV-2973-6	32	92	B	7800	19GQ7	20.0	EV-0607-0	0	80	C		Diode No. 2
Model 6000 A: No Adapter Required.							19GQ7	20.0	EV-0201-0	0	80	C		Diode No. 3
17JM6†	17.0	B3-5632-4	43	88	A	7000	19HR6	20.0	ET-1567-2	10	84	A	3600	
17JN6†	17.0	B3-A732-4	43	88	A	7000	19HS6	20.0	ET-1567-2	14	82	A	3200	
17JQ6	17.0	EV-7139-6	50	85	A	3800	19HV8	20.0	EV-9678-0	11	81	A	3000	Pent. Sect.
17JQ6	17.0	EV-0609-0	0	70	C		19HV8	20.0	EV-1203-0	14	59	A	1300	Triode Sect.
17JR6†	17.0	EV-2913-6	65	85	A	4200	19JN8	20.0	EV-9678-0	10	82	A	3200	Pent. Sect.
Model 6000A: No adapter required.							19JN8	20.0	EV-1203-0	17	89	A	5500	Triode Sect.
17JT6†	17.0	EV-2973-6	44	91	A	7000	19KG8	20.0	EV-9678-0	11	82	A	3100	Pent. Sect.
Model 6000 A: No Adapter Required.							19KG8	20.0	EV-2103-0	18	88	A	5100	Triode Sect.
17JZ8†	17.0	B3-7489-0	33	88	A	5000	19M-R9	17.0	ET-1567-2	15	73	A	1750	
17JZ8	17.0	B3-X20A-0	31	57	A	1350	19Q9†	20.0	EV-132X-6	10	82	A	3100	Pent. Sect.
17KV6†	17.0	EV-2973-6	41	87	B	4800	19Q9	20.0	EV-8907-6	18	87	A	4600	Triode Sect.
Model 6000A: No Adapter Required.							19X8	20.0	EV-7986-1	12	81	A	3000	Pent. Sect.
17LD8†	17.0	EV-2673-0	35	91	A	4800	19X8	20.0	EV-2308-1	20	84	A	3500	Triode Sect.
17LD8	17.0	EV-9801-0	31	73	A	1300	20AQ3	20.0	EV-090X-0	0	93	D		
Model 6000 A: No Adapter Required.							20EW7	20.0	EV-7608-0	27	72	A	2000	Triode No. 1
							20EW7	20.0	EV-2109-0	54	88	A	6000	Triode No. 2
							20EZ7	20.0	CR-8709-0	12	58	A	1250	Triode No. 1
							20EZ7	20.0	CR-5604-0	12	58	A	1250	Triode No. 2

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS	TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS	
20LF6†	20.0	B3-5632-4	69	85	A 4350	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET	24BF11†	25.0	B3-8AX9-0	25	88	A 5000	Pentode No. 1	
21GY5†	20.0	B3-527X-0	30	92	B 9000	DO NOT USE TESTER CONNECTOR. CONNECT CAP TO PIN 2 OF OCTAL SOCKET	24BF11	25.0	B3-3762-5	19	7	A 600	Pentode No. 2	
21HB5†	20.0	B3-A72X-0	57	89	A 5600		24GA7†	25.0	B3-4735-0	58	89	A 4500	Pent. Sect.	
21HD5†	20.0	B3-A79X-0	54	89	A 6000		24GA7	25.0	B3-0A08-0	0	85	D	Diode Sect.	
21HJ5†	20.0	B3-A792-X	54	90	A 6500		24JE6A†	25.0	EV-2X73-8	39	92	B 8100	USE ADAPTER SA-4, 1050-144, NOTE 3	
21JS6†	20.0	B3-5632-4	53	88	A 4300	CONNECT JUMPER FROM TUBE CAP TO PIN 6 OF OCTAL SOCKET	Model 6000 A:	No Adapter Required.						
21JV6†	20.0	B3-A732-X	55	91	A 7000		24JZ8†	25.0	B3-7489-0	32	86	A 4150	Pent. Sect.	
21JZ6†	20.0	B3-5632-4	56	91	A 7000	CONNECT A JUMPER FROM CAP TO PIN 8 OF OCTAL SOCKET	24JZ8	25.0	B3-X20A-0	29	60	A 1500	Triode Sect.	
21KA6†	20.0	B3-523X-4	57	89	A 5500	DO NOT USE TESTER CONNECTOR. JUMPER CAP TO PIN 1 OF THE OCTAL SOCKET	24LQ6†	25.0	EV-2X73-8	39	92	B 8100	USE ADAPTER SA-4, 1050-144, NOTE 3	
21KQ6	20.0	EV-8X39-0	65	87	A 4800	USE ADAPTER SA-4, 1050-144, NOTE 3	Model 6000A:	No Adapter Required.						
21LG6†	20.0	B3-58A4-0	64	86	A 4650	CONNECT CAP OF TUBE TO PIN 6 OF OCTAL SOCKET	24LZ6†	25.0	EV-6X73-8	75	88	A 4500	USE ADAPTER SA-4, 1050-144, NOTE 3	
21LR8†	20.0	EV-2673-0	40	87	A 4000	PERF. SECT. USE ADAPTER SA-4, 1050-144, NOTE 3	Model 6000A:	No Adapter Required.						
21LR8	20.0	EV-9801-0	24	62	A 1400	Triode Sect.	25AV5	25.0	HS-1583-0	42	89	A 5500		
Model 6000 A:	No Adapter Required.							25AX4	25.0	HY-0503-0	0	82	D	
21LU8†	20.0	B3-6489-0	40	87	A 4000	Pent. Sect.	25BK5	25.0	EV-3186-0	11	88	A 5000		
21LU8	20.0	B3-X20A-0	24	62	A 1400	Triode Sect.	25BQ6	25.0	HS-5X48-0	42	89	A 5500		
21MY8†	20.0	B3-6489-0	40	87	A 4000	Pent. Sect.	25C5	25.0	ET-2761-0	20	91	B 7500		
21MY8	20.0	B3-X20A-0	24	62	A 1400	Triode Sect.	25CA5	25.0	DU-2761-0	20	89	A 5500		
22BH3†	20.0	EV-0209-0	0	87	D	MAKE "LINE TEST" AT 100 ON 300 SCALE USE ADAPTER SA-4, 1050-144, NOTE 3	25CD6	25.0	HS-5X83-0	35	90	A 6500		
Model 6000 A:	No Adapter Required.							25CG3†	25.0	B3-0407-0	0	91	D	
22BW3†	25.0	B3-0X07-0	0	89	D		25CK3†	25.0	EV-0209-0	0	86	C		
22DE4	25.0	HY-0503-0	0	89	D		Model 6000A:	No Adapter Required.						
22JF6†	20.0	EV-2X73-8	32	92	B 7800	USE ADAPTER SA-4, 1050-144, NOTE 3	25CM3†	25.0	EV-0279-0	0	90	D		
Model 6000 A:	No Adapter Required.							Model 6000 A:	No Adapter Required.					
22JG6†	20.0	EV-2973-6	32	92	B 7800	USE ADAPTER SA-4, 1050-144, NOTE 3	25CT3	25.0	EV-0209-0	0	94	D		
Model 6000 A:	No Adapter Required.							25DK3	25.0	EV-020X-0	0	86	C	
22JR6†	20.0	EV-2913-6	65	85	A 4200	USE ADAPTER SA-4, 1050-144, NOTE 3	25DN6	25.0	HS-5X83-0	28	93	B 9000		
Model 6000A:	No adapter required.							25EC6	25.0	HS-5X83-0	42	89	A 5500	
22JU6†	20.0	EV-2X73-8	72	85	A 4200	USE ADAPTER SA-4, 1050-144, NOTE 3	25EH5	25.0	ET-2761-0	13	88	A 10000		
Model 6000 A:	No Adapter Required.							25F5	25.0	ET-2761-0	25	85	A 4000	
22KM6†	20.0	EV-2X73-8	65	89	A 5000	USE ADAPTER SA-4, 1050-144, NOTE 3	25F5A	25.0	ET-2761-0	25	86	A 4400		
Model 6000 A:	No Adapter Required.							25H-B25	25.0	EV-2X79-8	50	87	A 4400	USE ADAPTER SA-3, 1050-144, NOTE 3
22KV6†	20.0	EV-2973-6	41	87	B 4800	USE ADAPTER SA-4, 1050-144, NOTE 3	25HX5	25.0	EV-7963-0	50	88	A 5000	USE ADAPTER SA-3, 1050-144, NOTE 3	
Model 6000A:	No Adapter Required.							25JQ6	25.0	EV-7139-6	50	85	A 3800	Pent. Sect.
23JS6†	25.0	B3-5632-4	53	88	A 4300	CONNECT JUMPER FROM TUBE CAP TO PIN 6 OF OCTAL SOCKET. NOTE 3	25JQ6	25.0	EV-0609-0	0	70	C	Diode Sect.	
Model 6000A:	No Adapter Required.							25JZ8†	25.0	B3-7489-0	32	86	A 4150	Pent. Sect.
23MB6†	25.0	B3-5632-4	70	89	A 6400	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET	25JZ8	25.0	B3-X20A-0	29	60	A 1500	Triode Sect.	
23Z9†	25.0	B3-8597-0	35	88	A 5000	Pent. Sect.	25L6	25.0	HS-5348-1	33	88	A 5200		
23Z9	25.0	B3-XA07-0	20	76	A 2200	Triode No. 1	25W4	25.0	HY-0503-0	0	88	D		
23Z9	25.0	B3-3207-0	30	69	A 1800	Triode No. 2	26DQ5	25.0	HS-1X43-0	43	92	A 7800		
							26HU5	25.0	HY-1X32-0	70	90	A 7500		
							26LW6	25.0	HY-5X32-0	75	88	A 5500		
							26LX6†	25.0	B3-5632-4	70	90	A 7500	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET	
							27LF6†	25.0	B3-5632-4	69	85	A 4350	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET	
							28D7	25.0	JR-7536-2	13	83	B 3400	Pent. No. 1	
							28D7	25.0	JR-2436-7	13	83	B 3400	Pent. No. 2	
							28HA6	25.0	EV-2761-3	10	90	A 6500		
							28HD5†	25.0	B3-A79X-0	54	89	A 6000		

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS	TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS	
29GK6	25.0	EV-2781-3	10	90	A 5750		35C6	35.0	ET-2761-0	23	87	A 4500		
29LE6	25.0	EV-8X39-7	65	87	A 4800	USE ADAPTER SA-4 168-168	36EH5	35.0	ET-2761-0	10	89	A 5000		
30AG11†	35.0	B3-8709-0	15	87	A 4000	TRIODE NO. 1 MAKE "LINE TEST" AT 1250 ON 3000 SCALE	35GL6	35.0	ET-2751-0	35	88	A 5300		
30AG11	35.0	B3-5604-0	15	87	A 4000	Triode No. 2	35HB8	35.0	EV-9768-0	23	74	A 2100	Pent. Sect.	
30AG11	35.0	B3-0X0A-0	0	76	C	Diode No. 1	35HB8	35.0	EV-1302-0	20	63	A 1300	Triode Sect.	
30AG11	35.0	B3-0302-0	0	76	C	Diode No. 2	35L6	35.0	HS-5348-0	21	87	A 4600		
30HJ5†	25.0	B3-A792-X	54	90	A 6500		35LR6†	35.0	B3-5832-4	85	73	A 2250	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET.	
30JZ6†	25.0	B3-5632-4	56	91	A 7000	CONNECT JUMPER FROM CAP TO PIN 6 OF OCTAL SOCKET	35W4	35.0	ET-0507-0	0	88	D	---	
30KD6†	35.0	B3-5632-4	70	90	A 6400	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET.	36Z5	35.0	HS-0508-0	0	88	D	---	
30MB6†	35.0	B3-5632-4	70	90	A 6400	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET	36AM3	35.0	ET-0507-0	0	88	D	---	
30M-P27	25.0	ET-2761-0	54	84	A 4400		36KD6†	35.0	B3-5632-4	70	90	A 7500	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET	
30R-K47	25.0	EV-090X-0	0	93	D		36LW6	35.0	HY-5X32-0	75	88	A 5500		
31AL10†	35.0	B3-8457-0	26	90	A 7100	Pent. Sect.	36MC6†	35.0	EV-2X73-8	70	90	A 7500	USE ADAPTER SA-4 168-144. NOTE 3	
31AL10	35.0	B3-A90X-0	7	85	A 4000	Triode No. 1	Model 6000A: No Adapter Required.	38HE7†	50.0	B3-95A8-0	51	91	A 7000	PENT. SECT. MAKE "LINE TEST" AT 1400 ON 3000 SCALE
31AL10	35.0	B3-3207-0	22	78	A 2900	Triode No. 2	38HE7	50.0	B3-0204-0	0	86	C	---	Diode Sect.
31JS6A†	35.0	B3-5632-4	53	88	A 4300	CONNECT JUMPER FROM TUBE CAP TO PIN NO. 6 ON OCTAL SOCKET	38HK7†	35.0	B3-95A8-0	55	90	A 6000	Pent. Sect.	
31LQ6†	35.0	EV-2X73-8	39	92	B 8100	USE ADAPTER SA-4, 168-144. NOTE 3	38HK7	35.0	B3-0204-0	0	87	C	---	Diode Sect.
Model 6000A: No Adapter Required.							40FR5	35.0	ET-2761-0	38	85	A 3900		
31LR8†	35.0	EV-2673-0	40	87	A 4000	PENT. SECT. USE ADAPTER SA-4, 168-144. NOTE 3	40KD6†	50.0	B3-5632-4	70	90	A 7500	CONNECT JUMPER FROM TUBE CAP TO PIN 6 ON OCTAL SOCKET.	
31LR8	35.0	EV-9801-0	24	62	A 1400	Triode Sect.	42EC4	50.0	EV-0705-0	0	85	C	---	USE ADAPTER SA-3, 168-144. DO NOT USE TESTER CAP CONNECTOR. JUMPER CAP TO PIN 6 OF OCTAL SOCKET
Model 6000A: No Adapter Required.							42KN6†	50.0	B3-5632-4	60	89	A 5000		
31LZ6†	35.0	EV-6X73-8	75	88	A 4500	USE ADAPTER SA-4, 168-144. NOTE 3	50BM8	50.0	EV-3672-0	24	86	A 4300	Pent. Sect.	
Model 6000A: No Adapter Required.							50BM8	50.0	EV-1908-0	11	71	A 1900	Triode Sect.	
32ET5	35.0	ET-2761-0	37	86	A 4000		50C6	50.0	ET-2761-0	20	91	B 7500		
32GA7†	35.0	B3-4735-0	58	89	A 4500	Pent. Sect.	50DC4	50.0	ET-0507-0	0	90	D	---	
32GA7	35.0	B3-0A08-0	0	85	D	Diode Sect.	50EH5	50.0	ET-2761-0	13	88	A 10000		
32HQ7†	35.0	B3-95A8-0	43	86	B 4500	Pent. Sect.	50FE5	50.0	HS-5348-0	30	92	A 8300		
32HQ7	35.0	B3-0204-0	0	84	C	Diode Sect.	50FK6	50.0	ET-2761-0	20	87	A 4800		
33GT7†	35.0	B3-A5X8-0	31	91	B 6000	Pent. Sect.	50GY7†	50.0	B3-X5A8-0	31	91	B 6000	Pent. Sect.	
33GT7	35.0	B3-0204-0	0	85	D	Diode Sect.	50GY7	50.0	B3-0204-0	0	85	D	---	Diode Sect.
33GY7†	35.0	B3-X5A8-0	31	91	B 6000	Pent. Sect.	50HC6	50.0	ET-2751-0	13	88	A 10000		
33GY7	35.0	B3-0204-0	0	85	D	Diode Sect.	50HK6	50.0	ET-2751-0	20	91	B 7500		
33HE7†	35.0	B3-95A8-0	54	91	A 7000	Pent. Sect.	50HN5	50.0	EV-2793-0	15	93	A 9500		
33HE7	35.0	B3-0204-0	0	89	D	Diode Sect.	53HK7†	50.0	B3-95A8-0	55	90	A 6000	Pent. Sect.	
33JR6†	35.0	EV-2913-6	65	85	A 4200	USE ADAPTER SA-4, 168-144. NOTE 3	53HK7	50.0	B3-0204-0	0	87	C	---	Diode Sect.
Model 6000 A: No Adapter Required.							58HE7†	50.0	B3-95A8-0	54	91	A 7000	Pent. Sect.	
33JV6†	35.0	B3-A732-X	55	91	A 7000		58HE7	50.0	B3-0204-0	0	86	C	---	Diode Sect.
34CD3†	35.0	B3-0X07-0	0	93	D		60FX5	50.0	ET-2761-0	10	90	A 5750		
34CE3†	35.0	B3-0407-0	0	86	C		60HL5	50.0	EV-2793-0	27	91	A 8500	MAKE "LINE TEST" AT 1750 ON 3000 SCALE	
34CM3†	35.0	EV-0279-0	0	90	D	PLATE TO SCREEN SHORT NORMAL USE ADAPTER SA-4, 168-144. NOTE 3	KT66	6.3	HS-5348-1	13	90	A 6300		
Model 6000 A: No Adapter Required.							80	5.0	ER-0300-0	0	22	D	---	Plate No. 1
34GD5	35.0	ET-2761-0	36	87	A 4500		80	5.0	ER-0200-0	0	18	D	---	Plate No. 2
34DK3	35.0	EV-020X-0	0	86	C		83	5.0	ER-0300-0	0	92	D	---	Plate No. 1
35B5	35.0	ET-1562-0	23	87	A 4500		83	5.0	ER-0200-0	0	90	D	---	Plate No. 2
							KT88	6.3	HS-5348-1	13	88	A 5000		

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS	TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS	
866A	4.3	ER-0X00-0	0	92	D		5842	6.3	DZ-5106-0	19	93	A	8000	
884	6.3	HS-5308-0	*	94	F		{5844	6.3	ET-5207-0	26	81	A	3000	Triode No. 1
885	2.5	FR-3204-0	*	94	F		{5844	6.3	ET-6107-0	26	81	A	3000	Triode No. 2
{1217	6.3	ET-7562-1	11	59	B	1300	5847	6.3	DZ-1684-0	11	88	A	5000	
{1217	6.3	ET-1562-7	11	43	B	900	{5852	6.3	HS-0508-0	0	0	D		Plate No. 1
1218A	6.3	ET-6705-0	14	89	A	6000	{5852	6.3	HS-0308-0	0	0	D		Plate No. 2
1222	6.3	GR-4237-8	17	88	A	5000	5876	6.3	HS-3506-0	10	84	A	3600	USE NISKOK ADAPTER SA-9 CODE NO. 109-121
2050	6.3	HS-5308-6	*	94	F		5881	6.3	HS-5348-1	17	88	A	5000	
2051	6.3	HS-5308-6	*	94	F		5893	6.3	HS-3506-0	10	87	A	4600	USE NISKOK ADAPTER SA-9 CODE NO. 109-121
4604	6.3	CX-5X30-0	38	87	A	4500	{5896	6.3	DW-0507-4	0	80	D		Plate No. 1
{5636	6.3	DW-1572-4	13	67	A	1600	{5896	6.3	DW-0102-4	0	80	D		Plate No. 2
{5636	6.3	DW-4578-1	22	0	B	500	5897	6.3	DW-1805-0	25	84	A	3600	
5642	1.1	BS-0X00-0	0	0	D		5899	6.3	DW-1574-0	19	73	A	2000	
5643	6.3	DW-7105-2	*	85	D		5900	6.3	DW-1574-0	19	73	A	2000	
5654	6.3	ET-1562-0	24	65	A	1500	5902	6.3	DW-1572-0	40	86	A	4200	
{5670	6.3	KR-7608-0	16	86	A	4000	{5903	25.0	DW-0507-4	0	80	D		Plate No. 1
{5670	6.3	KR-3402-0	16	86	A	4000	{5903	25.0	DW-0102-4	0	80	D		Plate No. 2
5672	1.1	DV-4120-0	32	21	B	650	5904	25.0	DW-1805-0	36	73	A	2000	
5675	6.3	HS-3506-0	20	88	A	5000	5905	25.0	DW-1572-0	18	70	B	1800	
5676	1.1	ES-3100-0	26	62	A	1400	5906	25.0	DW-1572-0	13	81	A	3000	
5677	1.1	ES-3100-0	38	21	A	650	5907	25.0	DW-1572-0	15	75	B	2200	
5678	1.1	DV-4120-0	12	31	B	750	5908	25.0	DW-1572-4	20	69	B	1750	
5686	6.3	EV-2763-0	11	79	A	2600	{5915A	6.3	ET-1562-7	11	59	B	1300	Grid No. 1
{5687	12.6	EV-7906-1	26	91	A	7500	{5915A	6.3	ET-7562-1	11	43	B	900	Grid No. 3
{5687	12.6	EV-2103-9	26	91	A	7500	5916	25.0	DW-1572-4	20	67	A	1600	
5696	6.3	ET-1602-5	*	94	F		5930	2.5	ER-3200-0	68	81	A	3000	
5702	6.3	DU-7126-5	24	65	A	1500	{5931	5.0	JS-0600-0	0	45	D		Plate No. 1
5703	6.3	DU-5106-0	26	81	A	3000	{5931	5.0	JS-0400-0	0	35	D		Plate No. 2
5704	6.3	CT-0104-0	0	79	C		5932	6.3	HS-5348-1	17	88	A	5000	
5719	6.3	DW-1805-7	23	89	A	5500	5933	6.3	FR-3X24-0	25	85	A	3800	
5719	6.3	DW-1805-7	17	65	A	1500	{5963	12.6	EV-7608-0	24	75	A	2200	Triode No. 1
5725	6.3	ET-1562-7	11	48	A	1000	{5963	12.6	EV-2103-0	24	75	A	2200	Triode No. 2
{5726	6.3	ET-0701-6	0	78	C		{5964	6.3	ET-5207-6	21	85	A	4000	Triode No. 1
{5726	6.3	ET-0205-6	0	78	C		{5964	6.3	ET-6107-5	21	85	A	4000	Triode No. 2
5727	6.3	ET-1602-5	*	94	F		{5965	12.6	EV-7608-1	16	90	A	6500	Triode No. 1
5744	6.3	CT-4105-0	16	73	A	2000	{5965	12.6	EV-2103-6	16	90	A	6500	Triode No. 2
5749	6.3	ET-1567-2	11	72	A	1900	5971	1.1	FT-2100-0	20	65	A	1500	
{5750	6.3	ET-7562-1	0	35	B	800	5975	6.3	EV-3102-0	28	86	A	4000	
{5750	6.3	ET-1602-7	20	90	A	6500	5977	6.3	DW-1805-3	32	86	A	4000	
{5751	12.6	EV-7608-0	12	58	A	1250	5987	6.3	DW-1205-0	74	71	A	1850	
{5751	12.6	EV-2103-0	12	58	A	1250	5995	6.3	ET-0105-0	0	55	D		Leads-1-3-4-5
{5755	12.6	EV-6807-3	11	31	A	750	{5998	6.3	HY-4506-2	56	92	A	8000	Triode No. 1
{5755	12.6	EV-3102-6	11	31	A	750	{5998	6.3	HY-1203-5	56	92	A	8000	Triode No. 2
5763	6.3	EV-9167-3	11	87	A	4500	6005	6.3	ET-1562-0	11	86	A	4100	
5784	6.3	DU-7126-5	12	76	A	2200	6012	6.3	HS-3501-8	*	94	F		Strikes at about 25
{5814	12.6	EV-7608-0	16	80	A	2775	{6021	6.3	DW-7805-0	25	78	A	2500	Triode No. 1
{5814	12.6	EV-2103-0	16	80	A	2775	{6021	6.3	DW-2104-0	25	78	A	2500	Triode No. 2
{5829	6.3	DV-0607-0	0	78	C		6028	20.0	ET-1562-0	24	65	A	1500	
{5829	6.3	DV-0102-0	0	78	C		6046	25.0	HS-5348-1	33	88	A	5200	
5840	6.3	DW-1574-0	19	78	A	2500	6050	1.1	ES-3100-0	28	60	A	1300	

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS	TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS
6051	1.1	DV-4120-0	39	0	B 600		6211	12.6	EV-7608-2	24	84	A 3600	Triode No. 1
6052	6.3	DW-0507-4	0	80	D	Plate No. 1	6211	12.6	EV-2103-7	24	84	A 3600	Triode No. 2
6052	6.3	DW-0102-4	0	80	D	Plate No. 2	6216	6.3	EV-2173-0	20	92	A 9000	
6053	25.0	DW-0507-4	0	80	D	Plate No. 1	6221	6.3	DW-1805-0	23	84	A 3500	
6053	25.0	DW-0102-4	0	80	D	Plate No. 2	6222	6.3	DW-1805-0	22	21	A 650	
6055	25.0	DW-1805-0	36	73	A 2000		6223	6.3	DW-1578-0	15	78	A 2500	
6056	25.0	DW-1572-0	15	75	B 2200		6225	6.3	DW-1572-0	11	82	A 3100	
6058	6.3	ET-0701-6	0	78	C	Diode No. 1	6245	6.3	DU-7126-5	24	65	A 1500	
6058	6.3	ET-0205-6	0	78	C	Diode No. 2	6247	6.3	DW-2805-0	11	73	A 2000	
6072	12.6	EV-7608-0	18	58	A 1250	Triode No. 1	6263	6.3	HS-3506-0	18	88	A 5000	USE NICKOX ADAPTER SA-3 CODE NO. 1096-721
6072	12.6	EV-2103-0	18	58	A 1250	Triode No. 2	6264	6.3	HS-3506-0	10	87	A 4600	USE NICKOX ADAPTER SA-3 CODE NO. 1096-721
6080	7.5	HY-4506-2	100	83	A 3400	Triode No. 1	6265	6.3	ET-1562-7	12	73	A 2000	
6080	7.5	HY-1203-5	100	83	A 3400	Triode No. 2	6286	1.4	ES-3100-0	42	62	A 1400	
6082	25.0	HY-4506-2	100	83	A 3400	Triode No. 1	6293	6.3	HS-5X31-0	24	90	A 6500	
6082	25.0	HY-1203-5	100	83	A 3400	Triode No. 2	6350	12.6	EV-8607-3	26	87	A 4600	Triode No. 1
6084	6.3	EV-9613-8	18	71	A 1850		6350	12.6	EV-3102-8	26	87	A 4600	Triode No. 2
6085	12.6	EV-7608-0	18	80	A 2700	Triode No. 1	6384	6.3	GY-7351-0	21	89	A 5400	Triode No. 1
6085	12.6	EV-2103-0	18	80	A 2700	Triode No. 2	6386	6.3	KR-7608-5	24	86	A 4000	Triode No. 1
6086	20.0	EV-2613-9	10	90	A 6500		6386	6.3	KR-3402-5	24	86	A 4000	Triode No. 2
6096	6.3	ET-1562-0	24	65	A 1500		6397	2.5	HR-8360-0	33	72	A 1950	
6097	6.3	ET-0701-6	0	78	C	Diode No. 1	6414	12.6	EV-7608-0	17	84	A 3500	Triode No. 1
6097	6.3	ET-0205-6	0	78	C	Diode No. 2	6414	12.6	EV-2103-0	17	84	A 3500	Triode No. 2
6098	6.3	GY-7351-0	21	89	A 5400		6417	12.6	EV-9167-3	11	87	A 4500	
6110	6.3	DW-0507-4	0	74	C	Diode No. 1	6418	1.4	DV-0204-1	0	0	C	OK ABOVE 300 ON 3000 SCALE
6110	6.3	DW-0102-4	0	74	C	Diode No. 2	6463	12.6	EV-8607-1	25	88	A 5200	Triode No. 1
6111	6.3	DW-7805-0	26	86	A 4000	Triode No. 1	6463	12.6	EV-3102-6	25	88	A 5200	Triode No. 2
6111	6.3	DW-2104-0	26	86	A 4000	Triode No. 2	6485	6.3	ET-1567-2	11	81	A 3000	
6112	6.3	DW-7805-0	20	65	A 1500	Triode No. 1	6519	1.4	DV-4210-0	0	0	C	OK OVER 200 ON 2000 SCALE
6112	6.3	DW-2104-0	20	65	A 1500	Triode No. 2	6520	7.5	HY-4506-2	100	79	A 2600	Triode No. 1
6134	6.3	HS-4865-3	11	81	A 3000		6520	7.5	HY-1203-5	100	79	A 2600	Triode No. 2
6135	6.3	ET-8107-0	25	75	A 2200		6526	1.1	DV-4120-0	20	61	B 1250	
6136	6.3	ET-1567-2	11	76	A 2300		6533	6.3	GX-2105-0	20	53	A 1100	
6137	6.3	HS-4865-3	12	73	A 2000		6540	6.3	DU-7126-5	24	65	A 1500	
6146	6.3	HS-5X31-8	45	88	A 5000		6611	1.4	DV-0204-1	0	0	C	OK ABOVE 300 ON 3000 SCALE
6148	6.3	DU-7126-5	24	65	A 1500		6612	1.4	DV-0204-1	0	0	C	
6152	6.3	EV-3102-0	28	86	A 4000		6659	OFF	AP-0105-0	0	40	G	Leads = 1-5
6159	25.0	HS-5X31-8	45	88	A 5000		6660	6.3	ET-1567-2	11	72	A 1900	
6186	6.3	ET-1562-0	11	78	A 2500		6661	6.3	ET-1562-7	12	73	A 2000	
6189	12.6	EV-7608-0	24	75	A 2200	Triode No. 1	6662	6.3	ET-1562-7	11	72	A 1900	
6189	12.6	EV-2103-0	24	75	A 2200	Triode No. 2	6663	6.3	ET-0701-6	0	78	C	Diode No. 1
6197	6.3	EV-2631-7	11	88	A 5000		6663	6.3	ET-0205-6	0	78	C	Diode No. 2
6201	12.6	EV-7608-0	11	82	A 3000	Triode No. 1	6664	6.3	ET-6107-0	11	81	A 3000	
6201	12.6	EV-2103-0	11	82	A 3000	Triode No. 2	6669	6.3	ET-1562-0	11	86	A 4100	
6202	6.3	ET-0807-1	0	25	D	Plate No. 1	6676	6.3	ET-1562-7	11	81	A 3000	
6202	6.3	ET-0107-6	0	25	D	Plate No. 2	6677	6.3	EV-2631-7	11	88	A 5000	
6203	6.3	EV-0907-1	0	40	D	Plate No. 1	6678	6.3	EV-2637-0	11	73	A 2000	Pent. Sect.
6203	6.3	EV-0107-9	0	40	D	Plate No. 2	6678	6.3	EV-9108-0	12	90	A 6200	Triode Sect.
6205	6.3	DW-1572-4	19	78	A 2500		6679	12.6	EV-7608-0	11	81	A 3000	Triode No. 1
6206	6.3	DW-1572-4	19	73	A 2000		6679	12.6	EV-2103-0	11	81	A 3000	Triode No. 2
							6680	12.6	EV-7608-0	24	75	A 2200	Triode No. 1
							6680	12.6	EV-2103-0	24	75	A 2200	Triode No. 2

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS	TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS
6681	12.6	EV-7608-0	12	58	A 1250	Triode No. 1	7060	12.6	EV-8679-0	9	84	A 3000	Pent. Sect.
6681	12.6	EV-2103-0	12	58	A 1250	Triode No. 2	7060	12.6	EV-2103-0	13	83	A 2800	Triode Sect.
6688	6.3	EV-2791-8	11	81	A 3000		7061	12.6	EV-3917-0	11	86	A 4100	
6690	6.3	DW-7508-0	22	78	A 2500	Triode No. 1	7119	12.6	EV-7906-0	24	94	A 10000	Triode No. 1
6690	6.3	DW-2104-0	22	78	A 2500	Triode No. 2	7119	12.6	EV-2103-0	24	94	A 10000	Triode No. 2
6754	6.3	EV-0907-0	0	80	D	Plate No. 1	7137	6.3	ET-6702-0	20	90	A 6000	
6754	6.3	EV-0103-0	0	80	D	Plate No. 2	7167	12.6	ET-1562-0	11	81	B 3000	
6788	6.3	DW-1572-0	13	41	A 900		7189	6.3	EV-2793-0	11	90	A 6000	
6814	6.3	DW-1805-0	24	87	A 4500		7199	6.3	EV-7236-0	7	82	A 2500	Pent. Sect.
6829	12.6	EV-7608-0	16	90	A 6700	Triode No. 1	7199	6.3	EV-9108-0	27	75	A 2100	Triode Sect.
6829	12.6	EV-2103-0	16	90	A 6700	Triode No. 2	7212	6.3	HS-5X31-8	45	88	A 5000	
6832	6.3	DW-7805-0	27	51	A 1050	Triode No. 1	7233	6.3	EV-2908-0	0	49	C	OK ABOVE DIODES OK
6832	6.3	DW-2104-0	27	51	A 1050	Triode No. 2	7239	6.3	EV-1X69-7	28	73	A 2100	
6872	6.3	DU-7126-5	14	76	A 2300		7247	12.6	EV-7608-0	12	58	A 1250	Triode No. 1
6883	12.6	HS-5X31-8	45	88	A 5000		7247	12.6	EV-2103-0	25	75	A 2200	Triode No. 2
6887	6.3	ET-0701-0	0	83	C	Diode No. 1	7258	12.6	EV-8679-1	10	85	A 3700	Pent. Sect.
6887	6.3	ET-0205-0	0	83	C	Diode No. 2	7258	12.6	EV-2173-6	19	87	A 4400	Triode Sect.
6889	6.3	GY-7X51-0	21	89	A 5400		7308	6.3	EV-7608-0	24	89	A 5500	Triode No. 1
6900	12.6	EV-7906-1	26	91	A 7500	Triode No. 1	7308	6.3	EV-2103-0	24	89	A 5500	Triode No. 2
6900	12.6	EV-2103-9	26	91	A 7500	Triode No. 2	7316	12.6	EV-7608-0	24	75	A 2200	Triode No. 1
6919	6.3	ET-0701-6	0	78	C	Diode No. 1	7316	12.6	EV-2103-0	24	75	A 2200	Triode No. 2
6919	6.3	ET-0205-6	0	78	C	Diode No. 2	7355	6.3	HS-6385-0	12	91	A 7600	
6922	6.3	EV-7608-0	24	89	A 5500	Triode No. 1	7357	25.0	HS-5X31-8	45	88	A 5000	
6922	6.3	EV-2103-0	24	89	A 5500	Triode No. 2	7358	6.3	HS-5X31-8	23	91	A 7000	
6928	6.3	ET-1562-0	11	86	A 4100		7360	6.3	EV-3621-9	18	50	A 1000	CONNECT PIN 1 TO PIN 4 AND PIN 6 TO PIN 7 OR LOCAL SOCKET
6943	6.3	DW-1572-4	14	76	A 2400		7370	20.0	FY-7906-0	26	91	A 7500	Triode No. 1
6944	6.3	DW-1572-4	13	76	A 2300		7370	20.0	JU-2103-0	26	91	A 7500	Triode No. 2
6945	6.3	DW-1572-0	41	83	A 3200		7408	6.3	HS-5348-1	13	86	A 4100	
6946	6.3	DW-1805-0	24	85	A 3800		7543	6.3	ET-1567-2	11	76	A 2300	
6947	6.3	DW-7805-0	20	79	A 2600	Triode No. 1	7551	12.6	EV-2631-7	17	90	A 6000	
6947	6.3	DW-2104-0	20	79	A 2600	Triode No. 2	7558	6.3	EV-2631-7	17	90	A 6000	
6948	6.3	DW-7805-0	18	68	A 1650	Triode No. 1	7581	6.3	HS-5348-0	17	88	A 6000	
6948	6.3	DW-2104-0	18	68	A 1650	Triode No. 2	7586†	6.3	DR-4208-0	28	78	A 2500	USE ADAPTER SA-3, 1952-127, NOTE 3
6973	6.3	EV-3917-0	10	85	A 4000		Model 6000 A:						
7025	12.6	EV-7608-0	12	58	A 1250	Triode No. 1	7586	6.3	13-4208-0	28	78	A 2500	
7025	12.6	EV-2103-0	12	58	A 1250	Triode No. 2	7587†	6.3	DR-4X28-0	11	85	B 3800	USE ADAPTER SA-3, 1952-127, NOTE 3
7027	6.3	HS-5318-0	17	88	A 5000		Model 6000 A:						
7036	6.3	ET-1562-7	11	42	B 900	Grid No. 1	7587	6.3	13-4528-0	11	85	B 3800	
7036	6.3	ET-7562-1	11	35	B 800	Grid No. 3	"Do not use tester cap connection. Jumper plate cap to Pin 5 octal socket."						
7044	12.6	EV-7906-0	26	90	A 6000	Triode No. 1	7591	6.3	HS-6345-0	10	89	A 5100	
7044	12.6	EV-2103-0	26	90	A 6000	Triode No. 2	7683	6.3	EV-1382-0	10	50	A 1250	
7054	12.6	EV-2781-3	11	87	A 4500		7687	6.3	EV-2637-0	10	82	A 3200	Pent. Sect.
7055	12.6	ET-0701-6	0	78	C	Diode No. 1	7687	6.3	EV-9108-0	29	79	A 2100	Triode Sect.
7055	12.6	ET-0205-6	0	78	C	Diode No. 2	7695	50.0	EV-6917-0	30	94	A 9000	
7056	12.6	ET-1562-7	11	81	A 3000		7701	12.6	EV-2691-0	10	83	A 3300	
7057	12.6	EV-7608-9	16	87	A 4500	Triode No. 1	7716	12.6	EV-7986-0	10	87	A 4500	Pent. Sect.
7057	12.6	EV-2103-9	16	87	A 4500	Triode No. 2	7716	12.6	EV-2301-0	10	69	A 1700	Triode Sect.
7058	12.6	EV-7608-0	12	58	A 1250	Triode No. 1	7717	6.3	ET-1562-0	11	81	B 3000	
7058	12.6	EV-2103-0	12	58	A 1250	Triode No. 2	7719	12.6	EV-2103-0	29	84	A 3500	
7059	12.6	EV-2637-0	11	73	A 2000	Pent. Sect.							
7059	12.6	EV-9108-0	12	90	A 6200	Triode Sect.							

TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS	TUBE TYPE	FIL.	SELECTORS	BIAS	SHUNT	FUNCT. AND MUT. COND.	NOTATIONS
7724	12.6	EV-8907-0	10	15	A 600	Triode Sect.	8058†	6.3	DR-5X02-0	19	85	A 3800	JUMPER SHELL TO PIN 5 OF OCTAL SOCKET USE ADAPTER SA-3, 1850-122, NOTE 3
7724	12.6	EV-0601-0	0	80	C	Diode No. 1	Model 6000 A:						
7724	12.6	EV-0203-0	0	80	C	Diode No. 2	8058	6.3	13-5102-0	19	85	A 3800	
7728	12.6	EV-7608-0	11	81	A 3000	Triode No. 1	"Do not use tester cap connector. Jumper tube cap to Pin 1 of octal socket. Jumper shell to Pin 5 of novar socket."						
7728	12.6	EV-2103-0	11	81	A 3000	Triode No. 2	8064	25.0	DW-1578-0	15	75	A 2150	
7729	12.6	EV-7608-0	12	58	A 1250	Triode No. 1	8068	6.3	HS-5X83-0	15	90	A 7000	
7729	12.6	EV-2103-0	12	58	A 1250	Triode No. 2	8077	12.6	EV-2781-3	11	87	A 4500	
7730	12.8	EV-7608-0	24	75	A 2200	Triode No. 1	8084	12.6	DU-1562-7	18	81	A 3000	
7730	12.6	EV-2103-0	24	75	A 2200	Triode No. 2	8096	6.3	GX-2105-0	20	53	A 1100	
7731	6.3	EV-2637-0	11	73	A 2000	Pent. Sect.	8102	12.6	EV-9678-0	11	81	A 3000	Pent. Sect.
7731	6.3	EV-9108-0	12	90	A 6200	Triode Sect.	8102	12.6	EV-3102-0	21	85	A 3900	Triode Sect.
7732	6.3	ET-1562-7	11	81	A 3000		8106	12.6	EV-7189-0	16	87	A 4450	
7733	12.6	EV-2781-3	11	87	A 4500		8113	6.3	ET-1567-0	22	82	A 2600	
7734	6.3	EV-8917-0	14	72	A 1850	Pent. Sect.	8136	6.3	ET-1562-7	12	83	A 3300	
7734	6.3	EV-3602-0	64	86	A 4700	Triode Sect.	8149†	12.6	B3-X789-0	44	88	A 4500	
7737	6.3	EV-2791-8	11	81	A 3000		8150†	12.6	B3-X386-0	44	88	A 4500	CAP-P. JUMPER FROM PIN 3 TO CAP
7738	6.3	ET-2105-0	13	89	A 5500		8156†	12.6	B3-X376-0	25	90	A 5000	
7754	6.3	EV-6917-0	30	94	A 9000		8185	6.3	JR-2306-0	25	87	A 4300	
7757	6.3	DV-6X78-0	11	86	A 4100		8186	25.0	JR-2306-0	25	87	A 4300	
7759	25.0	DW-7805-0	25	78	A 2500	Triode No. 1	8203†	6.3	DR-4208-0	29	78	A 2400	USE ADAPTER SA-3, 1850-122, NOTE 3
7759	25.0	DW-2104-0	25	78	A 2500	Triode No. 2	Model 6000 A:						
7760	25.0	DW-7805-0	36	73	A 2000	Triode No. 1	8203	6.3	13-4208-0	29	78	A 2400	
7760	25.0	DW-2104-0	36	73	A 2000	Triode No. 2	8236	6.3	HS-1X43-0	43	92	A 7800	
7761	25.0	DW-1572-0	15	87	A 4700		8298	6.3	HS-5X31-8	23	90	A 8000	
7762	25.0	DW-1572-0	40	86	A 4200		8327	6.3	EV-2793-0	23	92	A 5500	
7802	6.3	HY-4506-2	45	93	A 9500	Triode No. 1	8334	6.3	ET-6705-0	14	89	A 6000	
7802	6.3	HY-1203-5	45	93	A 9500	Triode No. 2	8393†	12.6	DR-4208-0	27	85	A 3700	USE ADAPTER SA-3, 1850-122, NOTE 3
7803	6.3	EV-7608-0	22	91	A 7000	Triode No. 1	Model 6000 A:						
7803	6.3	EV-2103-0	22	91	A 7000	Triode No. 2	8393	12.6	13-4208-0	27	85	A 3700	
7861	12.6	KR-7608-0	17	88	A 5000	Triode No. 1	8417	6.3	HS-5348-0	10	93	A 10000	
7861	12.6	KR-3402-0	17	88	A 5000	Triode No. 2	8425	6.3	ET-1567-2	10	80	A 2900	
7867	6.3	HS-5X83-0	23	93	B 9000		8426	12.6	ET-1587-2	10	80	A 2900	
7868†	6.3	EV-2973-0	18	89	A 5200	USE ADAPTER SA-4, 1850-122, NOTE 3	8431	12.6	EV-7608-0	18	93	A 5500	Triode No. 1
Model 6000 A:		No Adapter Required.					8431	12.6	EV-2103-0	18	93	A 5500	Triode No. 2
7889	25.0	DW-7805-0	20	65	A 1500	Triode No. 1	8445	6.3	EV-2637-0	10	84	A 3500	Pent. Sect.
7889	25.0	DW-2104-0	20	65	A 1500	Triode No. 2	8445	6.3	EV-9108-0	20	84	A 3500	Triode Sect.
7895†	6.3	DR-4208-0	22	82	A 3200	USE ADAPTER SA-3, 1850-122, NOTE 3	8446	6.3	EV-9678-0	10	82	A 3000	Pent. Sect.
Model 6000 A:							8446	6.3	EV-1203-0	14	87	A 4000	Triode Sect.
7895	6.3	13-4208-0	22	82	A 3200		8489	6.3	EV-8679-0	10	84	A 3600	Pent. Sect.
7898	6.3	EV-7608-0	11	86	A 4000	Triode No. 1	8489	6.3	EV-2103-0	20	85	A 3800	Triode Sect.
7898	6.3	EV-2103-0	11	86	A 4000	Triode No. 2	8532	6.3	ET-1702-0	20	90	A 6000	
7905	6.3	KR-2680-7	10	88	A 4650		8552	12.6	HS-5X31-8	23	91	A 7000	
7984†	12.6	B3-X3A9-0	42	87	A 4050		8628†	6.3	BT-4208-0	15	70	A 1900	USE ADAPTER SA-3, 1850-122, NOTE 3
7985	6.3	ER-3782-6	13	82	A 3100		Model 6000 A:						
8032	12.6	HS-5X31-8	45	88	A 5000		8628	6.3	13-4208-0	15	70	A 1900	
8056†	6.3	DR-0208-4	0	68	C	OK ABOVE 1300 OH 2000 SCALE USE ADAPTER SA-3, 1850-122, NOTE 3							
Model 6000 A:													
8056	6.3	13-0208-4	0	68	C	OK ABOVE 1300 OH 2000 SCALE							



www.StevenJohnson.com

**Antique Technolgy, Tube Radios and Test Equipment
Vintage Schematics, and Publications**

Steve's Antique Technology