

MODEL 3716

L-1 CHASSIS			PARTS LIST --- L-1 CHASSIS			L-1 CHASSIS (cont)		
Item No.	Part No.	Description	Item No.	Part No.	Description	Item No.	Part No.	Description
1	W-37922	Dial Light Bulb	80	G3-42584	Tuning Indicator Socket	1	G6-31618	Choke-Bass & Mezzo P.P.
	W-40570	Dial Light Shield	82	W-41029-B	Phantom Cont. Sw.			P. Input
2	W-41187	Auto-Expressicator Tube	83	41235-A	Band Selector Sw.	2	G15-29535	Choke-Treble 1st A-F
3	G94-32000	Ant. Coil B.C.B.	84	G27-26719	Ant. & Gnd. Term. Assy.			Input
4	G108-32000	Ant. Coil Pol. B.	85	W-41287	AFC Bias Cont., 300 ohm	3	G65-24628	Choke-Treble P.P. Input
5	G107-32000	Ant. Coil H.F.B.			1 w.	4	G7-31618	Choke-Micro. P.P. Input
6	W-42739	1st I.F. Assy.	86	B-42295-A	Fidelity Line Sw.	5	W-42736	40 mf. 300 v. Cond.
7	W-42740	2nd I.F. Assy.	87	G3-37995	A-F Driver Trans.	6	G2-34002	100mmf. Cond.
8	G132-32004	A.F.C.I.F. Assy.	88	G62-24628	Output Trans.	7	G6-34002	25mmf. Cond.
9	G97-32002	Osc. Coil B.C.B.	89	G3-37900	Power Trans. 60 cy. 110 v	8	G5-34002	50mmf. Cond.
10	G96-32002	Osc. Coil Pol. B.	91Z	41375	3 meg. Tap 3 meg. Vol.	9	G1-34002	250mmf. Cond.
11	G95-32002	Osc. Coil H.F.B.			Cont.	10	W-25435	.003 mf. 400 v. Cond.
12	G68-32001	R.F. Coil B.C.B.	91Y		1 meg. Vol. Cont.	11	W-3575-B	.008 mf. 400 v. Cond.
13	G75-32001	R.F. Coil Pol. B.	92	W-42419	Neon Tuning Indicator	12	W-36931	.2 mf. 25 v. Cond.
14	G74-32001	R.F. Coil H.F.B.			Tube	13	W-22688	.1 mf. 400 v. Cond.
15	W-42738	50 mf. 25 v. Cond.	97	21237-A	60,000 ohm 1 w. Res.	14	W-29910-A	.25 mf. 200 v. Cond.
16	W-42737	35 mf. 400 v. Cond.	98	G37-26719	Phono. Term. Assy,	15	W-31935	.25 mf. 300 v. Cond.
17	W-42736	40 mf. 300 v. Cond.		C-43041	Escutcheon	16	W-31404	.5 mf. 300 v. Cond.
18	G18-34000	5600 mmf. Cond.		C-43043	Lens, Escutcheon	17	42904	Power Cord & Plug
19	G5-34002	.00005 mf. 200 v. Cond.		43042	Escutcheon Rubber Mtg.	18	W-43069	Microphone (complete)
21	G2-34002	.0001 mf. 200 v. Cond.		W-43230	Knob (2 req.)	19	B-42957	Relay S.P.D.T.
22	G6-34002	.000025 mf. 200 v. Cond.		W-43231	Knob (3 req.)	20	36317	10,000 ohm 1 w. Res.
23	G3-34002	.0005 mf. 200 v. Cond.		6WK	Cabinet	21	4921-C	10,000 ohm 1 w. Res.
24	W-35758	.008 mf. 400 v. Cond.		D-30	Screws- Escutcheon Mtg.	22	27121	5,000 ohm 1 w. Res.
25	W-41461	.0014 mf. 200 v. Cond.	99	42902	Power Cord & Plug (short)	23	40757	50,000 ohm 1 w. Res.
26	W-30805	.01 mf. 400 v. Cond.	100	MG73-42708	"AFIP" Cable Assy.	24	35600	100,000 ohm 1 w. Res.
27	6705	3500 ohm 1 w. Res.	102	MG74-42708	Field Cable to 650 DT 4	25	35601	300,000 ohm 1 w. Res.
28	W-36541	.02 mf. 160 v. Cond.			Speaker	26	36322	500,000 ohm 1 w. Res.
29	W-28621	.02 mf. 200 v. Cond.	L-2 CHASSIS					
30	W-41209	.048 mf. 200 v. Cond.	1	G6-31618	Choke-Bass & Mezzo P.P.	27	W-30539	26.7 ohm 2 1/2 w. Res.
31	W-35936	.05 mf. 200 v. Cond.				28	W-23012-A	40 ohm 3/4 w. Flex. Res.
32	W-32380	.05 mf. 200 v. Cond.	2	G15-29535	Choke-Treble 1st A-F	29	W-26049	450 ohm 3 w. Flex. Res.
32	W-27216	.05 mf. 200 v. Cond.				30	W-25291	500 ohm 1 1/2 w. Flex. Res.
34	W-32780-B	.05 mf. 400 v. Cond.				31	W-27503	1400 ohm 3/4 w. Flex.
35	W-28904	.004 mf. 200 v. Cond.						Res.
36	W-22688	.1 mf. 400 v. Cond.				32	W-26422	1,000 ohm 4 w. Flex. Res.
37	W-42554	.12 mf. 160 v. Cond.				33	W-32337	20 ohm 2 w. Candohm Res.
38	41218	B.C. Osc. Series Tr.				34	252DT4-J	Speaker (tweeter)
		Pol. Osc. Series Tr.				35	650DT4-M	Speaker (12 inch 1300
38	W-37891	3 Sec. Shunt Tr. Cond.						ohm field)
40	W-35951	3 Sec. Shunt Tr. Cond.				36	651DT4-M	Speaker (12 inch 525 ohm
41	W-42741-A	3 Gang Var. Tuning Cond.						field)
	MG8-42708	Dial Dr. Assy. Complete				37	953GT4-J	Speaker (18 inch)
	D-42871	Dial Glass (Calibrated)				38	W-42956	S.P.D.T. Sw.
	D-42754	Drive Unit Only				43	G1-42980	Socket L.P.S. (male)
	C-42729	Dial Mask (Pa. Backing)				44	G2-42980	Socket H.P.S. (male)
	W-42730	Hand - Long Dial				45	G98-28807	Socket A.F.I.P.
	W-42731	Hand - Short Dial				46	G99-28807	Socket M.I.P.
	W-40486	Screw - Hand Mtg.				47	G100-28807	Socket 9GT
	E-13761	Mystic Hand Flipper				48	G101-28807	Socket 6DT
	E-13762	Fidelity Flipper				49	G102-28807	Socket 2DT
	W-43080	Flipper Cont. Cable				50	G1-43000	Plug M.I.P. 4 Prong
		Assy. (4 req.)				51	G2-43000	Plug 9GT 5 Prong
	W-42308-A	Flipper Cont. Cable				52	G3-43000	Plug 6DT 6 Prong
		Pulley				53	G4-43000	Plug 2 DT 7 Prong
	40638	Band Indicator Cont.				54	G8-31618	Input Trans.
		Cable				55	G9-31618	Bass Output Trans.
	40537	Flex. Coupling Unit				56	G66-24628	Mezzo Output Trans.
42	42901	Power Cord & Plug (long)				57	G67-24628	Treble Output Trans.
43	G2-37918	Speaker Cable				58	G68-24628	Mike Output Trans.
44	36760	20,000 ohm 1 w. Res.				59	G47-25669	Filament Trans.
45	33390	30,000 ohm 1 w. Res.						
46	36761	40,000 ohm 1 w. Res.						
47	34019	75,000 ohm 1 w. Res.						
48	35600	1,000 ohm 1 w. Res.						
49	35929	150,000 ohm 1 w. Res.						
50	35930	200,000 ohm 1 w. Res.						
51	35601	3,000 ohm 1 w. Res.						
52	36322	5,000 ohm 1 w. Res.						
53	38623	750,000 Ohm 1 w. Res.						
54	35602	1 meg. 1 w. Res.						
55	36176	1.3 meg. 1 w. Res.						
56	35927	2 meg. 1 w. Res.						
57	36688	3 meg. 1 w. Res.						
58	G101-34003	R-F Neutralizing Cond.						
59	W-23012-A	40 ohm 3/4 w. Flex. Res.						
60	W-35467	220 ohm 1 w. Flex. Res.						
61	W-25937	275 ohm 1 w. Flex. Res.						
62	W-28589	350 ohm 1 w. Flex. Res.						
63	W-28106	500 ohm 1 w. Flex. Res.						
64	W-21452	1100 ohm 3/4 w. Flex.						
		Res.						
65	W-23013	2,000 ohm 1 1/2 w. Flex.						
		Res.						
66	W-23907	750 ohm 1 1/2 w. Flex. Res.						
67	4921-C	10,000 ohm 1 w. Res.						
68	W-42418	30,000 ohm 4 w. Res.						
69	36952	30,000 ohm 1 w. Res.						
70	W-41966	4,000-1,000-3,000-200						
		ohm Candohm Res.						
79	G167-36400	Auto Exp. Socket						