

TUBE COMPLEMENT:

- (V1) FM RF and 1st I-F Amplifier ... 6BJ6
- (V2) Oscillator-Converter ... 12BE6
- (V3) I-F Amplifier ... 6BJ6
- (V4) Limiter ... 6BH6
- (V5) FM Discriminator, AM Detector, and 1st Audio Amplifier ... 19T8
- (V6) Power Output ... 35B5
- (V7) Rectifier ... 35W4
- (11) Mazda #47, 6-8 v.

ELECTRICAL:

- Voltage ... 105-125 volts A-c or D-c
- Frequency ... 50-60 cps
- Wattage ... 33 watts

TUNING BAND:

- AM ... 540-1600 kc
- FM ... 88-108 mc

INTERMEDIATE FREQUENCIES:

- AM ... 455 kc
- FM ... 10.7 mc


POWER OUTPUT (117 volts line)

- Undistorted ... 1.1 watts
- Maximum ... 1.8 watts

LOUDSPEAKER:

212—Wood

210—Mahogany



211—Ivory

