



# PARTS LIST AND DESCRIPTIONS TUBES (GENERAL ELECTRIC, PENNSYLVANIA)

ITEM No.	USE	TYPE	NOTES	ITEM No.	USE	TYPE	NOTES
V1	RF Amplifier	IU4		V4	Del. - AVC - AF Amp.	IU5	
V2	Converter	IL6		V5	Output	3V4	
V3	IF Amplifier	IU4					

## ELECTROLYTIC CAPACITORS

ITEM No.	RATING	REPLACEMENT DATA			
		CAP. VOLT.	ZENITH PART No.	AEROVOX PART No.	CORNELL DUBILIER PART No.
CLA	.60	150	22-1741	AFH4-23	D0300
B	420	150			
C	40	150			
D	200	10			
C2	12	150	22-2056	PRS150V12	BBR12-150

## FIXED CAPACITORS

Capacity values given in the rating column are in mfd. for Paper Capacitors, and in mmfd. for Mica and Ceramic Capacitors.

ITEM No.	RATING	REPLACEMENT DATA										NOTES
		CAP. VOLT	ZENITH PART No.	AEROVOX PART No.	CENTRALAB PART No.	CORNELL DUBILIER PART No.	ERIE PART No.	MALLORY PART No.	PYRAMID PART No.	SANGAMO PART No.	SPRAGUE PART No.	
C3	470		22-6	BPD-00047	DD-471	BYA10T47	ED-470	UC-5347	5GA-T47			
C4	4700		22-4	BPD-0047	DD-472	BYA10D47	ED-0047	UC-5247	5HK-D47			
C5	15		22-2329	NP0-SI 15	TCZ-15	CTA6Q15C	TCO-15	ZT-5425	5TCC-Q15	NP0		
C6	25		22-1392	NP0-SI 25	TCZ-25	CTA6Q25C	TCO-25	ZT-545	5TCC-Q25	NP0		
C7	50		22-1761	NP0-SI 50	TCZ-50	CTA6Q50C	TCO-50		5TCC-Q5	NP0		
C8A			22-2934									
B	.047		22-1775	BPD-05	DF-503	CUB4547	ED-470	GEM-4147	4TM-S47			
C9	270	400	22-2058	I468-00027	D6-271	5W5T27	ED-270	UC-5327	IFM-327			
C10	270		22-2058	BPD-00027	DD-271	L10T27	ED-270	UC-5327	5GA-T27			
C11	1000		22-2218	SI 1000	D6-102	L76D1	GP-1000	UC-521	5GA-D1			
C12	1000		22-2284									
C13A			22-1390	I468-00047	DD-471	5W5T47	ED-470	UC-5347	IFM-347			
B	470		22-2126									
C14	250		22-2279	NP0-SI 120	TCZ-120	CTA6T12C	TCO-120		5TCC-T12	NP0		
C15	120		22-2280	NP0-SI 120	TCZ-120	CTA6T12C	TCO-120		5TCC-T12	NP0		
C16	120		22-2282	NP0-SI 10	TCZ-10	CTA6Q10C	TCO-10	ZT-541	5TCC-Q1	NP0		
C17	120		22-1953	NP0-SI 120	TCZ-120	CTA6T12C	TCO-120		5TCC-T12	NP0		
C18	10		22-2279									
C19	120		22-1433									
C20	2750		22-2935									
C21	4000		22-2933									
C22	4000											
C23A												
B	10000		22-3	BPD-01	DD-103	BYA6S1	ED-01	DC511	5HK-S1			
C24	3300		22-11	BPD-0033	DD-332	BYA10D33	ED-0033	UC-5233	5GA-D33			
C25	.022	200	22-2071	BPD-02	DD-203	CUB2S22	ED-02	GEM-2122	2TM-S22			
C26	10000		22-3	BPD-01	DD-103	BYA6S1	ED-01	DC511	5HK-S1			
C27	50		22-1674	SI 50	D6-500	LT6Q5	GP-50	UC-545	5GA-Q5			
C28	.022	400	22-2072	BPD-02	DD-203	CUB4S22	ED-02	GEM-4122	4TM-S22			
C29	10000		22-3	BPD-01	DD-103	BYA6S1	ED-01	DC511	5HK-S1			
C30	1000		22-17	BPD-001	DD-102	BYA6D1	ED-1000	DC521	5HK-D1			
C31	.022	200	22-2071	BPD-02	DD-203	CUB2S22	ED-02	GEM-2122	2TM-S22			
C32	.022	400	22-2072	BPD-02	DD-203	CUB4S22	ED-02	GEM-4122	4TM-S22			
C33	.047	200	22-1778	BPD-05	DD-503	CUB2S47	ED-02	GEM-2147	2TM-S47			
C34	10000		22-3	BPD-01	DD-103	BYA6S1	ED-01	DC511	5HK-S1			
C35	.01	600	22-1779	BPD-01	DD-103	CUB6S1	GP-10000	GEM-611	6TM-S1			
C36	.047	600	22-2569	BPD-05	DF-503	CUB6S47	GEM-6147	GEM-6147	6TM-S47			
C37	.047	400	22-1775	BPD-05	DF-503	CUB4S47	GEM-4147	GEM-4147	4TM-S47			
C38	.047	200	22-1777	P288N-1	DF-104	CUB2P1	GEM-201	GEM-201	2TM-P1			
C39	1		22-3	BPD-01	DD-103	BYA6S1	ED-01	DC511	5HK-S1			
C40	10000		22-3	BPD-01	DD-103	BYA6S1	ED-01	DC511	5HK-S1			
C41	10000		22-3	BPD-01	DD-103	BYA6S1	ED-01	DC511	5HK-S1			

① Not used in some versions

# PARTS LIST AND DESCRIPTIONS (Continued)

## COILS (RF-IF)

ITEM No.	USE	REPLACEMENT DATA				NOTES
		ZENITH PART No.	MEISSNER PART No.	MERIT PART No.	MILLER PART No.	
L1	Loop Stick	S-22865				(Complete) Model A600 (Complete) Model A600L 42 Microhenries
L2	Loop Stick	S-22892	19-7047			
L3	Ant. Loading	S-23857				4-9MC
L4	Ant. Coupling	S-23858				2-4MC
L5	Ant. Coll	S-40870				17.4-18.2MC
L6	Ant. Coll	S-23856				14.8-15.6MC
L7	Ant. Coll	S-17718				11.4-12.2MC
L8	Ant. Coll	S-17719				9.3-9.9MC
L9	Ant. Coll	S-17720				540-1600KC
L10	RF Coll	S-17721	14-1072	BC-382	72-RF	4-9MC
L11	RF Coll	S-20844				2-4MC
L12	RF Coll	S-40872				17.4-18.2MC
L13	RF Coll	S-23856				14.8-15.6MC
L14	RF Coll	S-17714				11.4-12.2MC
L15	RF Coll	S-17715				9.3-9.9MC
L16	RF Coll	S-17716				540-1600KC
L17	RF Coll	S-17717				4-9MC
L18	Osc. Coll	S-17709				2-4MC
L19	Osc. Coll	S-40871				17.4-18.2MC
L20	Osc. Coll	S-17731				14.8-15.6MC
L21	Osc. Coll	S-17726				11.4-12.2MC
L22	Osc. Coll	S-40860				9.3-9.9MC
L23	Osc. Coll	S-17728				4 Microhenries
L24	Osc. Coll	S-17729				
L25	Osc. Coupling	S-14403	19-1003	BC-564	4008	
L26	Input IF	95-1148	16-6758	BC-352	12-C1	
		95-1149	16-6770	BC-355	12-C6	

\* Use adapter plate.

① Drill mounting hole.

## SELENIUM RECTIFIER

ITEM No.	RATING	REPLACEMENT DATA			NOTES
		FEDERAL PART No.	INTERNATIONAL PART No.	SARKES TARZIAN PART No.	
M1	.063	1101A	RS100	100A	① Used in 220V adapter
M2		212-13	212-9		

## BATTERIES

ITEM No.	VOLTAGE	ZENITH PART No.	REPLACEMENT DATA			NOTES
			BURGESS "A-B" Pack	EVEREADY "A-B" Pack	MALLORY "A-B" Pack	
M3	"A" 9V "B" 90V	Z985X	G6B60	752	A-400	RAY-O-VAC "A-B" Pack AB 995

## BATTERIES

ITEM No.	VOLTAGE	ZENITH PART No.	REPLACEMENT DATA			NOTES
			BURGESS "A" "B"	EVEREADY "A" "B"	MALLORY "A" "B"	
M4	1.5V	Z1	8R	1052P	1052P	RAY-O-VAC "A" "B" 23 Note 1

Note 1. Used for dial light power.

# PARTS LIST AND DESCRIPTIONS (Continued)

## CONTROLS

ITEM No.	RATING		REPLACEMENT DATA				INSTALLATION NOTES	
	RESISTANCE	WATTS	ZENITH PART No.	CENTRALAB PART No.	CLAROSTAT PART No.	IRC PART No.		MALLOY PART No.
R1A B C	1Meg Shalt Switch	1/2	63-2276	B-69 Not Req. KB-2	A47-1Meg-S KSS-3 SWE-20	Q11-137 Not Req. 76-2	U54 Not Req. US-27	Volume

## RESISTORS

All wattages 1/2 watt, or less, unless otherwise listed.

ITEM No.	RATING		ZENITH PART No.	NOTES	ITEM No.	RATING		ZENITH PART No.	NOTES
	OHMS	WATT				OHMS	WATT		
R2	4700Ω		63-1814		R20	2.2Meg		63-1926	
R3	120Ω		63-1747		R21	10Meg		63-1954	
R4	10Ω		63-1701		R22	15Meg		63-1961	
R5	1Meg		63-1912		R23	4.7Meg		63-1940	
R6	3300Ω		63-1807		R24	1Meg		63-1912	
R7	150Ω		63-1750		R25	1Meg		63-1912	
R8	68K		63-1863		R26	270Ω		63-1761	
R9	1Meg		63-1912		R27	680Ω		63-1778	
R10	100K		63-1869		R28	1500Ω		63-1792	
R11	100Ω		63-1743		R29	100K		63-1869	
R12	2.2Meg		63-1926		R30	18K		63-1838	
R13	5.6Meg		63-1943		R31	27K		63-1845	
R14	4.7Meg		63-1840		R32	330K		63-1891	
R15	1000Ω		63-1785		R33	100Ω		63-1744	
R16	120Ω		63-1747		R34	560Ω		63-1775	
R17	10Meg		63-1954		R35	700Ω	4	63-2930	
R18	1Meg		63-1912		R36	130Ω	3	63-2839	
R19	47K								

# PARTS LIST AND DESCRIPTIONS (Continued)

## MISCELLANEOUS

ITEM No.	PART NAME	ZENITH PART No.	NOTES
M5	Dial Light	100-171	#222
M6	Tuning Gang	22-2520	3 Gang (Ant. 16-462MMF, RF 16-462MMF, Osc. 16-462MMF)
M7	Switch	85-542	Dial Light (Slide Type SP), Model A600
M8	Switch	85-550	Dial Light (Slide Type SP), Model A600L
M9	Switch	85-520	Power Change Over (Slide Type)
M10	Switch	85-543	Power Change Over (Slide Type) (Alternate)
M11	Switch	S-40856	Bandswitch Brkt. & Coil Assy. (Includes Bandswitch Part #85-502)
	Switch	85-495	Photo-Radio (Slide Type)
	Switch	85-503	Tone

## CABINETS & CABINET PARTS

(When Ordering Cabinets & Cabinet Parts, Specify Model, Chassis & Color)

NAME	PART NO.	DESCRIPTION
Knob	46-912	Bandswitch, (7 used) Model A600
Knob	46-1288	Bandswitch, (7 used) Model A600L
Knob	46-913	Tuning, Model A600
Knob	46-1289	Tuning, Model A600L
Knob	46-1242	Volume, Model A600
Knob	46-1290	Volume, Model A600L
Dial Scale	26-575	Chassis 6A40
Dial Scale	26-576	Chassis 6A41
Dial Pointer	59-300	Telescoping Assy., Model A600
Antenna	S-15802	Telescoping Assy., Model A600L
Antenna	S-21433	Model A600
Cabinet	14-1633	Model A600L
Cabinet	14-1675	Model A600L

## TRANSFORMER (AUDIO OUTPUT)

ITEM No.	IMPEDANCE		REPLACEMENT DATA				NOTES		
	PRI.	SEC.1	ZENITH PART No.	Halderson PART No.	Merit PART No.	Stancor PART No.		Thorderson PART No.	Triad PART No.
			Turns Ratio						
T1	7000Ω	3-4Ω	95-1369						

## SPEAKER

ITEM No.	TYPE		REPLACEMENT DATA		NOTES
	SIZE	V. C. IMP.	ZENITH PART No.	QUAM PART No.	
SP1	5 1/4"	PM 3-4Ω	49-748 ①	52A21	① Part #S-22197 Includes speaker & T1