




MINIATURE VOLTAGE STABILISERS SINGLE GAP


QS75/20
QS95/10
QS150/15
NOVEMBER, 1954

The **QS75/20** is a commercial equivalent of **CV284**.
The **QS95/10** is a commercial equivalent of **CV286**.
The **QS150/15** is a commercial equivalent of **CV287**.

BASE CONNECTIONS AND TUBE DIMENSIONS



QS75/20



QS95/10 and QS150/15

View from underside of bases.

Base : B7G
Bulb : Tubular

Overall length : 54 mm.
Seated length : 47.6 mm.
Max. diameter : 19 mm.

RATINGS

	QS75/20	QS95/10	QS150/15	
V _{ign} (a-k)	110	110	177	V
V _{stab}	*75 ± 5	†95 ± 5	*150 ± 5	V
V _{ign} (ign-k)	—	150	240	V
I _{tube} (max)	20	10	15	mA
I _{tube} (min)	2	2	2	mA
R _{ign}	—	0.25	0.25	MΩ
Regulation				
(I _{tube} min.-max.)	6	5	5	V
Stability {	(100 hr. period) ± 2	± 3	± 1	%
(1000 hr. period) ± 2	± 2	± 7	± 1.5	
* At I _{tube} = 10 mA.		† At I _{tube} = 5 mA.		

OPERATION

The stabilisers require an ignition voltage greater than the stabilised voltage, and the supply should be not less than one and a half times the stabilised voltage. The ignition voltage must be applied to the tube through a series resistor to absorb the excess voltage after ignition and prevent a heavy discharge current through the tube. When calculating the value of series resistor, an ignition current of approximately 4 mA should be allowed in addition to the load current.

Types QS95/10 and QS150/15 are fitted with ignition electrodes to facilitate ignition when a heavy load is permanently shunted across the tube. The ignition electrode voltage is applied through a series resistor (R_{ign}) from a higher voltage source and suitable values are given in the above ratings. This voltage may be taken from a separate supply if desired.

MARCONI'S WIRELESS TELEGRAPH COMPANY LIMITED

Head Office : Marconi House, Chelmsford · Telephone : Chelmsford 3221 · Telegraphic Address : Expanse, Chelmsford

QS75/20
QS95/10
QS150/15

