

CDP-C67ES/C615

SERVICE MANUAL




Photo: CDP-C67ES

US Model
CDP-C67ES/C615
Canadian Model
AEP Model
E Model
Australian Model
CDP-C615

Model Name Using Similar Mechanism	CDP-C312M
CD Mechanism Type	CDM16E2-5BD3
Optical Pick-Up Block Type	BU-5BD3

SPECIFICATIONS

System	Compact disc digital audio system	DIGITAL OUT (OPTICAL)	Wave length 660 nm
Laser	Semiconductor laser ($\lambda = 780 \text{ nm}$)	(optical output connector)	Output level -18 dBm
Laser output	Emission duration: continuous Max. $44.6 \mu\text{W}^*$ * This output is the value measured at a distance of about 200 mm from the objective lens surface on the Optical Pick-up Block.	HEADPHONES (stereo phone jack)	Output level max. 15 mW Load impedance 32 ohms
Frequency response	2 Hz - 20 kHz ($\pm 0.5 \text{ dB}$)	General	
Signal to noise ratio	More than 110 dB (C67ES) More than 100 dB (C615)	Power requirements	US and Canadian model: 120 V AC, 60 Hz Australian model: 240 V AC, 50/60 Hz
Dynamic range	More than 100 dB (C67ES) More than 98 dB (C615)		AEP model: 220-230 V AC, 50/60 Hz
Harmonic distortion	Less than 0.0025% (1 kHz) (C67ES) Less than 0.004% (1 kHz) (C615)		E model: 110-120 V, 220-240 V, 50/60 Hz
Channel separation	More than 105 dB (1 kHz) (C67ES) More than 100 dB (1 kHz) (C615)	Power consumption	13 W
Wow and flutter	Below measurable limit	Dimensions	Approx. 430 x 125 x 385 mm (w/h/d) (17 x 5 x 15 1/4 inches) not including projecting parts and controls
Outputs		Weight	Approx. 7 kg (15 lbs 7 oz), net (C67ES) Approx. 6 kg (13 lbs 4 oz), net (C615)
LINE OUT (FIXED) (phone jacks)	Output level 2 V (at 50 kilohms) Load impedance over 10 kilohms		
LINE OUT (VARIABLE) (phono jacks)	Output level max. 2 V (at 50 kilohms) Load impedance over 10 kilohms		

— Continued on next page —



COMPACT DISK PLAYER
SONY[®]

Remote commander RM-D615
 Remote control system Infrared control
 Power requirements 3 V DC with two batteries size AA
 (IEC esignation R6)

Supplied accessories
 Connecting cord (1)
 (2 phono plugs ↔ 2 phono plugs)
 Remote commander (1)
 Size AA batteries (2)
 Operating Manual (1)

Optional accessory
 Audio Optical connecting cord POC-15

Design and specifications subject to change without notice.

Note on the Transit Key

The transit key on the bottom exterior of the unit protects the optical system against shock during transportation. Before operating the CD player, be sure to remove the key by following the instructions on the label, and store it in a safe place. When transporting the unit, replace the key in its original hole and lock it in place.





TABLE OF CONTENTS

<u>Section</u>	<u>Title</u>	<u>Page</u>	<u>Section</u>	<u>Title</u>	<u>Page</u>
1. GENERAL			6. EXPLODED VIEWS		
1-1.	Location of Controls	5	6-1.	Front Panel and Case Assemblies	23
2. DISASSEMBLY			6-2.	Disc Tray Assembly	24
2-1.	Removal of Front Panel and Case Assemblies	7	6-3.	Chassis Assembly	25
2-2.	Removal of Disc Tray Assembly	7	6-4.	Optical Pick-up Block Assembly (BU-5BD3).....	26
2-3.	Removal of Optical Pick-up Block Assembly	7	7. ELECTRICAL PARTS LIST		27
3. IC101(CXA1372Q) PIN FUNCTION		8			
4. ELECTRICAL BLOCK CHECKING		9			
5. DIAGRAMS					
5-1.	Circuit Boards Location	11			
5-2.	Semiconductor Lead Layouts	11			
5-3.	IC Block Diagrams.....	12			
5-4.	Printed Wiring Boards.....	14			
5-5.	Schematic Diagram	19			

For the European countries




This Compact Disc player is classified as a CLASS 1 LASER product. The CLASS 1 LASER PRODUCT label is located on the rear exterior.

SAFETY-RELATED COMPONENT WARNING!!
 COMPONENTS IDENTIFIED BY MARK OR DOTTED LINE WITH MARK ON THE SCHEMATIC DIAGRAMS AND IN THE PARTS LIST ARE CRITICAL TO SAFE OPERATION. REPLACE THESE COMPONENTS WITH SONY PARTS WHOSE PART NUMBERS APPEAR AS SHOWN IN THIS MANUAL OR IN SUPPLEMENTS PUBLISHED BY SONY.

ATTENTION AU COMPOSANT AYANT RAPPORT À LA SÉCURITÉ!
 LES COMPOSANTS IDENTIFIÉS PAR UNE MARQUE SUR LES DIAGRAMMES SCHÉMATIQUES ET LA LISTE DES PIÈCES SONT CRITIQUES POUR LA SÉCURITÉ DE FONCTIONNEMENT. NE REMPLACER CES COMPOSANTS QUE PAR DES PIÈCES SONY DONT LES NUMÉROS SONT DONNÉS DANS CE MANUEL OU DANS LES SUPPLÉMENTS PUBLIÉS PAR SONY.

MODEL IDENTIFICATION

—Model Number Label—



US, Canadian model: AC: 120V 60Hz

AEP model: AC: 220–230V~50/60Hz

Australian model: AC: 240V~50/60Hz

E model: AC: 110–120V, 220–240V~50/60Hz

NOTES ON HANDLING THE OPTICAL PICK-UP BLOCK OR BASE UNIT

The laser diode in the optical pick-up block may suffer electrostatic breakdown because of the potential difference generated by the charged electrostatic load, etc. on clothing and the human body.

During repair, pay attention to electrostatic breakdown and also use the procedure in the printed matter which is included in the repair parts.

The flexible board is easily damaged and should be handled with care.

NOTES ON LASER DIODE EMISSION CHECK

The laser beam on this model is concentrated so as to be focused on the disc reflective surface by the objective lens in the optical pick-up block. Therefore, when checking the laser diode emission, observe from more than 30cm away from the objective lens.

SAFETY CHECK-OUT

After correcting the original service problem, perform the following safety check before releasing the set to the customer:

Check the antenna terminals, metal trim, "metallized" knobs, screws, and all other exposed metal parts for AC leakage. Check leakage as described below.

LEAKAGE TEST

The AC leakage from any exposed metal part to earth ground and from all exposed metal parts to any exposed metal part having a return to chassis, must not exceed 0.5 mA (500 microamperes). Leakage current can be measured by any one of three methods.

1. A commercial leakage tester, such as the Simpson 229 or RCA WT-540A. Follow the manufacturers' instructions to use these instruments.
2. A battery-operated AC milliammeter. The Data Precision 245 digital multimeter is suitable for this job.
3. Measuring the voltage drop across a resistor by means of a VOM or battery-operated AC voltmeter. The "limit" indication is 0.75 V, so analog meters must have an accurate low-voltage scale. The Simpson 250 and Sanwa SH-63Trd are examples of a passive VOM that is suitable. Nearly all battery operated digital multimeters that have a 2V AC range are suitable. (See Fig. A)




Fig. A. Using an AC voltmeter to check AC leakage.

PROTECTION OF EYES FROM LASER BEAM DURING SERVICING

This set employs a laser. Therefore, be sure to follow carefully the instructions below when servicing.

CAUTION

Use of controls or adjustments or performance of procedures other than those specified herein may result in hazardous radiation exposure.

1. Laser Diode Properties

- Material: GaAlAs
 - Wavelength: 780 nm
 - Emission Duration: continuous
 - Laser Output Power: less than 44.6 μ W*
- * This output is the value measured at a distance of 200 mm from the objective lens surface on the Optical Pick-up Block.

2. During service, do not take the Optical Pick-up Block apart, and do not adjust the APC circuit. If there is a breakdown in the APC circuit (including laser diode), replace the entire Optical Pick-up Block (including APC board).

BESKYTTELSE AF ØJNE MOD LASERSTRÅLING UNDER SERVICE

I dette apparat anvendes laserlys. Derfor skal nedenstående instruktioner nøje følges under service.

Følg iverigt instruktionerne i servicemanualen.

ADVARSEL!!

Under service må øjnene ikke komme nær objektiv-linsen på den optiske pick-up enhed. I tilfælde af at det er nødvendigt at kontrollere udsendelsen af laserlys, skal det ske i en afstand af mere end 25 cm fra den optiske pick-up.

1. Laser-diode data


- Materiale: GaAlAs
 - Bølgelængde: 780 nm
 - Udstråling: Kontinuerlig
 - Laseroutput: Max. 0,4 mW*
- * Målt i 1,6 mm afstand fra overfladen af objektiv-linsen på den optiske pick-up enhed.
- Klassifikation: Klasse IIIb.

2. Adskil aldrig den optiske pick-up enhed under service, og juster ikke APC kredsløbet (Automatic Power Control). Hvis APC kredsløbet (incl. laser-dioden) bryder ned, skal hele den optiske pick-up enhed (incl. APC printkortet) udskiftes.

LASER ADVARSEL MÆRKNING

Følgende mærkning findes indvendig i apparatet:


1. Advarsel Mærkning



VAROITUS: Laite sisältää, laserdiodin, joka lähettää (näkömättömä) silmille vaarallista lasersäteilyä.

SECTION 1 GENERAL


1-1. LOCATION OF CONTROLS



- | | |
|----------------------------------|--|
| 1 POWER switch | 17 ▲ OPEN/CLOSE button |
| 2 CONTINUE button | 18 DISC SKIP button |
| 3 DISC 1-5 buttons | 19 LINE OUT/PHONE LEVEL control |
| 4 PEAK SEARCH button | 20 HEADPHONES jack |
| 5 REPEAT button | 21 Numeric buttons (1-10) |
| 6 TIME button | 22 > 10 (over 10) button |
| 7 Display window | 23 MUSIC SCAN button |
| 8 CHECK (program check) button | 24 Disc tray |
| 9 CLEAR (program clear) button | 25 DIGITAL SIGNAL PROCESSOR EFFECT level control |
| 10 FADER button | 26 DIGITAL SIGNAL PROCESSOR FLAT button |
| 11 EDIT/TIME FADE button | 27 DIGITAL SIGNAL PROCESSOR mode select buttons |
| 12 ◀◀/▶▶ (AMS*) buttons | 28 PROGRAM button |
| 13 ▶ (play) button | 29 SHUFFLE button |
| 14 (pause) button | 30 Remote sensor |
| 15 ■ (stop) button | |
| 16 ◀◀/▶▶ (manual search) buttons | |


* AMS is the abbreviation of Automatic Music Sensor.

Remote Commander



- 1 MUSIC SCAN button
- 2 DISC SKIP button
- 3 DISC 1-5 buttons
- 4 Numeric buttons
- 5 CLEAR (program clear) button
- 6 REPEAT button
- 7 FADER button
- 8 DSP SELECT button
- 9 LINE OUT LEVEL buttons
- 10 DSP FLAT button
- 11 ◀▶ (manual search) buttons
- 12 ◀◀▶▶ (AMS) buttons
- 13 || (pause) button
- 14 ▶ (play) button
- 15 ■ (stop) button
- 16 TIME button
- 17 >20 (over 20) button
- 18 CHECK (program check) button
- 19 CONTINUE button
- 20 SHUFFLE button
- 21 PROGRAM button

Installing Batteries in the Remote Commander



On battery life


- About half a year of normal operation can be expected when using the Sony SUM-3(NS) batteries.
- When the batteries are run down, the remote commander will not operate the unit. In this case, replace both batteries with new ones.

Notes on the remote commander and remote control operation


- Keep the commander away from extremely hot or humid places.
- Avoid dropping any foreign objects into the commander casing, particularly when replacing the batteries.
- Avoid exposing the remote sensor to direct sunlight or lighting apparatus. Such exposure can cause a malfunction.
- To avoid damage caused by battery leakage and corrosion, remove the batteries when the commander will not be used for a long time.

SECTION 2 DISASSEMBLY

2-1. REMOVAL OF FRONT PANEL AND CASE ASSEMBLIES




2-2. REMOVAL OF DISC TRAY ASSEMBLY



2-3. REMOVAL OF OPTICAL PICK-UP BLOCK ASSEMBLY

1) Replace the set up side down.



SECTION 3

IC101 (CXA1372Q) PIN FUNCTION


Pin No.	Pin Name	I/O	Function
1	VC		When \pm power : GND. When signal power : middle point (2.5V)
2	FGD	I	FGD terminal of gain select (time constant) in focus gain normal, down
3	FS3	I	Connecting terminal between FS3 terminals
4	FLB	I	Capacitor connecting terminal for equalizing low-frequency response of focus servo
5	FEO	O	Focus drive output
6	FE-	I	Focus amplifier inverting input
7	SRCH	I	Time constant connecting terminal to create focus search waveform
8	TGU	I	TGU terminal of gain select time constant in tracking gain normal, up
9	TG2	I	Connecting terminal between TG2 terminals
10	AVcc		Analog power (when \pm power : +5V, when single power : +5V)
11	TAO	O	Tracking drive output
12	TA-	I	Tracking amplifier inverting input
13	SL+	I	Sled amplifier non-inverting input
14	SLO	O	Sled drive output
15	SL-	I	Sled amplifier non-inverting input
16	FSET	I	Resistor of 510 k Ω connecting terminal for phase compensation setting
17	ISET	I	Resistor connecting terminal for current source setting
18	SSTOP	I	Limit switch connecting terminal
19	AVEE		Analog power (when \pm power : -5V, when single power : GND)
20	DIRC	I	Direct control terminal
21	LOCK	I	"L" : sled free-run protector operates
22	CLK	I	Serial data transmission clock input from CPU (or DSP)
23	XLT	I	Latch input from CPU (or DSP)
24	DATA	I	Serial data input from CPU (or DSP)
25	SENS	O	SENS signal output
26	XRST	I	System reset. "L" : reset
27	C. OUT	O	Output for tracking counter
28	DGND		Digital ground (when \pm power : GND, when single power : GND)
29	MIRR	O	Mirror output
30	DFCT	O	Defect output. "H" : when defected
31	ASY	I	Auto asymmetry control input
32	EFM	O	EFM comparator output
33	FOK	O	Focus OK
34	CC2	I	Defect bottom hold input (fed by capacitor coupling)
35	CC1	O	Defect bottom hold output
36	DVcc		Digital power (when \pm power : +5V, when single power : +5V)
37	CB	I	Defect bottom hold capacitor connecting terminal
38	CP	I	Mirror hold capacitor connecting terminal
39	RFI	I	RF signal input (fed by capacitor coupling)
40	RFO	I	RF signal input (fed by DC coupling)
41	DVEE		Digital power (when \pm power : -5V, when single power : GND)
42	TZC	I	Tracking zero-cross comparator input
43	TE	I	Tracking error input
44	TDFCT	I	Hold capacitor connecting terminal against defects
45	ATSC	I	Anti-shock input
46	FZC	I	Focus zero-cross comparator input
47	FE	I	Focus error input
48	FDFCT	I	Hold capacitor connecting terminal against defects

SECTION 4 ELECTRICAL BLOCK CHECKING

Note :


1. CD Block basically constructed to operate without adjustment. Therefore, check each item in order given.
2. Use YEDS-18 disc (3-702-101-01) unless otherwise indicated.
3. Use the oscilloscope with more than 10MΩ impedance.
4. Clean an object lens by an applicator with neutral detergent when the signal level is low than specified value with the following checks.

S Curve Check



Procedure :

1. Connect oscilloscope to test point TP (FEO) on BD board.
2. Connect between test point TP (FES) and TP (VC) by lead wire.
3. Turned Power switch on and actuate the focus serch. (actuate the focus serch when disc table is moving in and out.)
4. Check the oscilloscope waveform (S curve) is symmetrical between A and B. And confirm peak to peak level within $3 \pm 1V_{p-p}$.




5. After check, remove the lead wire connected in step 2.

Note : • Try to measure several times to make sure that the ratio of A : B or B : A is more than 10 : 7.

• Take sweep time as long as possible and light up the brightness to obtain best waveform.

RF Level Check




Procedure :


1. Connect oscilloscope to test point TP (RF) on BD board.
2. Turn Power switch on.
3. Put disc (YEDS-18) in and playback.
4. Confirm that oscilloscope waveform is clear and check RF signal level is correct or not.

Note :

Clear RF signal waveform means that the shape "◇" can be clearly distinguished at the center of the waveform.




E-F Balance Check



Procedure :

1. Connect test point TP (ADJ) to ground and TP (TES) to TP (VC) with lead wire.
2. Connect oscilloscope to test point TP (TEO) on BD board.
3. Turn Power switch on.
4. Put disc (YEDS-18) in and playback.
5. Confirm that the oscilloscope waveform is symmetrical on the top and bottom in relation to 0V, and check this level.




6. Remove the lead wire connected in step 1.

RF PLL Free-run Frequency Check

Procedure :

1. Connect frequency counter to test point (PCK) with lead wire.



2. Turn Power switch on.
3. Confirm that reading on frequency counter is 4. 3218MHz.


Focus/Tracking Gain

This gain has a margin, so even if it is slightly off. There is no problem.


Therefore, do not perform, this adjustment.

Please note that it should be fixed to mechanical center position when you moved and do not know original position.

Adjustment Locations: [BD board]




[Main board]




SECTION 5 DIAGRAMS

1. CIRCUIT BOARDS LOCATION




2. SEMICONDUCTOR LEAD LAYOUTS




5-3. IC BLOCK DIAGRAMS


IC101 CXA1372Q




IC202 M5290P-16




IC102 LA6532M




IC201 M5293L




IC901 CXD2701Q




IC202 M5290P-16



IC301 CXD2500Q




IC901 CXD2701Q







5-4. PRINTED WIRING BOARDS
 • Refer to page 11 for Semiconductor Lead Layouts.








• Semiconductor Location

Ref. No.	Location
D201	H-26
D202	G-26
D203	D-25
D204	D-25
D205	E-25
D206	D-25
D208	D-18
D209	D-18
D341	G-22
D351	G-21
D601	C-4
D701	I-32
D801	F-7
D802	F-6
D803	F-5
D804	F-5
D805	F-4
IC101	E-30
IC102	D-30
IC201	H-26
IC202	F-25
IC203	F-22
IC204	G-25
IC301	I-23
IC302	H-24
IC303	G-23
IC306	F-20
IC307	F-20
IC308	H-27
IC309	D-19
IC401	I-18
IC402	G-17
IC551	H-13
IC901	J-24
IC902	I-26
IC903	J-20
IC904	I-26
IC910	F-19
Q101	F-31
Q201	G-26
Q202	F-24
Q203	E-23
Q204	G-24
Q205	F-24
Q206	F-24
Q209	E-22
Q341	F-16
Q342	F-16
Q343	G-16
Q344	G-20
Q371	G-17
Q372	F-17
Q373	G-17
Q374	F-17
Q375	F-17
Q376	F-17
Q401	H-17
Q901	G-20
Q902	G-19
Q903	G-19
Q941	F-19
Q942	F-18
Q943	F-18
Q971	F-18
Q972	F-18
Q973	F-18



Note:
 • ○ : parts extracted from the component side.
 • ● : Through hole.
 • [Pattern] : Pattern on the side which is seen.
 • [Pattern] : Pattern of the rear side.





5-5. SCHEMATIC DIAGRAM

• Refer to page 12 for IC BLOCK Diagrams.

Note:

- All capacitors are in μF unless otherwise noted. pF: μpF . 50WV or less are not indicated except for electrolytics and tantalums.
- All resistors are in Ω and 1/4W or less unless otherwise specified.



Note:


The components identified by mark Δ or dotted line with mark Δ are critical for safety. Replace only with part number specified.




Note:

Les composants identifiés par une marque Δ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

- — : B+ Line.
- - - - : B- Line.
- \square : adjustment for repair.
- Δ : internal component.
- Voltage and waveforms are dc with respect to ground under no-signal conditions.
- Voltage are taken with a VOM (Input Impedance 10M Ω) Voltage variations may be noted due to normal production tolerances.
- Waveforms are taken with a oscilloscope. Voltage variations may be noted due to normal production tolerances.
- Circled numbers refer to waveforms.
- Signal path.
- \Rightarrow : CD \Rightarrow : digital out







EXPLODED VIEWS

NOTE:

• -XX, -X mean standardized parts, so they may have some difference from the original one.

• Color Indication of Appearance Parts
Example:
KNOB, BALANCE (WHITE)...(RED)

↑ ↑
Parts color Cabinet's color

• Items marked " * " are not stocked since they are seldom required for routine service. Some delay should be anticipated when ordering these items.


• The mechanical parts with no reference number in the exploded views are not supplied.

• Hardware (# mark) list is given in the last of this parts list.

The components identified by mark or dotted line with mark are critical for safety. Replace only with part number specified.


Les composants identifiés par une marque sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

6-1. FRONT PANEL AND CASE ASSEMBLIES




Ref. No.	Part No.	Description	Remark	Ref. No.	Part No.	Description	Remark
1	A-4675-298-A	KNOB (HP) ASSY		10	* 1-639-471-11	HEADPHONE JACK BOARD	
2	4-944-154-02	KNOB (DSP)		11	* 1-639-470-11	HEADPHONE VOLUME BOARD	
3	3-354-981-01	SPRING (SUS), RING		12	1-590-834-11	WIRE, FLAT TYPE (13 CORE)	
4	X-4941-484-2	PANEL ASSY, FRONT (C615:US, Canadian)		13	1-590-835-11	WIRE, FLAT TYPE (34 CORE)	
4	X-4941-486-2	PANEL ASSY, FRONT (C67ES)		14	4-928-635-01	SCREW, +BV (2.6X8) TAPPING	
4	X-4941-485-2	PANEL ASSY, FRONT (AEP, E, Australian)		15	X-4924-463-1	FOOT ASSY (C67ES) (C615:AEP, E, Australian)	
5	4-922-921-01	BUTTON (POWER)		15	X-4924-464-1	FOOT ASSY (C615:US, Canadian)	
6	* 1-639-469-11	POWER SW BOARD		16	* 4-944-153-01	CASE	
7	* 1-639-468-11	DSP BOARD		17	3-704-366-01	SCREW (CASE) (M3X8)	
8	* 1-639-467-11	DISPLAY BOARD		18	3-703-685-21	SCREW (+BV 3X8)	
9	* 1-639-466-11	FUNCTION BOARD		19	* 4-929-561-01	CUSHION (CASE)	
				20	A-4675-309-A	REINFORCEMENT (TOP PLATE) ASSY (C67ES)	

6-2. DISC TRAY ASSEMBLY




Ref. No.	Part No.	Description	Remark	Ref. No.	Part No.	Description	Remark
51	4-926-384-01	SCREW, STEP		58	4-926-399-01	BELT	
52	* 4-926-383-01	TABLE (B), DISK (C615)		59	4-923-597-01	SCREW, STEP	
52	4-926-383-11	TABLE (B), DISK (C67ES)		60	* 4-926-388-01	BRACKET (ADJUSTMENT)	
53	4-921-029-01	YOKE, CHUCKING		61	4-944-160-01	TABLE (A), DISK (C615)	
54	1-452-340-21	MAGNET		61	4-944-161-01	TABLE (A), DISK (C67ES)	
55	* 4-930-506-02	BRACKET (PRESS PULLEY)		62	4-934-307-01	ESCUTCHEON (C67ES)	
56	4-921-022-01	PULLEY, CHUCKING		63	4-928-635-01	SCREW, +BV (2.6X8) TAPPING (C67ES)	
57	4-926-395-01	SPRING, COMPRESSION		64	* 1-638-729-11	TABLE MOTOR BOARD	
				65	1-590-849-11	WIRE, FLAT TYPE (5 CORE)	
				M701	A-4604-585-A	MOTOR ASSY, ROTARY (TABLE)	

6-3. CHA



Ref. No.	Part No.	Description	Remark
101			
102			
103			
104	* 4		
105			
106			
107			
108	* 4		
109	* 1		
110			
111			
112			
113			
114	X		
115			
116	* 1		
117	* A		
117	* A		
117	* A		
117	* A		
118	* 4		
119	3		
120	* 4		
121	* 4		

6-3. CHASSIS ASSEMBLY




The components identified by mark Δ or dotted line with mark Δ are critical for safety. Replace only with part number specified.

Les composants identifiés par une marque Δ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

Ref.No.	Part No.	Description	Remark
101	1-535-892-11	JUMPER, FILM (WITH TERMINAL)	
102	4-933-134-01	SCREW (+PTPHW M2, 6X6)	
103	4-917-541-01	SPRING (B)	
104	* 4-934-373-01	BRACKET (BU)	
105	4-937-911-01	SPRING, TENSION	
106	4-917-519-01	LEVER, SET	
107	4-924-412-01	SPRING (B), TENSION	
108	* 4-934-382-01	CUSHION	
109	* 1-638-730-11	LOADING MOTOR BOARD	
110	4-934-375-01	GEAR (LOADING B)	
111	4-934-381-01	GEAR (LOADING C)	
112	4-934-391-01	GEAR (LOADING A)	
113	4-926-317-01	SCREW, STEP	
114	X-4941-529-1	PULLEY ASSY	
115	4-944-490-01	BELT (TIMING)	
116	* 1-638-731-11	OPEN/UP SW BOARD	
117	* A-4617-851-A	MAIN BOARD, COMPLETE (AEP, Australian)	
117	* A-4617-842-A	MAIN BOARD, COMPLETE (C67ES)	
117	* A-4617-843-A	MAIN BOARD, COMPLETE (C615:US, Canadian)	
117	* A-4617-853-A	MAIN BOARD, COMPLETE (E)	
118	* 4-944-178-01	SHEET (INSULATING)	
119	3-531-576-11	RIVET	
120	* 4-943-997-01	CHASSIS	
121	* 4-943-996-01	SPRING, LEAF	

Ref.No.	Part No.	Description	Remark
122	* 4-943-680-21	PANEL, BACK (C67ES)	
122	* 4-943-680-31	PANEL, BACK (C615:US)	
122	* 4-943-680-41	PANEL, BACK (Canadian)	
122	* 4-943-680-51	PANEL, BACK (AEP)	
122	* 4-943-680-61	PANEL, BACK (Austrian)	
122	* 4-943-680-71	PANEL, BACK (E)	
123	* 3-703-244-00	BUSHING (2104), CORD (EXCEPT E)	
123	* 3-703-571-11	BUSHING (S) (4516), CORD (E)	
124	. 1-574-358-31	CORD, POWER (WITH CONNECTOR) (Australian)	
124	. 1-575-651-21	CORD, POWER (AEP)	
124	. 1-575-653-21	CORD, POWER (E)	
124	. 1-590-836-11	CORD, POWER (US, Canadian)	
125	. 1-569-007-11	ADAPTOR, CONVERSION 2P (E)	
M702	A-4604-834-A	MOTOR ASSY, LOADING	
S201	. 1-571-722-11	SWITCH, VOLTAGE SELECTION (E)	
S701	1-572-713-11	SWITCH, PUSH (WITH CONNECTOR) (DOWN)	
T901	. 1-450-133-11	TRANSFORMER, POWER (US, Canadian)	
T901	. 1-450-134-11	TRANSFORMER, POWER (AEP, Australian)	
T901	. 1-450-135-11	TRANSFORMER, POWER (E)	

6-4. OPTICAL PICK-UP BLOCK ASSEMBLY (BU-5BD3)



The components identified by mark Δ or dotted line with mark Δ are critical for safety. Replace only with part number specified.

Les composants identifiés par une marque Δ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

Ref.No.	Part No.	Description	Remark
151	. 8-848-144-11	DEVICE, OPTICAL KSS-240A	
152	1-575-001-11	WIRE, FLAT TYPE (12 CORE)	
153	4-917-567-01	GEAR (M)	
154	4-933-126-01	INSULATOR (A)	
155	4-917-565-01	SHAFT, SLED	

Ref.No.	Part No.	Description	Remark
156	4-917-564-01	GEAR (P), FLATNESS	
157	* A-4617-371-A	BD BOARD, COMPLETE	
M101	X-4917-504-1	MOTOR ASSY (SLED)	
M102	X-4917-523-3	MOTOR ASSY (SPINDLE)	
S101	1-572-085-11	SWITCH, LEAF (LIMIT IN)	

SECTION 7 ELECTRICAL PARTS LIST

NOTE:

The components identified by mark Δ or dotted line with mark Δ are critical for safety. Replace only with part number specified.

Les composants identifiés par une marque Δ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

When indicating parts by reference number, please include the board name.

- Due to standardization, replacements in the parts list may be different from the parts specified in the diagrams or the components used on the set.
- -XX, -X mean standardized parts, so they may have some difference from the original one.
- **RESISTORS**
All resistors are in ohms
METAL: Metal-film resistor
METAL OXIDE: Metal Oxide-film resistor
F: nonflammable
- Items marked "*" are not stocked since they are seldom required for routine service. Some delay should be anticipated when ordering these items.
- **SEMICONDUCTORS**
In each case, μ : μ , for example:
uA...: μ A..., uPA...: μ PA...,
uPB...: μ PB..., uPC...: μ PC...,
uPD...: μ PD...
- **CAPACITORS**
uF: μ F
- **COILS**
uH: μ H

Ref. No.	Part No.	Description	Remark	Ref. No.	Part No.	Description	Remark
* A-4617-371-A BD BOARD, COMPLETE *****				< CONNECTOR >			
< CAPACITOR >				CN101	1-568-796-11	SOCKET, CONNECTOR 22P	
C101	1-163-038-00	CERAMIC CHIP 0.1uF	25V	CN102	1-568-795-11	SOCKET, CONNECTOR 12P	
C102	1-163-989-11	CERAMIC CHIP 0.033uF	10% 25V	< IC >			
C103	1-126-163-11	ELECT 4.7uF	20% 50V	IC101	8-752-050-82	IC CXA1372Q	
C104	1-163-038-00	CERAMIC CHIP 0.1uF	25V	IC102	8-759-822-36	IC LA6532M	
C105	1-126-154-11	ELECT 47uF	20% 6.3V	< JUNPER >			
C106	1-126-154-11	ELECT 47uF	20% 6.3V	J101	1-216-295-00	METAL CHIP 0	5% 1/10W
C107	1-126-154-11	ELECT 47uF	20% 6.3V	J102	1-216-295-00	METAL CHIP 0	5% 1/10W
C108	1-163-038-00	CERAMIC CHIP 0.1uF	25V	< TRANSISTOR >			
C109	1-163-038-00	CERAMIC CHIP 0.1uF	25V	O101	8-729-901-01	TRANSISTOR DTC144EK	
C110	1-163-989-11	CERAMIC CHIP 0.033uF	10% 25V	< RESISTOR >			
C111	1-131-367-00	TANTALUM 22uF	10% 20V	R101	1-216-097-00	METAL CHIP 100K	5% 1/10W
C112	1-164-232-11	CERAMIC CHIP 0.01uF	50V	R102	1-216-095-00	METAL CHIP 82K	5% 1/10W
C113	1-164-232-11	CERAMIC CHIP 0.01uF	50V	R103	1-216-091-00	METAL CHIP 56K	5% 1/10W
C114	1-164-161-11	CERAMIC CHIP 0.0022uF	10% 100V	R104	1-216-099-00	METAL CHIP 120K	5% 1/10W
C115	1-164-161-11	CERAMIC CHIP 0.0022uF	10% 100V	R105	1-216-069-00	METAL CHIP 6.8K	5% 1/10W
C117	1-163-038-00	CERAMIC CHIP 0.1uF	25V	R106	1-216-061-00	METAL CHIP 3.3K	5% 1/10W
C118	1-163-038-00	CERAMIC CHIP 0.1uF	25V	R107	1-216-114-00	METAL GLAZE 510K	5% 1/10W
C119	1-164-161-11	CERAMIC CHIP 0.0022uF	10% 100V	R108	1-216-105-00	METAL CHIP 220K	5% 1/10W
C120	1-163-989-11	CERAMIC CHIP 0.033uF	10% 25V	R109	1-216-061-00	METAL CHIP 3.3K	5% 1/10W
C151	1-163-019-00	CERAMIC CHIP 0.0068uF	10% 50V	R110	1-216-049-00	METAL CHIP 1K	5% 1/10W
C152	1-163-038-00	CERAMIC CHIP 0.1uF	25V	R111	1-216-049-00	METAL CHIP 1K	5% 1/10W
C153	1-163-006-11	CERAMIC CHIP 560PF	10% 50V	R112	1-216-083-00	METAL CHIP 27K	5% 1/10W
C154	1-164-161-11	CERAMIC CHIP 0.0022uF	10% 100V	R113	1-216-071-00	METAL CHIP 8.2K	5% 1/10W
C155	1-163-023-00	CERAMIC CHIP 0.015uF	5% 50V	R114	1-216-105-00	METAL CHIP 220K	5% 1/10W
C171	1-163-038-00	CERAMIC CHIP 0.1uF	25V	R152	1-216-073-00	METAL CHIP 10K	5% 1/10W
C172	1-163-038-00	CERAMIC CHIP 0.1uF	25V				
C173	1-163-038-00	CERAMIC CHIP 0.1uF	25V				
C174	1-163-038-00	CERAMIC CHIP 0.1uF	25V				

BD **MAIN** **FUNCTION** **DISPLAY** **DSP**

Ref. No.	Part No.	Description	Remark		
R153	1-216-085-00	METAL CHIP	33K	5%	1/10W
R154	1-216-085-00	METAL CHIP	33K	5%	1/10W
R155	1-216-093-00	METAL CHIP	68K	5%	1/10W
R156	1-216-081-00	METAL CHIP	22K	5%	1/10W
R157	1-216-079-00	METAL CHIP	18K	5%	1/10W
R158	1-216-079-00	METAL CHIP	18K	5%	1/10W
R159	1-216-079-00	METAL CHIP	18K	5%	1/10W
R160	1-216-049-00	METAL CHIP	1K	5%	1/10W
R171	1-216-001-00	METAL CHIP	10	5%	1/10W
R172	1-216-001-00	METAL CHIP	10	5%	1/10W
R173	1-216-001-00	METAL CHIP	10	5%	1/10W
R174	1-216-001-00	METAL CHIP	10	5%	1/10W
< VARIABLE RESISTOR >					
RV101	1-238-016-11	RES. ADJ. CARBON 10K			
RV102	1-238-016-11	RES. ADJ. CARBON 10K			
< SWITCH >					
S101	1-572-085-11	SWITCH, LEAF (LIMIT)			

* A-4617-842-A MAIN BOARD, COMPLETE (C67ES)					
* A-4617-843-A MAIN BOARD, COMPLETE (C615:US, Canadian)					
* A-4617-851-A MAIN BOARD, COMPLETE (AEP, Australian)					
* A-4617-853-A MAIN BOARD, COMPLETE (E)					

* 1-639-466-11 FUNCTION BOARD					

* 1-639-467-11 DISPLAY BOARD					

* 1-639-468-11 DSP BOARD					

* 4-363-146-21 HEAT SINK, V. OUT					
* 4-944-156-01 HOLDER, LED					
7-682-548-09 SCREW +BVT 3X8 (S)					
< CAPACITOR >					
C201	1-124-572-11	ELECT	100uF	20%	63V
C202	1-126-059-11	ELECT	10uF	20%	50V
C203	1-126-937-11	ELECT	4700uF	20%	16V
C204	1-126-017-11	ELECT	6800uF	20%	16V
C205	1-126-163-11	ELECT	4.7uF	20%	50V
C206	1-126-059-11	ELECT	10uF	20%	50V
C207	1-126-059-11	ELECT	10uF	20%	50V
C208	1-124-997-11	ELECT	470uF	20%	10V
C209	1-124-997-11	ELECT	470uF	20%	10V
C210	1-126-024-11	ELECT	220uF	20%	16V

Ref. No.	Part No.	Description	Remark		
C211	1-124-893-11	ELECT	2200uF	20%	10V
C212	1-124-997-11	ELECT	470uF	20%	10V
C213	1-164-159-11	CERAMIC	0.1uF		50V
C214	1-130-487-00	MYLAR	0.022uF	5%	50V
C221	1-161-494-00	CERAMIC	0.022uF		25V
C301	1-126-022-11	ELECT	47uF	20%	16V
C302	1-164-159-11	CERAMIC	0.1uF		50V
C303	1-164-159-11	CERAMIC	0.1uF		50V
C304	1-164-159-11	CERAMIC	0.1uF		50V
C311	1-130-491-00	MYLAR	0.047uF	5%	50V
C312	1-161-374-11	CERAMIC	0.0015uF	20%	50V
C313	1-161-494-00	CERAMIC	0.022uF		25V
C314	1-162-306-11	CERAMIC	0.01uF	20%	16V
C315	1-126-300-11	ELECT	0.47uF	20%	50V
C316	1-161-494-00	CERAMIC	0.022uF		25V
C320	1-164-159-11	CERAMIC	0.1uF		50V
C321	1-164-159-11	CERAMIC	0.1uF		50V
C331	1-162-208-31	CERAMIC	24PF	5%	50V
C332	1-164-159-11	CERAMIC	0.1uF		50V
C337	1-164-159-11	CERAMIC	0.1uF		50V
C338	1-164-159-11	CERAMIC	0.1uF		50V
C339	1-164-159-11	CERAMIC	0.1uF		50V
C342	1-126-022-11	ELECT	47uF	20%	16V
C343	1-164-159-11	CERAMIC	0.1uF		50V
C349	1-164-159-11	CERAMIC	0.1uF		50V
C350	1-126-022-11	ELECT	47uF	20%	16V
C351	1-161-494-00	CERAMIC	0.022uF		25V
C353	1-162-196-31	CERAMIC	5.6PF	10%	50V
C354	1-162-196-31	CERAMIC	5.6PF	10%	50V
C355	1-161-494-00	CERAMIC	0.022uF		25V
C356	1-126-022-11	ELECT	47uF	20%	16V
C357	1-124-997-11	ELECT	470uF	20%	10V
C361	1-162-286-31	CERAMIC	220PF	10%	50V
C362	1-162-286-31	CERAMIC	220PF	10%	50V
C363	1-162-285-31	CERAMIC	180PF	10%	50V
C364	1-162-285-31	CERAMIC	180PF	10%	50V
C365	1-162-285-31	CERAMIC	180PF	10%	50V
C366	1-162-285-31	CERAMIC	180PF	10%	50V
C367	1-162-286-31	CERAMIC	220PF	10%	50V
C368	1-162-286-31	CERAMIC	220PF	10%	50V
C371	1-130-479-00	MYLAR	0.0047uF	5%	50V
C372	1-130-479-00	MYLAR	0.0047uF	5%	50V
C373	1-130-472-00	MYLAR	0.0012uF	5%	50V
C374	1-130-472-00	MYLAR	0.0012uF	5%	50V
C375	1-126-024-11	ELECT	220uF	20%	16V
C376	1-126-024-11	ELECT	220uF	20%	16V
C377	1-126-022-11	ELECT	47uF	20%	16V
C378	1-126-022-11	ELECT	47uF	20%	16V
C379	1-130-473-00	MYLAR	0.0015uF	5%	50V

MAIN	FUNCTION	DISPLAY	DSP
------	----------	---------	-----

Ref. No.	Part No.	Description	Remark	Ref. No.	Part No.	Description	Remark
C380	1-130-473-00	MYLAR	0.0015uF 5%	50V		< CONNECTOR >	
C390	1-164-159-11	CERAMIC	0.1uF	50V			
C391	1-164-159-11	CERAMIC	0.1uF	50V			
C401	1-126-022-11	ELECT	47uF	20%	16V		
C402	1-164-159-11	CERAMIC	0.1uF	50V			
C403	1-126-023-11	ELECT	100uF	20%	16V		
C404	1-126-023-11	ELECT	100uF	20%	16V		
C405	1-162-294-31	CERAMIC	0.001uF	10%	50V		
C406	1-162-294-31	CERAMIC	0.001uF	10%	50V		
C407	1-162-294-31	CERAMIC	0.001uF	10%	50V		
C408	1-164-159-11	CERAMIC	0.1uF	50V			
C409	1-164-159-11	CERAMIC	0.1uF	50V			
C410	1-164-159-11	CERAMIC	0.1uF	50V			
C412	1-126-022-11	ELECT	47uF	20%	16V		
C413	1-161-494-00	CERAMIC	0.022uF	25V			
C414	1-161-494-00	CERAMIC	0.022uF	25V			
C415	1-161-494-00	CERAMIC	0.022uF	25V			
C416	1-164-159-11	CERAMIC	0.1uF	50V			
C425	1-162-294-31	CERAMIC	0.001uF	10%	50V		
C426	1-162-294-31	CERAMIC	0.001uF	10%	50V		
C427	1-162-294-31	CERAMIC	0.001uF	10%	50V		
C428	1-162-294-31	CERAMIC	0.001uF	10%	50V		
C429	1-162-294-31	CERAMIC	0.001uF	10%	50V		
C430	1-162-294-31	CERAMIC	0.001uF	10%	50V		
C431	1-162-294-31	CERAMIC	0.001uF	10%	50V		
C432	1-162-294-31	CERAMIC	0.001uF	10%	50V		
C450	1-126-024-11	ELECT	220uF	20%	16V		
C460	1-126-024-11	ELECT	220uF	20%	16V		
C520	1-161-494-00	CERAMIC	0.022uF	25V			
C521	1-126-022-11	ELECT	47uF	20%	16V		
C901	1-161-494-00	CERAMIC	0.022uF	25V			
C902	1-126-022-11	ELECT	47uF	20%	16V		
C903	1-161-494-00	CERAMIC	0.022uF	25V			
C904	1-126-022-11	ELECT	47uF	20%	16V		
C910	1-126-012-11	ELECT	470uF	20%	16V		
C911	1-126-012-11	ELECT	470uF	20%	16V		
C941	1-162-219-31	CERAMIC	68PF	5%	50V		
C942	1-126-022-11	ELECT	47uF	20%	16V		
C943	1-124-463-00	ELECT	0.1uF	20%	50V		
C944	1-124-463-00	ELECT	0.1uF	20%	50V		
C945	1-124-463-00	ELECT	0.1uF	20%	50V		
C971	1-162-219-31	CERAMIC	68PF	5%	50V		
C972	1-126-022-11	ELECT	47uF	20%	16V		
C973	1-124-463-00	ELECT	0.1uF	20%	50V		
C974	1-124-463-00	ELECT	0.1uF	20%	50V		
C975	1-124-463-00	ELECT	0.1uF	20%	50V		
CN201	* 1-573-047-11	PIN, CONNECTOR					
CN301	* 1-573-046-11	SOCKET, CONNECTOR 18P					
CN381	* 1-568-856-11	SOCKET, CONNECTOR 13P					
CN401	* 1-573-080-11	SOCKET, CONNECTOR (34P, L TYPE)					
CN402	* 1-568-944-11	PIN, CONNECTOR 6P					
CN403	* 1-568-824-11	SOCKET, CONNECTOR 5P					
CN404	* 1-568-943-11	PIN, CONNECTOR 5P					
CN501	* 1-573-080-11	SOCKET, CONNECTOR (34P, L TYPE)					
CN503	* 1-568-942-11	PIN, CONNECTOR 4P					
CN901	* 1-568-947-11	PIN, CONNECTOR 9P					
D201	8-719-200-82	DIODE 11ES2					
D202	8-719-109-97	DIODE RD6. 8ES-2B					
D203	8-719-200-82	DIODE 11ES2					
D204	8-719-200-82	DIODE 11ES2					
D205	8-719-200-82	DIODE 11ES2					
D206	8-719-200-82	DIODE 11ES2					
D208	8-719-109-89	DIODE RD5. 6ES-82					
D209	8-719-912-20	DIODE 1SS120					
D341	8-719-210-21	DIODE 11EQS04					
D351	8-719-912-20	DIODE 1SS120					
D801	8-719-301-52	DIODE SEL2810A-C (HALL)					
D802	8-719-301-52	DIODE SEL2810A-C (CHURCH)					
D803	8-719-301-52	DIODE SEL2810A-C (JAZZ CLUB)					
D804	8-719-301-52	DIODE SEL2810A-C (STADIUM)					
D805	8-719-301-52	DIODE SEL2810A-C (DISCO)					
FL501	1-519-655-11	FLUORESCENT INDICATOR					
IC201	8-759-633-42	IC M5293L					
IC202	8-759-630-21	IC M5290P-16					
IC203	8-759-945-58	IC RC4558P					
IC204	8-759-604-86	IC M5F7807L					
IC301	8-752-337-26	IC CXD2500AQ					
IC302	8-752-342-65	IC CXD2560M					
IC303	8-752-343-01	IC CXD2561M (C615)					
IC303	8-752-344-10	IC CXD2561M-1 (C67ES)					
IC306	8-759-990-82	IC TL082CP					
IC307	8-759-982-03	IC RC5532DD					
IC308	8-759-977-71	IC GP1F31T (DIGITAL OUT OPTICAL)					
IC309	8-759-981-85	IC RC4558D					
IC401	8-752-831-21	IC CXP50116-2233Q					
IC402	8-759-821-32	IC CXA-1291P					
IC901	8-752-341-99	IC CXD2701Q					

MAIN FUNCTION DISPLAY DSP

Ref. No.	Part No.	Description	Remark
IC902	8-759-973-04	IC MSM41464-10RS-K	
IC903	8-759-636-84	IC M37470M4-054SP	
IC904	8-759-917-18	IC SN74HC004AM	
IC910	8-759-982-03	IC RC55320D	
< JACK >			
J381	* 1-569-443-11	JACK. PIN 4P (LINE OUT FIXED/VARIABLE) (C615)	
J381	* 1-569-443-21	JACK. PIN 4P (LINE OUT FIXED/VARIABLE) (C67ES)	
< COIL >			
L331	1-408-403-00	INDUCTOR 3.3uH	
L332	1-412-473-21	INDUCTOR 0uH	
L333	1-412-473-21	INDUCTOR 0uH	
L334	1-412-473-21	INDUCTOR 0uH	
L335	1-412-473-21	INDUCTOR. SMALL TYPE	
< LINK >			
PS201	△ 1-532-685-00	LINK. IC 0.8A ICP-N20 (AEP, E. Australian)	
PS202	△ 1-532-637-00	LINK. IC 1.0A ICP-N25 (AEP, E. Australian)	
< TRANSISTOR >			
Q201	8-729-119-76	TRANSISTOR 2SA1175-HFE	
Q202	8-729-140-96	TRANSISTOR 2SD774-34	
Q203	8-729-111-67	TRANSISTOR 2SB1094-L	
Q204	8-729-900-65	TRANSISTOR DTA144ES	
Q205	8-729-900-89	TRANSISTOR DTC144ES	
Q206	8-729-900-89	TRANSISTOR DTC144ES	
Q209	8-729-281-52	TRANSISTOR 2SC1815-Y	
Q341	8-729-900-65	TRANSISTOR DTA144ES	
Q342	8-729-900-65	TRANSISTOR DTA144ES	
Q343	8-729-900-65	TRANSISTOR DTA144ES	
Q344	8-729-900-89	TRANSISTOR DTC144ES	
Q371	8-729-141-30	TRANSISTOR 2SC3623A-LK	
Q372	8-729-141-30	TRANSISTOR 2SC3623A-LK	
Q373	8-729-141-30	TRANSISTOR 2SC3623A-LK	
Q374	8-729-141-30	TRANSISTOR 2SC3623A-LK	
Q375	8-729-231-55	TRANSISTOR 2SC2878-AB	
Q376	8-729-231-55	TRANSISTOR 2SC2878-AB	
Q401	8-729-900-89	TRANSISTOR DTC144ES	
Q901	8-729-900-63	TRANSISTOR DTA124ES	
Q902	8-729-900-63	TRANSISTOR DTA124ES	
Q903	8-729-900-63	TRANSISTOR DTA124ES	
Q941	8-729-231-55	TRANSISTOR 2SC2878-AB	
Q942	8-729-231-55	TRANSISTOR 2SC2878-AB	
Q943	8-729-231-55	TRANSISTOR 2SC2878-AB	
Q971	8-729-231-55	TRANSISTOR 2SC2878-AB	

Ref. No.	Part No.	Description	Remark
Q972	8-729-231-55	TRANSISTOR 2SC2878-AB	
Q973	8-729-231-55	TRANSISTOR 2SC2878-AB	
< RESISTOR >			
R201	1-249-435-11	CARBON 33K 5% 1/4W	
R202	1-249-438-11	CARBON 56K 5% 1/4W	
R203	1-249-429-11	CARBON 10K 5% 1/4W	
R204	1-249-425-11	CARBON 4.7K 5% 1/4W	
R205	1-249-425-11	CARBON 4.7K 5% 1/4W	
R208	1-249-423-11	CARBON 3.3K 5% 1/4W	
R209	1-249-413-11	CARBON 470 5% 1/4W	
R210	1-249-429-11	CARBON 10K 5% 1/4W	
R211	1-249-410-11	CARBON 270 5% 1/4W	
R212	1-247-790-11	CARBON 20 5% 1/4W	
R213	1-247-790-11	CARBON 20 5% 1/4W	
R214	1-249-417-11	CARBON 1K 5% 1/4W	
R215	1-249-417-11	CARBON 1K 5% 1/4W	
R301	1-249-417-11	CARBON 1K 5% 1/4W	
R302	1-249-417-11	CARBON 1K 5% 1/4W	
R303	1-249-417-11	CARBON 1K 5% 1/4W	
R305	1-249-411-11	CARBON 330 5% 1/4W	
R311	1-249-423-11	CARBON 3.3K 5% 1/4W	
R312	1-249-429-11	CARBON 10K 5% 1/4W	
R313	1-249-423-11	CARBON 3.3K 5% 1/4W	
R314	1-249-429-11	CARBON 10K 5% 1/4W	
R318	1-249-441-11	CARBON 100K 5% 1/4W	
R321	1-249-417-11	CARBON 1K 5% 1/4W	
R322	1-249-417-11	CARBON 1K 5% 1/4W	
R323	1-249-417-11	CARBON 1K 5% 1/4W	
R324	1-249-418-11	CARBON 1.2K 5% 1/4W	
R330	1-249-417-11	CARBON 1K 5% 1/4W	
R331	1-249-417-11	CARBON 1K 5% 1/4W	
R332	1-247-887-00	CARBON 220K 5% 1/4W	
R342	1-249-417-11	CARBON 1K 5% 1/4W	
R343	1-249-441-11	CARBON 100K 5% 1/4W	
R344	1-249-441-11	CARBON 100K 5% 1/4W	
R345	1-249-425-11	CARBON 4.7K 5% 1/4W	
R346	1-249-425-11	CARBON 4.7K 5% 1/4W	
R347	1-249-441-11	CARBON 100K 5% 1/4W	
R348	1-249-429-11	CARBON 10K 5% 1/4W	
R351	1-249-428-11	CARBON 8.2K 5% 1/4W	
R352	1-249-428-11	CARBON 8.2K 5% 1/4W	
R353	1-249-428-11	CARBON 8.2K 5% 1/4W	
R354	1-249-428-11	CARBON 8.2K 5% 1/4W	
R355	1-249-428-11	CARBON 8.2K 5% 1/4W	
R356	1-249-428-11	CARBON 8.2K 5% 1/4W	
R357	1-249-428-11	CARBON 8.2K 5% 1/4W	
R358	1-249-428-11	CARBON 8.2K 5% 1/4W	
R359	1-247-903-00	CARBON 1M 5% 1/4W	

Note:
The components identified by mark Δ or dotted line with mark Δ are critical for safety. Replace only with part number specified.

Note:
Les composants identifiés par une marque Δ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

MAIN FUNCTION DISPLAY DSP

Ref. No.	Part No.	Description	Remark		
R361	1-249-423-11	CARBON	3.3K	5%	1/4W
R362	1-249-423-11	CARBON	3.3K	5%	1/4W
R363	1-249-423-11	CARBON	3.3K	5%	1/4W
R364	1-249-423-11	CARBON	3.3K	5%	1/4W
R365	1-247-856-00	CARBON	11K	5%	1/4W
R366	1-247-856-00	CARBON	11K	5%	1/4W
R367	1-247-856-00	CARBON	11K	5%	1/4W
R368	1-247-856-00	CARBON	11K	5%	1/4W
R369	1-249-419-11	CARBON	1.5K	5%	1/4W
R370	1-249-419-11	CARBON	1.5K	5%	1/4W
R371	1-249-419-11	CARBON	1.5K	5%	1/4W
R372	1-249-419-11	CARBON	1.5K	5%	1/4W
R373	1-247-887-00	CARBON	220K	5%	1/4W
R374	1-247-887-00	CARBON	220K	5%	1/4W
R375	1-249-409-11	CARBON	220	5%	1/4W
R376	1-249-409-11	CARBON	220	5%	1/4W
R377	1-249-409-11	CARBON	220	5%	1/4W
R378	1-249-409-11	CARBON	220	5%	1/4W
R379	1-249-425-11	CARBON	4.7K	5%	1/4W
R380	1-249-425-11	CARBON	4.7K	5%	1/4W
R381	1-249-425-11	CARBON	4.7K	5%	1/4W
R382	1-249-425-11	CARBON	4.7K	5%	1/4W
R383	1-249-414-11	CARBON	560	5%	1/4W
R384	1-249-414-11	CARBON	560	5%	1/4W
R385	1-249-393-11	CARBON	10	5%	1/4W
R386	1-249-393-11	CARBON	10	5%	1/4W
R389	1-249-414-11	CARBON	560	5%	1/4W
R390	1-249-414-11	CARBON	560	5%	1/4W
R401	1-249-433-11	CARBON	22K	5%	1/4W
R402	1-249-433-11	CARBON	22K	5%	1/4W
R403	1-249-433-11	CARBON	22K	5%	1/4W
R404	1-249-425-11	CARBON	4.7K	5%	1/4W
R405	1-249-425-11	CARBON	4.7K	5%	1/4W
R406	1-249-425-11	CARBON	4.7K	5%	1/4W
R407	1-249-433-11	CARBON	22K	5%	1/4W
R408	1-249-441-11	CARBON	100K	5%	1/4W
R409	1-247-864-11	CARBON	24K	5%	1/4W
R410	1-247-880-11	CARBON	110K	5%	1/4W
R411	1-249-440-11	CARBON	82K	5%	1/4W
R412	1-247-876-11	CARBON	75K	5%	1/4W
R413	1-249-440-11	CARBON	82K	5%	1/4W
R414	1-247-874-11	CARBON	62K	5%	1/4W
R415	1-249-435-11	CARBON	33K	5%	1/4W
R416	1-247-878-00	CARBON	91K	5%	1/4W
R417	1-247-878-00	CARBON	91K	5%	1/4W
R418	1-247-878-00	CARBON	91K	5%	1/4W
R419	1-249-440-11	CARBON	82K	5%	1/4W
R420	1-249-440-11	CARBON	82K	5%	1/4W
R421	1-249-393-11	CARBON	10	5%	1/4W

Ref. No.	Part No.	Description	Remark		
R422	1-249-393-11	CARBON	10	5%	1/4W
R423	1-249-393-11	CARBON	10	5%	1/4W
R424	1-249-411-11	CARBON	330	5%	1/4W
R425	1-249-429-11	CARBON	10K	5%	1/4W
R426	1-249-429-11	CARBON	10K	5%	1/4W
R427	1-249-429-11	CARBON	10K	5%	1/4W
R428	1-249-429-11	CARBON	10K	5%	1/4W
R429	1-249-429-11	CARBON	10K	5%	1/4W
R430	1-249-429-11	CARBON	10K	5%	1/4W
R431	1-249-429-11	CARBON	10K	5%	1/4W
R432	1-249-429-11	CARBON	10K	5%	1/4W
R450	1-249-435-11	CARBON	33K	5%	1/4W
R451	1-249-441-11	CARBON	100K	5%	1/4W
R452	1-249-437-11	CARBON	47K	5%	1/4W
R453	1-249-405-11	CARBON	100	5%	1/4W
R454	1-249-405-11	CARBON	100	5%	1/4W
R460	1-249-435-11	CARBON	33K	5%	1/4W
R461	1-249-441-11	CARBON	100K	5%	1/4W
R462	1-249-437-11	CARBON	47K	5%	1/4W
R463	1-249-405-11	CARBON	100	5%	1/4W
R464	1-249-405-11	CARBON	100	5%	1/4W
R471	1-249-422-11	CARBON	2.7K	5%	1/4W
R472	1-249-424-11	CARBON	3.9K	5%	1/4W
R473	1-249-427-11	CARBON	6.8K	5%	1/4W
R474	1-249-432-11	CARBON	18K	5%	1/4W
R476	1-249-422-11	CARBON	2.7K	5%	1/4W
R477	1-249-424-11	CARBON	3.9K	5%	1/4W
R478	1-249-427-11	CARBON	6.8K	5%	1/4W
R479	1-249-432-11	CARBON	18K	5%	1/4W
R481	1-249-422-11	CARBON	2.7K	5%	1/4W
R482	1-249-424-11	CARBON	3.9K	5%	1/4W
R483	1-249-427-11	CARBON	6.8K	5%	1/4W
R484	1-249-432-11	CARBON	18K	5%	1/4W
R501	1-249-422-11	CARBON	2.7K	5%	1/4W
R502	1-249-424-11	CARBON	3.9K	5%	1/4W
R503	1-249-427-11	CARBON	6.8K	5%	1/4W
R504	1-249-432-11	CARBON	18K	5%	1/4W
R505	1-249-422-11	CARBON	2.7K	5%	1/4W
R506	1-249-424-11	CARBON	3.9K	5%	1/4W
R507	1-249-427-11	CARBON	6.8K	5%	1/4W
R508	1-249-432-11	CARBON	18K	5%	1/4W
R509	1-249-422-11	CARBON	2.7K	5%	1/4W
R805	1-249-409-11	CARBON	220	5%	1/4W
R806	1-249-425-11	CARBON	4.7K	5%	1/4W
R807	1-249-434-11	CARBON	27K	5%	1/4W
R808	1-249-430-11	CARBON	12K	5%	1/4W
R809	1-247-850-11	CARBON	6.2K	5%	1/4W
R810	1-247-844-11	CARBON	3.6K	5%	1/4W
R811	1-247-838-00	CARBON	2K	5%	1/4W

MAIN FUNCTION DISPLAY DSP POWER
HEADPHONE VOL HEADPHONE JACK

Ref. No.	Part No.	Description	Remark		
R812	1-249-416-11	CARBON	820	5%	1/4W
R901	1-249-417-11	CARBON	1K	5%	1/4W
R902	1-249-417-11	CARBON	1K	5%	1/4W
R903	1-249-417-11	CARBON	1K	5%	1/4W
R905	1-249-417-11	CARBON	1K	5%	1/4W
R908	1-249-429-11	CARBON	10K	5%	1/4W
R909	1-249-429-11	CARBON	10K	5%	1/4W
R910	1-249-429-11	CARBON	10K	5%	1/4W
R911	1-249-429-11	CARBON	10K	5%	1/4W
R912	1-249-429-11	CARBON	10K	5%	1/4W
R915	1-249-441-11	CARBON	100K	5%	1/4W
R916	1-249-441-11	CARBON	100K	5%	1/4W
R917	1-249-441-11	CARBON	100K	5%	1/4W
R918	1-249-405-11	CARBON	100	5%	1/4W
R919	1-249-405-11	CARBON	100	5%	1/4W
R921	1-249-417-11	CARBON	1K	5%	1/4W
R922	1-249-420-11	CARBON	1.8K	5%	1/4W
R923	1-249-417-11	CARBON	1K	5%	1/4W
R924	1-249-417-11	CARBON	1K	5%	1/4W
R925	1-249-417-11	CARBON	1K	5%	1/4W
R941	1-249-419-11	CARBON	1.5K	5%	1/4W
R943	1-249-441-11	CARBON	100K	5%	1/4W
R945	1-249-425-11	CARBON	4.7K	5%	1/4W
R946	1-249-425-11	CARBON	4.7K	5%	1/4W
R947	1-249-425-11	CARBON	4.7K	5%	1/4W
R948	1-249-421-11	CARBON	2.2K	5%	1/4W
R949	1-249-422-11	CARBON	2.7K	5%	1/4W
R950	1-247-836-11	CARBON	1.6K	5%	1/4W
R951	1-247-828-11	CARBON	750	5%	1/4W
R952	1-247-832-11	CARBON	1.1K	5%	1/4W
R953	1-249-410-11	CARBON	270	5%	1/4W
R971	1-249-419-11	CARBON	1.5K	5%	1/4W
R973	1-249-441-11	CARBON	100K	5%	1/4W
R975	1-249-425-11	CARBON	4.7K	5%	1/4W
R976	1-249-425-11	CARBON	4.7K	5%	1/4W
R977	1-249-425-11	CARBON	4.7K	5%	1/4W
R978	1-249-421-11	CARBON	2.2K	5%	1/4W
R979	1-249-422-11	CARBON	2.7K	5%	1/4W
R980	1-247-836-11	CARBON	1.6K	5%	1/4W
R981	1-247-828-11	CARBON	750	5%	1/4W
R982	1-247-832-11	CARBON	1.1K	5%	1/4W
R983	1-249-410-11	CARBON	270	5%	1/4W
< VARIABLE RESISTOR >					
RV801	1-241-509-11	RES. VAR. CARBON 10K (EFFECT MIN/MAX)			

Ref. No.	Part No.	Description	Remark
< SWITCH >			
S201	△ 1-571-722-11	SWITCH, VOLTAGE SELECTION (E)	
S471	1-554-303-21	SWITCH, TACTILE (1)	
S472	1-554-303-21	SWITCH, TACTILE (2)	
S473	1-554-303-21	SWITCH, TACTILE (3)	
S474	1-554-303-21	SWITCH, TACTILE (4)	
S475	1-554-303-21	SWITCH, TACTILE (5)	
S476	1-554-303-21	SWITCH, TACTILE (6)	
S477	1-554-303-21	SWITCH, TACTILE (7)	
S478	1-554-303-21	SWITCH, TACTILE (8)	
S479	1-554-303-21	SWITCH, TACTILE (9)	
S480	1-554-303-21	SWITCH, TACTILE (10)	
S481	1-554-303-21	SWITCH, TACTILE (>10)	
S482	1-554-303-21	SWITCH, TACTILE (MUSIC SCAN)	
S483	1-554-303-21	SWITCH, TACTILE (CHECK)	
S484	1-554-303-21	SWITCH, TACTILE (CLEAR)	
S485	1-554-303-21	SWITCH, TACTILE (FADER)	
S501	1-554-303-21	SWITCH, TACTILE (◀◀)	
S502	1-554-303-21	SWITCH, TACTILE (▶▶)	
S503	1-554-303-21	SWITCH, TACTILE (■)	
S504	1-554-303-21	SWITCH, TACTILE (OPEN/CLOSE ▲)	
S505	1-554-303-21	SWITCH, TACTILE (DISC SKIP)	
S506	1-554-303-21	SWITCH, TACTILE (EDIT/TIME FADE)	
S507	1-554-303-21	SWITCH, TACTILE (◀◀)	
S508	1-554-303-21	SWITCH, TACTILE (▶▶)	
S509	1-554-303-21	SWITCH, TACTILE (▶)	
S510	1-554-303-21	SWITCH, TACTILE (■)	
S511	1-554-303-21	SWITCH, TACTILE (TIME)	
S512	1-554-303-21	SWITCH, TACTILE (REPEAT)	
S801	1-554-303-21	SWITCH, TACTILE (HALL)	
S802	1-554-303-21	SWITCH, TACTILE (CHURCH)	
S803	1-554-303-21	SWITCH, TACTILE (JAZZ CLUB)	
S804	1-554-303-21	SWITCH, TACTILE (STADIUM)	
S805	1-554-303-21	SWITCH, TACTILE (DISCO)	
S806	1-554-303-21	SWITCH, TACTILE (FLAT)	
< CRYSTAL >			
X351	1-567-965-11	VIBRATOR, CRYSTAL (22.5MHz)	
X901	1-577-358-21	VIBRATOR, CERAMIC (4MHz)	

* 1-639-469-11	POWER SW BOARD	*****	
* 1-639-470-11	HEADPHONE VOL BOARD	*****	
* 1-639-471-11	HEADPHONE JACK BOARD	*****	
* 4-922-980-01	HOLDER (LED)		

<p>Note: The components identified by mark △ or dotted line with mark △ are critical for safety. Replace only with part number specified.</p>	<p>Note: Les composants identifiés par une marque △ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.</p>
--	---

POWER

HEADPHONE VOL

HEADPHONE JACK

TABLE MOTOR



LOADING MOTOR


OPEN/UP SW

Ref. No.	Part No.	Description	Remark
< CAPACITOR >			
C551	1-161-494-00	CERAMIC 0.022uF	25V
C701	1-162-291-31	CERAMIC 560PF 10%	50V
C702	1-162-291-31	CERAMIC 560PF 10%	50V
C703	1-164-159-11	CERAMIC 0.1uF	50V
C704	1-161-494-00	CERAMIC 0.022uF	25V
< CONNECTOR >			
CN702	* 1-568-832-11	SOCKET, CONNECTOR 13P	
< DIODE >			
D601	8-719-970-49	DIODE 8R4361F (VOL POINT)	
< IC >			
IC551	8-741-100-48	IC SBX1610-59	
< JACK >			
J701	1-568-519-21	JACK, LARGE TYPE (HEADPHONES) (C615)	
J701	1-568-519-41	JACK, LARGE TYPE (HEADPHONES) (C67ES)	
< RESISTOR >			
R551	1-249-422-11	CARBON 2.7K 5%	1/4W
R552	1-249-424-11	CARBON 3.9K 5%	1/4W
R553	1-249-427-11	CARBON 6.8K 5%	1/4W
R554	1-249-432-11	CARBON 18K 5%	1/4W
R555	1-249-422-11	CARBON 2.7K 5%	1/4W
R556	1-249-424-11	CARBON 3.9K 5%	1/4W
R557	1-249-427-11	CARBON 6.8K 5%	1/4W
< VARIABLE RESISTOR >			
RV701	1-238-750-11	RES. VAR. CARBON 10K/10K (PHONE/LINE OUT LEVEL)	
< SWITCH >			
S551	1-554-303-21	SWITCH, TACTILE (DISC 1)	
S552	1-554-303-21	SWITCH, TACTILE (DISC 2)	
S553	1-554-303-21	SWITCH, TACTILE (DISC 3)	
S554	1-554-303-21	SWITCH, TACTILE (DISC 4)	
S555	1-554-303-21	SWITCH, TACTILE (DISC 5)	
S556	1-554-303-21	SWITCH, TACTILE (CONTINUE)	
S557	1-554-303-21	SWITCH, TACTILE (SHUFFLE)	
S558	1-554-303-21	SWITCH, TACTILE (PROGRAM)	
S559	1-554-303-21	SWITCH, TACTILE (PEAK SEARCH)	
S560	1-572-714-11	SWITCH, PUSH (POWER ON/OFF)	

Ref. No.	Part No.	Description	Remark
* 1-638-729-11		TABLE MOTOR BOARD *****	
* 1-638-730-11		LOADING MOTOR BOARD *****	
* 1-638-731-11		OPEN/UP SW BOARD *****	
< CAPACITOR >			
C704	1-161-375-00	CERAMIC 0.0022uF 20%	50V
C705	1-161-375-00	CERAMIC 0.0022uF 20%	50V
< CONNECTOR >			
CN705	* 1-566-214-11	PIN, CONNECTOR (PC BOARD) 2P	
CN707	* 1-573-044-11	SOCKET, CONNECTOR	
< DIODE >			
D701	8-719-970-19	DIODE GP1A521	
< RESISTOR >			
R701	1-249-416-11	CARBON 820 5%	1/4W
< SWITCH >			
S702	1-571-300-21	SWITCH, ROTARY (OPEN/UP)	

MISCELLANEOUS *****			
12	1-590-834-11	WIRE, FLAT TYPE (13 CORE)	
13	1-590-835-11	WIRE, FLAT TYPE (34 CORE)	
54	1-452-340-21	MAGNET	
65	1-590-849-11	WIRE, FLAT TYPE (5 CORE)	
101	1-535-892-11	JUMPER, FILM (WITH TERMINAL)	
124	△ 1-574-358-31	CORD, POWER (WITH CONNECTOR) (Australian)	
124	△ 1-575-651-21	CORD, POWER (AEP)	
124	△ 1-575-653-21	CORD, POWER (E)	
124	△ 1-590-836-11	CORD, POWER (US, Canadian)	
125	△ 1-569-007-11	ADAPTOR, CONVERSION 2P (E)	
151	△ 8-848-144-11	DEVICE, OPTICAL XSS-240A	
152	1-575-001-11	WIRE, FLAT TYPE (12 CORE)	
M101	X-4917-504-1	MOTOR ASSY (SLED)	
M102	X-4917-523-3	MOTOR ASSY (SPINDLE)	
M701	A-4604-585-A	MOTOR ASSY, ROTARY (TABLE)	
M702	A-4604-834-A	MOTOR ASSY, LOADING	
S701	1-572-713-11	SWITCH, PUSH (WITH CONNECTOR) (DOWN)	
T901	△ 1-450-133-11	TRANSFORMER, POWER (US, Canadian)	
T901	△ 1-450-134-11	TRANSFORMER, POWER (AEP, Australia n)	
T901	△ 1-450-135-11	TRANSFORMER, POWER (E)	

Note:
The components identified by mark  or dotted line with mark  are critical for safety. Replace only with part number specified.

Note:
Les composants identifiés par une marque  sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

Ref. No.	Part No.	Description	Remark
ACCESSORY & PACKING MATERIAL			

	1-465-729-11	REMOTE COMMANDER	
	1-558-271-11	CORD. CONNECTION (C67ES)	
	1-559-533-11	CORD. CONNECTION (C615)	
	3-701-630-00	BAG, POLYETHYLENE	
	3-707-584-01	COVER, BATTERY	
	3-753-146-11	MANUAL, INSTRUCTION (English, French, Spanish, Portuguese) (AEP, E. Canadian)	
	3-753-146-21	MANUAL, INSTRUCTION (English) (C615:US, Australian)	
	3-753-146-41	MANUAL, INSTRUCTION (German, Dutch, Swedish, Italian) (AEP)	
	3-753-147-21	MANUAL, INSTRUCTION (English) (C67ES)	
	3-795-629-11	INSTRUCTION	
	4-937-945-01	PLATE (TRANSPORT), LOCK	
*	4-941-548-01	LABEL, CLASS 1 (AEP, E, Australian)	
*	4-944-109-41	INDIVIDUAL CARTON (C615)	
*	4-944-109-51	INDIVIDUAL CARTON (C67ES)	
*	4-944-110-01	CUSHION (FRONT)	
*	4-944-111-01	CUSHION (REAR)	

HARDWARE LIST

# 1	7-685-647-79	SCREW +BVTP 3X10 TYPE2 N-S
# 2	7-682-548-04	SCREW +BVTT 3X8 (S)
# 3	7-685-870-01	SCREW +BVTT 3X5 (S)
# 4	7-685-648-79	SCREW +BVTP 3X12 TYPE2 N-S
# 5	7-682-554-04	SCREW +B 3X25
# 6	7-685-648-79	SCREW (M3X12), TAPPING
# 7	7-685-136-19	SCREW +P 2.6X12 TYPE2 NON-SLIT
# 8	7-685-647-79	SCREW, TAPPING
# 9	7-621-255-15	SCREW +P 2X3
# 10	7-685-134-19	SCREW +BTP 2.6X8 TYPE2 N-S
# 11	7-683-401-04	BOLT, HEXAGON SOCKET 3X4 (C67ES)