

Model 857T, Chassis RE 378, is electrically similar to sets described on this page. If differs in physical respects and has a phono jack.

ALIGNMENT PROCEDURE

Output meter connection	Across speaker voice coil
Output meter reading to indicate 500 milliwatts (standard output)	1.26 volts
Connection of generator ground lead	Floating ground
Generator modulation	30% 400 cycles
Position of volume control	Fully clockwise

Position of Variable	Frequency of Generator	Dummy Antenna	Generator Output Connection	Trimmers Adjusted in order Shown for Maximum Output	Function of Trimmer
Open	455	.05 $\mu$ f	Pin 7 12BE6	A1, A2, A3, A4	I. F. Oscillator
Open	1650		* Test Loop	A5	Antenna
1400	1400		* Test Loop	A6 on	
600	600		* Test Loop	Check Point	

\* Standard Hazeltine Test Loop Model 1150 or 3 turns of wire about 6" in diameter placed about one foot from the set loop.

