

## Model 171

## Specifications

Model 171 is a twelve tube dual band superheterodyne designed for operation from A.C. electric circuits. The intermediate frequency is 181.5 Kc.

## Voltages and Tube Limits

The following are the tubes and voltages measured with the receiver in operating con-

dition but with no signal to the antenna circuit, and with a line voltage of 117.5 volts (235 volts for 220 volt receivers). All voltages, except filament are measured with a 500 volt D.C. voltmeter (1000 ohms per volt) from tube contact to chassis. Filament voltages are measured with a low range A.C. voltmeter.

Tube	Position	Plate	Screen Grid	Cathode	Suppressor Grid	Filament
58	R. F. Amplifier	267	115	3.0	3.0	2.5
56	Oscillator	60		7.0		2.5
58	Modulator	267	115	5.5	5.5	2.5
58	I. F. Amplifier	267	115	4.5	4.5	2.5
2B7	A. V. C. Tube	267	115	4.5	4.5	2.5
56	QAVC Tube	70		0-20.0*		2.5
56	Detector	0		0		2.5
56	Phase Shifter	58		2.5		2.5
56	A. F. Amplifier	170		115		2.5
2-2A5	Output	260	267	17.5		2.5
80	Rectifier	355				4.9

**Voltage limits are plus or minus 10% of values given.**

\*Voltage depends on position of "Q" control.

