



Hoffman
RADIO CORP.

LOS ANGELES, CALIFORNIA

SYMBOL	DESCRIPTION
C1-C2-C3	Three-Section Variable (388-388-180 Mmf.)
C4, C5, C6	Trimmers; Part of Variable Condenser
C7, C8	.05 Mfd, 200 Volt, Tubular Paper
C9, C12, C13, C15	100 Mmf. ± 20%, Mica
C10-C11	.05 Mfd, 400 Volt, Tubular Paper
C14, C16	.005 Mfd, 600 Volt, Tubular Paper
C17	.01 Mfd, 600 Volt, Tubular Paper
C18-C19-C20	Dry Electrolytic Condenser (20-20-20 Mfd 450-450-25 Volt)
C21	.001 Mfd, 600 Volt, Tubular Paper
C22	.01 Mfd, 600 Volt, Tubular Paper (Metal Can)
C23	500 Mmf. ± 5%, Silver Mica
L1	Oscillator Coil
L5	Loudspeaker, 5" P.M.
R1, R8	.22 Megohm ± 20%, ½ Watt
R2	22,000 Ohm ± 20%, ½ Watt
R3	2.2 Megohm ± 20%, ½ Watt
R4	10,000 Ohm ± 10%, 2 Watt
R5	47,000 Ohm ± 20%, ½ Watt
R6	.5 Megohm Potentiometer (Volume)
R7	10 Megohm ± 20%, ½ Watt
R9	.47 Megohm ± 20%, ½ Watt
R10	560 Ohm ± 10%, ½ Watt
R11	.25 Megohm Potentiometer With Switch (Tone)
R12	47 Ohm ± 20%, ½ Watt
R13	330 Ohm ± 20%, ½ Watt
R14	1500 Ohm ± 5%, 6½ Watt

MODEL A301 CHASSIS No. 101S

Hoffman Model 301 with Chassis 101S is electrically identical to Chassis 100, except for the speaker used and the use of a 1500 ohm resistor instead of the 1500 ohm speaker field winding.

Hoffman
RADIO CORP.

LOS ANGELES, CALIFORNIA