GENERAL ELECTRIC CO.

MODEL L-678





IF PEAK 455 KC

Stock No	Symbol	Description	List Price
*RC-7017	C-1, -2	CONDENSER—Tuning Condenser	$5.80
*RC-6515	C-3	CAPACITOR—Oscillator padder	.30
*RC-072	C-4	CAPACITOR—.05 Mfd., 200 V. paper	.25
*RC-130	C-5	CAPACITOR—0.2 Mfd., 400 V. paper	.30
*RC-023	C-6, 7	CAPACITOR—.005 Mfd., 600 V. paper	.25
*RC-039	C-8	CAPACITOR—.01 Mfd., 600 V. paper	.25
*RC-5145	C-9a	CAPACITOR—30 Mfd., 150 V.	.75
*RC-5145	C-9b	CAPACITOR—50 Mfd., 150 V.	
*RC-092	C-11	CAPACITOR—.05 Mfd., 600 V. paper	.30
*RC-060	C-13	CAPACITOR—.03 Mfd., 600 V. paper	.25
*RC-293	C-14	CAPACITOR—470 Mmf., mica	.30
*RC-250	C-15	CAPACITOR—220 Mmf., mica	.25
*RC-216	C-16	CAPACITOR—47 Mmf., mica	.25
*RC-104	C-17	CAPACITOR—0.1 Mfd., 400 V. paper	.30
*RC-226	C-20	CAPACITOR—10 Mmf., mica	.25
*RQ-1295	R-1	CAPACITOR—33,000 ohms, ½ W. carbon	.70–5
*RQ-1339	R-2	RESISTOR—2.2 megohm, ½ W. carbon	.70–5
RV-119	R-3, S-1	VOLUME CONTROL—0.5 megohm potentiometer	1.45
*RQ-1365	R-4	RESISTOR—15 megohm, ½ W. carbon	.70–5
*RQ-1323	R-5	RESISTOR—470,000 ohms, ½ W. carbon	.70–5
*RQ-1331	R-6	RESISTOR—1.0 megohm, ½ W. carbon	.70–5
*RQ-1271	R-7	RESISTOR—3,300 ohms, ½ W. carbon	.70–5
*RQ-1297	R-8	RESISTOR—39,000 ohms, ½ W. carbon	.70–5
*RQ-1323	R-9	RESISTOR—470,000 ohms, ½ W. carbon	.70–5
*RQ-1239	R-10	RESISTOR—150 ohms, ½ W. carbon	.70–5
*RQ-1459	R-11	RESISTOR—1,000 ohms, 1 W. carbon	.20
*RQ-1323	R-12	RESISTOR—470,000 ohms, ½ W. carbon	.70–5
*RQ-1307	R-13	RESISTOR—100,000 ohms, ½ W. carbon	.70–5
*RR-773	R-14	RESISTOR—BL42B Ballast resistor	.40
*RL-528	L-1	LOOP—Built-in antenna and back cover assembly	1.00
*RL-2016	L-2	COIL—Oscillator coil	.25
*RT-341	L-3	TRANSFORMER—1st I.F. transformer	.80
*RT-342	L-4	TRANSFORMER—2nd I.F. transformer	.80
*RT-475	T-1	TRANSFORMER—Output transformer	1.00

FOR OTHER DATA SEE INDEX



MOTOR ASSEMBLY MODEL 1 (60-cycle only)

*RB-187	BRACKET—Rubber-edged drive wheel bracket assembly	$0.20
*RB-188	BRACKET—Rubber edged idler wheel bracket assembly	.20
*RB-627	BUSHING—Motor mtg. rubber bushing	.20–5
*RC-5146	CAPACITOR—Motor capacitor	1.00
*RH-112	HAIRPIN COTTER—Rubber wheel hairpin cotter	.10–10
*RM-129	MOTOR—60-cycle motor complete	4.50
*RP-157	PLATE—Motor mounting plate and spindle bearing assembly	.90
*RS-471	SPRING—Idler wheel bracket tension spring	.30–5
*RS-934	SPINDLE—Turntable spindle and snap ring	.30
*RT-916	TURNTABLE—8-inch flocked turntable	1.60
*RW-910	WHEEL—Rubber-edged wheel	.35



MOTOR ASSEMBLY—MODEL 2

(60-cycle and 50-cycle)

*RM-133	MOTOR—60-cycle motor assembly complete	$4.75
RM-152	MOTOR—50-cycle motor assembly complete	5.25
*RP-165	PLATE—Main plate and turntable shaft bearing assembly	1.00
*RP-166	PLATE—Motor mounting plate	.35
*RP-167	PLATE—Rubber-edged wheel movable plate and bearing assembly	.80
*RP-316	PULLEY—60-cycle drive pulley	.15
RP-333	PULLEY—50-cycle drive pulley	.35–2
*RS-493	SPRING—Movable plate tension spring	.10
*RS-943	SPINDLE—Turntable spindle and cotter	.25
*RS-953	SPACERS—Rotor spacers between bearings	.15–5
*RT-924	TURNTABLE—8-inch turntable	1.50
*RW-912	WHEEL—Rubber-edged wheel, washer, oil felt and cotter	1.50

(PRICES SUBJECT TO CHANGE WITHOUT NOTICE)



Fig. 1. Trimmer Location