


[illegible]

**MODELS 5A410, 5A430
CHASSIS 4501, 4504**



TUBE	ELEMENT	PIN	VOLTS
12SA7	Plate	3	80-89
	S. Grid	4	80-89
	Grid	5	.7
12SK7	Plate	8	80-89
	S. Grid	6	80-89
	Grid	4	.65
12SQ7	Plate	6	55-65
	Grid	2	.8
50L6	Plate	3	110-118
	S. Grid	4	80-89

STEP	DUMMY ANT.	TEST OSC. CONNECTION	TEST OSC. FREQUENCY	RECEIVER DIAL	ADJUST	REMARKS
1	.01 mfd.	12SA7 grid (pin No.5)	455 kc. modulated	Any quiet spot	C13,C12,C9,C8 for max. output	Repeat in reverse order
2	-----	Loop*	1500 kc. modulated	150	C5 for maximum output	
3	-----	Loop*	1500 kc. modulated	150	C2 for maximum output	Rock gang while adjusting
4	REPEAT COMPLETE ALIGNMENT PROCEDURE CAREFULLY					

* Make a two or three turn loop about 12 inches in diameter. Connect to output terminals of the signal generator. Place this loop in a plane parallel to the receiver loop antenna and about a foot away from the receiver loop.

**MODELS 5A410, 5A430
CHASSIS 4501, 4504**