



MODEL P--later production differs from earlier type as follows--uses types 77, 78 and 6Z5 tubes in place of types 36 and KR-1. The type 78 is used in the R.F. stage. The screen voltage has been dropped on this tube through a 50K ohm resistor R-248 which is by-passed by an .01 Mfd. condenser A-311. The voltage on the screen is about 55 volts with the volume full on. The voltages and connections to the detector socket are the same as in the earlier models. The tube is now a 77.

