

GAMBLE-SKOGMO INC.

MINNEAPOLIS, -- MINNESOTA

Model 1682A

Generator Frequency	Connection at Radio	Dummy Antenna	Range Switch Setting	Dial Setting	Trimmers to Tune	Approx. Sensitivity .05 Watt O. P
I. F. 456 k.c.	Center Stator of Var. Cond.	.1 Mfd.	B. C.	H. F. End	I. F. Trans. Tune to Max.	65 to 75 Mv.
B. C. 1650 k.c.	Ant.	200 Mmf.	B. C.	H. F. Limit of Travel	B., C. Osc.	—
1400 k.c.	"	"	"	1400— See Note "A"	B. C. RF. " " Loop Tune to Max.	20 Mv.
600 k.c.	"	"	"	600— Rock Rotor	Padder	15 Mv.
11.6 m.c.	Ant.	400 Ohms	S. W.	11.6 m.c.	S. W. Osc	40 to 50 Mv.
9.6 m.c.	Ant.	400 Ohms	S. W.	Check Dial at 9.6 Mc.		

