

Models 6158, 6159,  
6192.

<u>WAVE BAND- SWITCH POSITION</u>	<u>POSITION OF VARIABLE</u>	<u>GENERATOR FREQUENCY</u>	<u>DUMMY ANTENNA</u>	<u>GENERATOR CONNECTION</u>	<u>TRIMMERS ADJUSTED (IN ORDER SHOWN)</u>	<u>TRIMMER FUNCTION</u>	<u>APPROXIMATE MICROVOLTS</u>
"AM"	Closed	455 kc	.1 mfd.	6A8G Grid	T2, T1	IF Output IF Input	810
"SW"	15 mc(rock)	15 mc	400 ohms.	Ant. Term.	C13	Translator	40
"9"	9.55 mc	9.55 mc	400 ohms.	Ant. Term.	C9*	Oscillator	60
					C16	Translator	
"11"	11.71 mc	11.71 mc	400 ohms.	Ant. Term.	C7*	Oscillator	40
					C15	Translator	
"15"	14.9 mc	14.9 mc	400 ohms.	Ant. Term.	C5*	Oscillator	40
					C14	Translator	
"AM"	1400 kc	1400 kc	.0002 mfd.	Ant. Term.	C17, C13, C1	Osc., Transl., RF	30
"AM"	600 kc(rock)	600 kc	.0002 mfd.	Ant. Term.	C18	Padder	40

## WIRING DIAGRAM FOR SILVERTONE CHASSIS 101.555

