


MODELS 801,802
Schematic,Voltage
Parts



PART NO.	DESCRIPTION	PART NO.	DESCRIPTION	PART NO.	DESCRIPTION
1001-E	Universal Transformer	1110	Volume Control and switch	250,000 ohm 1/3 watt	
1102	3 Gang Geared Condenser	1114-A	Sensitivity Control	100,000 ohms 1/3 watt	
*1104	B.C. & L.W. Antenna Coil	1034	Phono-radio switch	50,000 ohms 1/3 watt	
*1105	B.C. & L.W. R.F. Coils	1111	Candohm Resistor	6,000 ohms 1/3 watt	
*1106	B.C. & L.W. Oscillator Coils	1112	3 Gang Switch	50 ohms 1/3 watt	
1107	Iron Core Expanded I.F.	1113	Band Indicator	20,000 ohms 1 watt	
9021	Triple Tuned Output I.F.	1114	8-1/2 inch Dynamic Speaker Mica	50 M.M.F.	
1108	6-1/2 inch dial assembly	Condensers	25 MFD 350V wet electrolytic	100 M.M.F.	
*802-4	4 Band Translucent Scale		condenser	250 M.M.F.	
*8021	Dual Padder Condenser		8 MFD 450V wet electrolytic	.0015 M.F.D.	
1064	Isolantite Trimmer		condenser		
1170	H.F. Antenna Coil (10 to 28 meters)		2/10 400V Cub Condenser		
1171	H.F. R.F. Coil (10-28 meters)		2/10 200V Cub Condenser		
1172	H.F. Oscillator Coil (10-28 meters)		1/10 400V Cub Condenser		
1173	S.W. Antenna Coil (27-77 meters)		1/10 200V Cub Condenser		
1174	S.W. R.F. Coil (27-77 meters)		.05 400V Cub Condenser		
1175	S.W. Oscillator Coil (27-77 meters)		.01 400V Cub Condenser		
1109	Tone Control and S.P. D.T. Switch		.004 800V Cub Condenser		
		Resistors	1 megohm 1/3 watt		
			500,000 ohm 1/3 watt		

*Used only on Model 802

FOR MODEL 801 ONLY

1183 B.C. Antenna Coil

1184 B.C. R.F. Coil

1185 B.C. Oscillator Coil

1038-C 300-800 M.M.F. padder condenser

801-3 3-band translucent scale

1106
0-0.1W
8021 DUAL
PADDER COND