

IF 262 KC.

Model 830 Schematic Diagram Parts List

Diag. No.	Part No.	Description
1	1X4068	Antenna Coil & Shield Assembly
2	1X4051	R.F. Coil & Shield Assembly
3	1X4042	Oscillator Coil & Shield Assembly
4	1X4033	I.F. Coil & Shield Assembly
5	1X4022	Diode Coil & Shield Assembly
6	25B4368	Power Transformer
7	25A4019	Output Transformer
8	24A4290	Vibrator Choke
9	1X4080	"A" Choke Assembly
10	50B4150	Speaker (5½" Dynamic)
11	23A5186	Electrolytic Condenser
12	19B4110	Variable Condenser
13	8A3310	Tub. Cond. (.1-200)
14	8A4092	Tub. & Strap (.1-300)
15	8A3305	Tub. Cond. (.05-100)
16	8A1400	Tub. Cond. (.01-100)
17	8A3329	Tub. Cond. (.01-.0005-400)
18	8A4089	Tub. Cond. (.25-100)

Diag. No.	Part No.	Description
19	8A4093	Tub. & Strap (.01-1600)
20	8A4020	Tub. & Strap (.5-100)
21	65X4165	Fuse (15 amp.)
22	6B6013	Carbon Res. (15,000-1/2-20) N.I.
23	6B6012	Carbon Res. (33,000-1/2-20) Ins..
24	6B6008	Carbon Res. (300-1/2-20) Ins.
25	6B6081	Carbon Res. (68-1/3-20) N.I.
26	6B6009	Carbon Res. (330-1/2-20) N.I.
27	6B6004	Carbon Res. (1 meg-1/2-20) Ins.
28	6B6015	Carbon Res. (220,000-1/2-20) Ins.
29	6B6011	Carbon Res. (470,000-1/3-20) N.I.
30	6B6006	Carbon Res. (2,200-1-20) N.I.
31A	6B6005	Carbon Res. (50-1/2-20) N.I.
31B	6B6005	Carbon Res. (50-1/2-20) N.I.
32	6B6010	Carbon Res. (330-1/2-20) Ins.
33	18A4046	Volume Control & Switch (.5 meg)
34	48A5333	Vibrator

Motorola

AMERICA'S FINEST AUTO RADIO

MODEL 8-30