



MONTGOMERY WARD

CONDENSERS

RESISTORS

MODEL 04BR-570A

PARTS

- R1 BE13022 5M ohm— $\frac{1}{2}$ watt
- R2 BE130166 150 ohm— $\frac{1}{2}$ watt
- R3 BE13012 50M ohm— $\frac{1}{2}$ watt
- R4 BE13026 1000 ohm— $\frac{1}{2}$ watt
- R5 BE130157 12M ohm— $\frac{1}{2}$ watt
- R6 BE1304 3 megohm— $\frac{1}{2}$ watt
- R7 BE130168 100 ohm— $\frac{1}{2}$ watt
- R8 BE130168 100 ohm— $\frac{1}{2}$ watt
- R9 BE101225 1 megohm volume control
- R10 BE130233 60 ohm— $\frac{1}{2}$ watt
- R11 BE130233 60 ohm— $\frac{1}{2}$ watt
- R12 BE130223 10 megohm— $\frac{1}{2}$ watt
- R13 BE13037 750M ohm— $\frac{1}{2}$ watt
- R14 BE13011 250M ohm— $\frac{1}{2}$ watt
- R15 BE13079 400 ohm— $\frac{1}{2}$ watt
- R16 BE130222 350 ohm— $\frac{1}{2}$ watt
- R17 BE130235 1500 ohm— $\frac{1}{2}$ watt

- T1 BE111187 Loop Antenna Assembly
- T2 BE110155 Oscillator Coil
- T3 BE108129C Input I.F. Coil—455 kc.
- T4 BE108130D Output I.F. Coil—455 kc.
- T5 BE105113 Output Transformer
- T6 BE114205 5" P.M. Speaker
- T7 BE104216 Power Transformer
- L1 BE12312 R.F. Choke
- L2 BE10566 R.F. "A" Choke
- L3 BE10568 R.F. Choke
- L4 BE10566 R.F. "A" Choke
- P1 BE12626 Plug-in Vibrator Unit

- C BE102134 2 gang variable condenser
- C1 BE1009 .05 x 200 volts
- C2 Antenna trimmer on gang
- C3 Oscillator trimmer on gang
- C4 BE10020 .1 x 200 v.
- C5 BE1295 .0001 mica
- C6 BE10020 .1 x 200 v.
- C7 BE10013 .05 x 400 v.
- C8 BE10031 .5 x 120 v.
- C9 BE10031 .5 x 120 v.
- C10 BE10073 .008 x 1200 v.
- C11 BE12951 .000125 mica
- C12 BE10012 .003 x 600 v.
- C13 BE12960 .00015 mica
- C14 BE10011 .01 x 400 v.
- C15 BE10020 .1 x 200 v.
- C16 BE11911 20 mfd. lytic—25 w. v.
- C17 BE11911 40 mfd. lytic—200 w. v.
- C18 BE11911 20 mfd. lytic—200 w. v.
- C19 BE11911 20 mfd. lytic—200 w. v.
- C20 BE10019 .006 x 600 v.
- C21 BE10020 .1 x 200 v.

C16, C17, C18, C19 are in same unit