



audio output. INTERMEDIATE FREQUENCY: 455 K. C.  
TUNING RANGE: 540 to 1550 K. C.  
BATTERY CURRENT: "A" 200 M. A. "B" 5.6 M. A.



**Model PT-66** is a five tube, electric push-button tuning, superheterodyne radio with a manual tuning range covering 540 to 1580 K. C.

Six electric push-buttons are provided on this model. Five of the push-buttons are used for stations and one push-button for selecting dial tuning. The push-buttons cover a frequency range as follows: 540 to 1600 kilocycles.



SCHE. No.	DESCRIPTION	PART No.	SCHE. No.	DESCRIPTION	PART No.
1	Loop Antenna Assembly	32-3186	21	Resistor (130 ohms, ½ watt)	33-113338
2	Tuning Condenser	31-2449	22	Tubular Condenser (.04 mf., 400 v.)	30-4119
3	Tubular Condenser (.05 mf., 200 v.)	30-4519			
4	Tubular Condenser (.25 mf., 400 v.)	30-4804	23	Output Transformer	
5	Resistor (32,000 ohms, ½ watt)	33-322154		(for Speaker 36-1469-1)	32-8047
6	Mica Condenser (110 mmf.)	30-1130		(for Speaker 36-1469-9)	32-8044
7	Oscillator Transformer	32-3152		(for Speaker 36-1469-2)	32-8044
8	Tubular Condenser (.05 mf., 200 v.)	30-4519	24	Speaker	36-1469
9	1st I. F. Transformer	32-3177		Cone Assembly	
10	2nd I. F. Transformer	32-3178		(for Speaker 36-1469-9)	36-4113
11	Resistor (2.2 mega., ½ watt)	33-522154		(for Speaker 36-1469-1)	36-4115
12	Mica Condenser (250 mmf.)	61-0033		(for Speaker 36-1469-2)	36-4112
13	Resistor (27,000 ohms, ½ watt)	33-327334	25	Tubular Condenser (.04 mf., 400 v.)	30-4119
14	Volume Control (500,000 ohms)	33-5306	26	Electrolytic Condenser	
15	Tubular Condenser (.01 mf., 200 v.)	30-4479	27	(20-20 mf., 150 v.)	30-2332
16	Resistor (4.7 mega., ½ watt)	33-537154	28	Pilot Coil—Part of Speaker No.	36-1469
17	Resistor (220,000 ohms, ½ watt)	33-422154	28	Pilot Lamp	34-2098
18	Tubular Condenser (.01 mf., 400 v.)	30-4572	29	Line Resistor	33-3387
19	Mica Condenser (<250 mmf.)	61-0033	30	Push Button Switch	42-1485
20	Resistor (470,800 ohms, ½ watt)	33-447154	31	Padding Condenser Strip	31-6296