

Note (A)—This capacity obtained by pair twisted wires

RESISTANCE VALUES (OHMS)	
(1)	20,000 VOL. CONT.
(8)	8,000
(9)	20,000
(11)	25,000
(17)	4000,000
(21)	1,000,000
(22)	10,000
(24)	240,000
(25)	490,000
(32)	925 (WIRE WOUND)

FIXED CONDENSER VALUES (MFD)	
(5)	.000325
(7)	.001
(10)	.09–.09
(23)	A–.001–B–.015
(26)	.006
(31)	.015–.015



PHILCO

MODEL 57

No. on Figs.	Description	Part No.
(1)	Volume Control and "On-Off" Switch	33-5011
(2)	Antenna Transformer	32-1153
(3)	Tuning Condenser Assembly	31-1035
(4)	Compensating Condenser (Antenna; Part of (3))	
(5)	Condenser	30-1004
(6)	Wave Band Switch	42-1027
(7)	Condenser	5215
(8)	Resistor (Gray-Black-Red)	5838
(9)	Resistor (Red-Black-Orange)	6650
(10)	Condenser (Double)	4989-C
(11)	Resistor (Red-Green-Orange)	3656
(12)	Compensating Condenser (I. F. Primary)	04000-A
(13)	Oscillator Coil	32-1023
(14)	Compensating Cond. (High Frequency—1400 kilocycles) (Part of (3))	
(15)	Compensating Cond. (Low Frequency)	04000-S
(16)	I. F. Transformer	32-1155
(22)	Resistor (Yellow-Black-Green)	6010

No. on Figs.	Description	Part No.
(18)	Compensating Cond. (I. F. Secondary)	04000-D
(19)	Compensating Condenser	04000
(21)	Resistor (Brown-Black-Green)	4409
(22)	Resistor (Brown-Black-Orange)	4412
(18)	Condenser (Double)	7762-B
(24)	Resistor (Red-Yellow-Yellow)	4410
(25)	Resistor (Yellow-White-Yellow)	3769
(26)	Condenser	7625-E
(27)	Output Transformer	32-7041
(28)	Voice Coil and Cone Assembly	36-3029
(29)	Field Coil and Pot Assembly	36-3081
(30)	Electrolytic Condenser (Double)	30-2004
(31)	Condenser (Double)	3793-R
(14)	Resistor (Wire Wound)	7465
(30)	Power Transformer	32-7046
	Tube Shield	28-1107
	Four Prong Socket	7544
	Six Prong Socket	7547