



No. on Figs.	Description	Part No.
1	Wave Trap.....	38-5199
2	Wave-band Switch.....	42-1066
3	Resistor (10,000 ohms) (Brown-Black-Orange).....	33-1000
4	Antenna Transformer.....	32-1412
5	Condenser (.000015 Mfd.).....	30-1030
6	Tuning Condenser Assembly.....	31-1231
7	Compensating Condenser (ANT.).....	Part of 8
8	Resistor (200 ohms Flexible) (Red-Black-Brown).....	7217
9	Condenser (.05 Mfd. Tubular).....	30-4020
10	Resistor (50,000 ohms) (Green-Green-Orange).....	6098
11	Compensating Condenser (OSC. HF).....	Part of 8
12	Condenser (.003 Mfd. Mica).....	30-1022
13	Compensating Condenser (Osc. I. F.).....	04000-S
14	Condenser (.0008 Mfd. Mica).....	5878
15	Resistor (32,000 ohms) (Orange-Red-Orange).....	5279
16	Oscillator Transformer.....	32-1413
17	Compensating Condenser (1st I. F. Pri.).....	04000M
18	1st I. F. Transformer.....	32-1414
19	Compensating Condenser (1st I. F. Secondary).....	04000M
20	Resistor (400 ohms Flexible).....	33-3016
21	Condenser (.05 Mfd. Tubular).....	30-4020
22	Compensating Condenser (2d I. F. Primary).....	04000M
23	2d I. F. Transformer.....	32-1415
24	Compensating Condenser (2d I. F. Secondary).....	04000J
25	Resistor (50,000 ohms) (Green-Brown-Orange).....	6098
26	Condenser (.0001 Mfd. Twin Bakelite Block).....	8035-B
27	Condenser (.1 Mfd. Tubular).....	30-4170
28	Resistor (70,000 ohms) (Violet-Black-Orange).....	33-1115
29	Resistor (70,000 ohms) (Violet-Black-Orange).....	33-1115
30	Condenser (.00011 Mfd. Mica).....	30-1006
31	Condenser (.02 Mfd. Tubular).....	30-4113
32	Resistor (500,000 ohms) (Yellow-White-Yellow).....	6097
33	Tone Control.....	30-4192
34	Condensers in Tone Control.....	Inside 35

No. on Figs.	Description	Part No.
35	Output Transformer.....	32-7019
36	Voice Coil & Cone Assembly (8-12).....	36-3014
37	Field Coil and Pot. Assembly (8-12).....	36-3341
38	Resistor (2 Megohms) (Red-Black-Green).....	33-1025
39	Volume Control and On-Off Switch.....	33-5006
40	Condenser (.01 Mfd.) (Bakelite Block).....	3903-AB
41	Resistor (1 Megohm) (Brown-Black-Green).....	33-1096
42	Condenser (.1 Mfd.).....	30-4122
43	Resistor (.1 Meg.) (White-White-Orange).....	6099
44	Resistor (B. C. Wire-wound) (22, 235 ohms).....	33-3037
45	Resistor (.1 Meg.) (White-White-Orange).....	6099
46	Condenser (.05 Mfd. Tubular).....	30-4123
47	Resistor (37,000 ohms) (Orange-Violet-Orange).....	33-1098
48	Filter Choke.....	32-7018
49	Condenser (Electrolytic—6 Mfd.).....	30-2021
50	Condenser (Electrolytic—8-8 Mfd.).....	30-2028
51	Condenser (.09 Mfd. Bakelite Block).....	4989-D
52	Power Transformer.....	8046
53	Condenser (.015 Mfd. Bakelite Block).....	3793-W
54	Condenser (.05 Mfd. Tubular).....	30-4020
55	Dial Light.....	6608
56	Four Prong Socket.....	7544
57	Six Prong Socket.....	7547
58	Seven Prong Socket.....	27-6005
59	Tube Shield.....	28-1107
60	Chassis Mounting Screw.....	W-567
61	Chassis Mounting Washer (Metal).....	W-315
62	Chassis Mounting Washer (Rubber).....	5189
63	Knob (Large).....	27-4051
64	Knob (Small).....	27-4052
65	Dial Assembly.....	31-1234
66	Dial Scale.....	27-5087
67	A. C. Cord and Plug Assembly.....	L-943A