


Model No. D2325-A



| SIGNAL GENERATOR | | | | TUNER SETTING | ADJUST FOR MAXIMUM OUTPUT |
|------------------|----------------------|---|----------------|-----------------------------------|-----------------------------------|
| FREQUENCY | COUPLING CAPACITY | CONNECTION TO RADIO | GROUND SIDE | | |
| I.F. | 455 KC | .1 mfd. | Pin 7 6BE6 | GANG OPEN (plates out of mesh) | Top and Bottom cores T4 and T5 |
| Osc. | 1620 KC | .1 mfd. | Pin 7 6BE6 | GANG OPEN (plates out of mesh) | C2C Osc. trimmer on gang |
| R.F. | 1400 KC | .1 mfd. | Pin 1 6BA6 | TUNE TO (1400 KC signal) | C2B R.F. trimmer on gang |
| Ant. | 1400 KC | Connect 3 turn loop to generator place near loop on receiver | | TUNE TO (1400 KC signal) | C2A Antenna trimmer on gang |

