



DIAG NO	PART NO	DESCRIPTION	DIAG NO	PART NO	DESCRIPTION
C1	22-305	2-3.5MMFD TRIMMER	1	20-133	WAVE TRAP ASSEM
C2	250	0.5 MFD 200V	2	20-134	ANTENNA CHOKE
C3	212	0.5 MFD 400V	3	20-4362	ANTENNA COIL ASSEM
C4	205	200-550MFD PADDER	4	85-89	BAND SELECTOR SWITCH
C5	384	0015 MFD 600V	5	95-349	1ST I.F. TRANSFORMER
C6	485	0.05 MFD 600V	6	95-550	2ND I.F. TRANSFORMER
C7	127	25 MMFD 600V	7	25-351	POWER TRANS 115V 50-60 CYCLE
C8	486	0012 MFD 600V	8	95-361	POWER TRANS 250V ALL VOLT
C9	188	02 MFD 400V	9	44-7	PHONO JACK
C10	162	0001 MFD 600V	10	85-39	PHONO SWITCH
C11	147	0005 MFD 600V	11	9-363	OSC COIL ASSEM
C12	435	02 MFD 600V			
C13	198	2 MFD 200V			
C14	82	001 MFD 600V			
C15	494	1 MFD 600V			
C16	506	16 MFD ELEC COND WRT 250V			
C17	408	2-35MMFD TRIMMER COND			
C18	482	2-GANG VARIABLE COND			
C19	505	12 MFD ELEC COND WRT 325V			
C20	170	1 MFD 400V			
C21	487	0.5 MFD (BRAID LEADS) 400V			
R1	65-362	400 OHMS 1/4 W			
R2	280	49 M OHMS 1/4 W			
R3	373	11 M OHMS 1/2 W			
R4	263	30 M OHMS 1/2 W			
R5	293	990 M OHMS 1/4 W			
R6	320	400 M OHM VOL CONTR SW			
R7	518	990 OHMS 1/4 W			
R8	258	490 M OHMS 1/4 W			
R9	321	50 M OHM TONE CONTROL			
R10	378	190 M OHMS 1/4 W			
R11	486	80 M OHMS 1 W			

SWITCH ON VOLUME CONTROL

A C SUPPLY

DIAL LIGHTS

SPEAKER FIELD 2125 OHM

I.F. FREQUENCY 450 KC

5 TUBE SUPERHETERODYNE-3 BANDS

CHASSIS NO 5516

ZENITH RADIO CORPORATION  
CHICAGO, ILLINOIS

