



| DIAG. N ^o | PART N ^o | DESCRIPTION | DIAG. N ^o | PART N ^o | DESCRIPTION | DIAG. N ^o | PART N ^o | DESCRIPTION | DIAG. N ^o | PART N ^o | DESCRIPTION |
|----------------------|---------------------|----------------------|----------------------|---------------------|--------------------|----------------------|---------------------|---------------------------|----------------------|---------------------|-----------------------------|
| C1 | 22-878 | TWO-GANG VARIABLE | C19 | 22-865 | COMPENSATING COND. | R14 | 63-586 | 3500 OHM | A | 22-798 | 12T I.F. TRANS. PRI. |
| C2 | 22-289 | 50 MMFD. | C20 | 22-708 | OSC. PADDER | R15 | 63-605 | 1000 OHM | B | | 12T I.F. SEC. |
| C3 | 22-829 | .05 MFD. | | | | R16 | 63-1036 | 3-SECTION CANOHM | C | | 22T I.F. PRI. |
| C4 | 22-350 | .25 MFD. | | | | R17 | 63-1012 | 90 OHM WIREWOUND | D | | 22T I.F. SEC. |
| C5 | 22-196 | .01 MFD. | R1 | 63-654 | 180M OHM | | | | E | | BROADCAST OSC. (SEE NOTE) |
| C6 | 22-142 | 100 MMFD. | R2 | 63-593 | 47M OHM | 1 | 57257 | ANTENNA COIL ASSEMBLY | F | | ANT. BROADCAST (ON GANG) |
| C7 | 22-826 | .01 MFD. | R3 | 63-597 | 470M OHM | 2 | 57252 | OSC. COIL ASSEMBLY | G | | BROADCAST PADDER (SEE NOTE) |
| C8 | 22-827 | .1 MFD. | R4 | 63-649 | 56M OHM | 3 | 56992 | OSC. COUPLING COIL ASSEM. | H | | BROADCAST OSC. (SEE NOTE) |
| C9 | 22-807 | .001 MFD. | R5 | 63-296 | 220M OHM | 4 | 57044 | AUTO TUNING UNIT ASSEM. | I | | S.W. OSC. (SEE NOTE) |
| C10 | 22-243 | .01 MFD. | R6 | 63-669 | 39 MEGOHM | 5 | 85-195 | BAND SELECTOR SW. | J | | S.W. DETECTOR |
| C11 | 22-448 | .004 | R7 | 63-1080 | VOLUME CONTROL | 6 | 95-607 | 12T I.F. TRANSFORMER | K | | POL. BAND OSC. (SEE NOTE) |
| C12 | 22-880 | 20 MFD. ELECTROLYTIC | R8 | 63-587 | 4700 OHM | 7 | 95-614 | 22T I.F. TRANSFORMER | L | | |
| C13 | 22-880 | 20 " " | R9 | 63-591 | 22M OHM | 8 | 56994 | 12T I.F. TRANSFORMER | N | | |
| C14 | 22-880 | 20 " " | R10 | 63-604 | 10 MEGOHM | 9 | 85-196 | POWER SW. | | | |
| C15 | 22-879 | 60 MFD. | R11 | 63-271 | 1 MEGOHM | | | | | | |
| C16 | 22-869 | .05 MFD. | R12 | 63-600 | 2.2 MEGOHM | | | | | | |
| C17 | 22-869 | .05 MFD. | R13 | 63-640 | 8200 OHM | | | | | | |
| C18 | 22-350 | .002 MFD. | | | | | | | | | |

MODEL SPEAKER

5G441 49-316 8"

5G442 49-317 10"

5G461 49-318 10"

I.F. FREQUENCY 455 KC

5 TUBE SUPERHETERODYNE

110V. A.C. - BATT. PACK - UNIVERSAL

CHASSIS N^o 5539 - 3 BAND

ZENITH RADIO CORPORATION

CHICAGO, ILL.

MODELS 5G441, 5G442, 5G461 (Chassis No. 5539)