

Chassis No. 5B05-5B06

Zenith Radio



-A.P.S.T. SW. ON V.C



SOCKET VOLTAGES—BOTTOM VIEW

DIAG. NO.	PART NO.	DESCRIPTION	DIAG. NO.	PART NO.	DESCRIPTION	DIAG. NO.	PART NO.	DESCRIPTION	
C1	22-1215	TWO GANG VARIABLE	5B05	R1	63-654	180 M OHM	1	20-239	ANTENNA COIL
	22-1216	TWO GANG VARIABLE	5B06	R2	63-646	33 M OHM	2	5-9597	OSCILLATOR COIL ASSEMBLY
C2	22-829	.05 MFD.	200K	R3	63-600	2.2 MEGOHM	3	95-816	1ST I.F. TRANSFORMER
C3	22-827	.1 MFD.	280K	R4	63-1236	VOLUME CONTROL	4	95-817	2ND I.F. TRANSFORMER
C4	22-162	.0001 MFD	600K	R4	63-1241	VOLUME CONTROL	5B05	85-285	T.C. SWITCH
C5	22-1027	20MFD. ELECTROLYTIC	150K	R5	63-534	68 M OHM	5	85-284	" " " LEFT
C6	22-1286	20MFD. "	25K	R6	63-587	4700 OHM	6	85-289	" " " RIGHT
C7	22-1017	.05 MFD.	200K	R7	63-976	15 MEGOHM	6	85-288	" " " RIGHT
C8	22-448	.004 MFD.	600K	R8	63-271	1 MEGOHM	7	85-254	CHANGEOVER SWITCH
C9	22-492	.002 MFD.	600K	R9	63-1097	870 OHM WIREWOUND	1 W.		
C10	22-470	.00015 MFD.	600K	R10	63-1299	3 SECTION CANDOHM	1/2 W	A	1ST I.F. TRANS. PRI
C11	22-182	.00025 MFD.	600K	R11	63-1099	33 OHM WIREWOUND	1/2 W	B	1ST I.F. TRANS. SEC.
C12	22-243	.01 MFD.	400K	R12	63-439	2700 OHM	1/2 W	C	2ND I.F. TRANS. PRI
C13	22-1026	40 MFD. ELECTROLYTIC	150V	R13	63-627	180 OHM	1/2 W.	D	2ND I.F. TRANS. SEC.
C14	22-1291	20 MFD. "	150V					F	BROADCAST OSC. (ON GANG)
C15	22-163	.01 MFD.	400K					G	BROADCAST ANT. (ON GANG)
C16	22-867	.001 MFD.	600K						