



DIAG. N°	PART N°	DESCRIPTION	DIAG. N°	PART N°	DESCRIPTION	DIAG. N°	PART N°	DESCRIPTION
C1	22-1201	THREE-GANG VARIABLE	R3	63-589	10M OHM	4	95-808	1ST I.F. TRANS.
C2	22-829	.05 MFD. 200 V.	R4	69-976	15 MEG OHM	5	98-809	2ND I.F. TRANS.
C3	22-1017	.05 MFD. 200 V.	R5	63-600	2.2 MEG OHM	6	100-67	PILOT LIGHT 6.3 V. .15A.
C4	22-243	.01 MFD. 400 V.	R6	69-1112	VOLUME CONTROL			
C5	22-854	.0005 MFD. 600 V.	R7	63-597	470M OHM			
C6	22-1049	.03 MFD. 400 V.	R8	63-686	150 OHM WIREWOUND			
C7	22-1014	20MFD.ELECTROLYTIC 150 V.						
C8		20MFD.ELECTROLYTIC 150 V.						
R1	63-590	15M OHM 1/4 W.	1	39576	WAVE MAGNET ASSEMBLY	A		1ST I.F. TRANS. PRI.
R2	63-579	220 OHM 1/4 W.	2	39570	DETECTOR COIL ASSEMBLY	B		1ST I.F. TRANS. SEC.
			3	59571	OSCILLATOR COIL ASSEMBLY	C		2ND I.F. TRANS. PRI.
						D		2ND I.F. TRANS. SEC.
						F		BROADCAST OSC. (ON GANG)
						B		BROADCAST ANT. (ON GANG)
						H		BROADCAST DET. (ON GANG)

Models 6D612-6D612W-6D622-6D628

Zenith Radio Chassis No. 6B04

Operation	Connect Oscillator to	Dummy Antenna	Input Signal Frequency	Band	Set Dial At	Trimmers
1	Converter Grid	.5 mfd.	455 Kc.	BC	1600 Kc.	A, B, C, D
2	Single Turn Loop Coupled Loosely to Wave Magnet	.5 mfd.	1600 Kc.	"	1600 Kc.	F
3		.5 mfd.	1400 Kc.	"	1400 Kc.	H, G