



6.4
0
246

MODEL
6 S 596
6 S 597

Chassis No. 6A20

DIAG N ^o	PART N ^o	DESCRIPTION		DIAG N ^o	PART N ^o	DESCRIPTION		DIAG N ^o	PART N ^o	DESCRIPTION	
C 1	22-1044	TWO GANG VARIABLE		C20	22-219	.03 MFD.	200V.	R 14	63-1123	VOLUME CONTROL	1/4 W.
C 2	22-289	50 MMFD.	600 V.	C21	22-1036	14 MFD. ELECTROLYTIC	450 V.	R 15	63-976	15 MEGOHM	1/4 W.
C3	22-829	.05 MFD.	200 V.	C22	22-1041	.005 MFD.	600 V.	R 16	63-296	220 OHM	1/2 W.
C4	22-828	.05 MFD.	400 V.					R 17	63-1056	280 OHM WIREWOUND	1 1/2 W.
C5	22-162	.0001 MFD.	600 V.								
C6	22-182	.00025 MFD.	600 V.								
C 7	22-868	COMPENSATING COND		R 1	63-637	4700 OHM	1/4 W.			WAVE MAGNET ASSEMBLY	
C8	22-1022	.005 MFD.	600 V.	R 2	63-593	47 M OHM	1/4 W.	1			
C9		.5 MFD. ELECTROLYTIC	450 V.	R 3	63-150	10 M OHM	1/2 W.	2	S8507	ANTENNA COIL ASSEMBLY	
C10	22-1034	15 MFD. "	350 V.	R 4	63-583	1000 OHM	1/4 W.	3	S8508	OSCILLATOR COIL ASSEMBLY	
C11	22-827	.1 MFD.	200 V.	R 5	63-599	15 MEGOHM	1/4 W.	4	S8457	AUTOMATIC TUNING UNIT	
C12	22-470	.00015 MFD.	600 V.	R 6	63-102	15 M OHM	1/2 W.	5	S8359	R.F. CHOKE & RES. ASSEMBLY	
C13	22-147	.0005 MFD.	600 V.	R 7	63-101	8200 OHM	2 W.	6	S8326	WAVE TRAP ASSEMBLY	
C14	22-188	.02 MFD.	400 V.	R 8	63-108	42 OHM WIREWOUND	1/2 W.	7	85-255	BAND SELECTOR SWITCH	
C15	22-229	.005 MFD.	600 V.	R 9	63-624	68 OHM	1/4 W.	8	95-708	1ST I.F. TRANSFORMER	
C16	22-492	.002 MFD.	600 V.	R 10	63-597	470 M OHM	1/4 W.	9	85-709	2ND I.F. TRANSFORMER	
C17	22-854	.0005 MFD.	600 V.	R 11	63-596	330 M OHM	1/4 W.	10	S8531	TONE CONTROL SWITCH	
C18	22-448	.004 MFD.	600 V.	R 12	63-713	47 M OHM	1/4 W.	11	95-705	POWER TRANS. 50-60 V 117 V.	
C19	22-830	.02 MFD.	600 V.	R 13	63-719	470 M OHM	1/4 W.	12	100-36	PILOT LIGHT 6.3 V .25 A.	