



DIAG NO	PART NO	DESCRIPTION	DIAG NO	PART NO	DESCRIPTION
C1	22-567	TWO GANG VARIABLE COND.	1	20-154	WAVE TRAP ASSEMBLY
C2	22-487	.05 MFD.	2	5-4941	ANTENNA COIL & SHIELD ASSEMBLY
C3	22-550	DUAL FIXED PADDER	3	5-4942	OSCILLATOR COIL & SHIELD ASSEMBLY
C4	22-170	.1 MFD.	4	95-413	1ST I.F. TRANSFORMER
C5	22-812	.05 MFD.	5	95-414	2ND I.F. TRANSFORMER
C6	22-358	.002 MFD.	6	95-105	BAND SELECTOR SWITCH
C7	22-187	.05 MFD.	7	95-416	POWER TRANSFORMER
C8	22-327	.02 MFD.	8	95-450	117V. 50-60 CYCLE POWER TRANSFORMER
C9	22-102	.0001 MFD.	9		A.C. VOLTAGE 25 CYCLE SPEAKER TRANSFORMER
C10	22-147	.0005 MFD.			
C11	22-180	.1 MFD.			
C12	22-435	.02 MFD.			
C13	22-492	.002 MFD.			
C14	22-171	.05 MFD.			
C15	22-596	.05 MFD. DRY ELECTROLYTIC			
C16		.1 MFD. DRY ELECTROLYTIC			
C17					
R-1	63-593	47 M OHMS	A		
R-2	63-680	10 M OHMS	B		
R-3	63-677	33 M OHMS	C		
R-4	63-271	1 M OHMS	D		
R-5	63-587	4700 OHMS	E		
R-6	63-286	220 M OHMS	F		
R-7	63-587	470 M OHMS	G		
R-8			H		
R-9	63-521	50 M OHMS TONE CONTR.	I		
R-10	63-520	400 M OHMS VOLUME CONTR.	J		
R-11	63-605	1000 OHMS	K		
R-12	63-613	3 SECTION CANNON	L		
			N		

Models 6-S-203, 6-S-222, 6-S-223,
6-S-229, 6-S-239, 6-S-241
(5638 Chassis)

I.F. FREQUENCY 456 K.C.
6 TUBE SUPERHETERODYNE - 3 BANDS
CHASSIS NO 5638

ZENITH RADIO CORPORATION