



DIAG. NO.	PART NO.	DESCRIPTION	DIAG. NO.	PART NO.	DESCRIPTION	DIAG. NO.	PART NO.	DESCRIPTION	DIAG. NO.	PART NO.	DESCRIPTION
C1	22-1030	TWO GANG VARIABLE	C21	22-886	COMPENSATING COND.	R17	63-972	15M OHM 1W	A	22-1015	13T I.F. TRANS. PRI.
C2	22-289	50 MMFD.				R18	63-1056	260 OHM WIREWOUND 1 1/2 W	B		18T I.F. " SEC.
C3	22-829	.05 MFD.							C		2ND I.F. " PRI.
C4	22-828	.05 MFD.							D		2ND I.F. " SEC.
C5	22-182	.00025 MFD.	R1	63-260	100 M OHM 1/4 W.				E		WAVE TRAP
C6	22-1037	DUAL PADDER	R2	63-587	4700 OHM 1/4 W.	1		WAVEMAGNET ASSEMBLY	F		BROADCAST OSC. (NOTE 1)
C7	22-825	.1 MFD.	R3	63-713	47 M OHM 1/4 W.	2	58404	ANTENNA COIL ASSEMBLY	G		" ANT (NOTE 2)
C8	22-327	.02 MFD.	R4	63-621	39 OHM 1/4 W.	3	58403	OSCILLATOR COIL ASSEM.	H		" PADDER (NOTE 2)
C9	22-448	.004 MFD.	R5	63-589	10M OHM 1/4 W.	4	58457	AUTOMATIC TUNING ASSEM.	J		SHORT WAVE OSC. (NOTE 1)
C10	22-228	.005 MFD.	R6	63-605	1000 OHM 1/4 W.	5	85-226	BAND SELECTOR SWITCH	K		" ANT. (NOTE 2)
C11	22-954	.00035 MFD.	R7	63-599	1.5 MEG OHM 1/4 W.	6	38359	R.F. CHOKE & RES. ASSEM.	M		POLICE BAND ANT. (NOTE 2)
C12	22-470	.00015 MFD.	R8	63-960	68 M OHM 1/4 W.	7	38326	WAVE TRAP COIL ASSEM.	Q		
C13	22-492	.002 MFD.	R9	63-719	470 M OHM 1/4 W.	8	95-703	18T I.F. TRANSFORMER			NOTES:
C14	22-684	.0005 MFD.	R10	63-1122	VOLUME CONTROL	9	95-704	2ND I.F. TRANSFORMER			(1) TRIMMERS F&K ARE
C15	22-630	.02 MFD.	R11	63-593	47 M OHM 1/4 W.	10	58452	10T I.F. TRANSFORMER			MOUNTED ON STRIP #22-1033
C16	22-219	.03 MFD.	R12	63-594	68 M OHM 1/4 W.	11	58451	10T I.F. TRANSFORMER			(2) TRIMMERS G, J, M & Q ARE
C17	22-827	.1 MFD.	R13	63-976	15 MEG OHM 1/4 W.	12	95-705	10T I.F. TRANSFORMER			MOUNTED ON STRIP #22-1031
C18	22-1034	15 MFD. ELECTROLYTIC	R14	63-296	220 M OHM 1/4 W.	13	100-36	PWR. TRANS. 50-60W 117V			
C19	22-1034	15 MFD. "	R15	63-597	470 M OHM 1/4 W.			PILOT LIGHT 6.3V .25 A.			
C20	22-1036	14 MFD. "	R16	63-975	82 OHM WIREWOUND 1/2 W						

I.F. FREQUENCY 455 K.C.
 7 TUBE SUPERHETERODYNE
 CHASSIS N° 7A02 3 BAND A.C.
 ZENITH RADIO CORPORATION