



C-1	0.05 MF. 500 V.	C-16	10 MF. 450 M. K.
C-2	0.05 MF. 500 V.	C-17	10 MF. 450 M. K.
C-3	0.05 MF. 500 V.	C-18	0.01 MF. 400 V.
C-4	0.01 MF. 400 V.	C-19	0.01 MF. 400 V.
C-5	0.01 MF. 400 V.	C-20	0.01 MF. 400 V.
C-6	0.01 MF. 400 V.	C-21	0.01 MF. 400 V.
C-7	0.01 MF. 400 V.	C-22	0.01 MF. 400 V.
C-8	0.01 MF. 400 V.	C-23	0.01 MF. 400 V.
C-9	0.01 MF. 400 V.	C-24	0.01 MF. 400 V.
C-10	0.01 MF. 400 V.	C-25	0.01 MF. 400 V.
C-11	0.01 MF. 400 V.	C-26	0.01 MF. 400 V.
C-12	0.01 MF. 400 V.	C-27	0.01 MF. 400 V.
C-13	0.01 MF. 400 V.	C-28	0.01 MF. 400 V.
C-14	0.01 MF. 400 V.	C-29	0.01 MF. 400 V.
C-15	0.01 MF. 400 V.	C-30	0.01 MF. 400 V.

R-1	10,000 Ω	R-14	10,000 Ω
R-2	10,000 Ω	R-15	10,000 Ω
R-3	10,000 Ω	R-16	10,000 Ω
R-4	10,000 Ω	R-17	10,000 Ω
R-5	10,000 Ω	R-18	10,000 Ω
R-6	10,000 Ω	R-19	10,000 Ω
R-7	10,000 Ω	R-20	10,000 Ω
R-8	10,000 Ω	R-21	10,000 Ω
R-9	10,000 Ω	R-22	10,000 Ω
R-10	10,000 Ω	R-23	10,000 Ω
R-11	10,000 Ω	R-24	10,000 Ω
R-12	10,000 Ω	R-25	10,000 Ω
R-13	10,000 Ω	R-26	10,000 Ω
R-14	10,000 Ω	R-27	10,000 Ω
R-15	10,000 Ω	R-28	10,000 Ω
R-16	10,000 Ω	R-29	10,000 Ω
R-17	10,000 Ω	R-30	10,000 Ω
R-18	10,000 Ω	R-31	10,000 Ω
R-19	10,000 Ω	R-32	10,000 Ω

I.F. Alignment

456 KC for Maximum.

B.C. Alignment

Adj. osc. trim. 1720 KC.

Adj. ant. trim. 1500 KC.

Adj. Padder at 600 KC.

S.W. Alignment

Adj. S.W. osc. trim. at 23 MC. through 250 MF cond. and 400 res. open trim. cond. further opened (cap. reduced) until second response is heard. This response (trim at low cap.) is correct response to use. Other is image.