



5573

	1.	2.	3.	4.	5.	6.	7.	8.	9.	10.	11.	12.	13.	14.	15.
C2.	●	○	○	○	○	○	○	○	○	○	○	○	○	○	○
C1.	○	●	○	○	○	○	○	○	○	○	○	○	○	○	○
M.	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○
F.	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○

	A.	B.	C.	D.	E.	F.
VOCE.	○	●	○	○	○	○
MUSICA 1.	●	○	●	○	○	○
MUSICA 2.	●	●	○	○	○	○
TONO 1.	●	●	○	○	○	○
TONO 2.	●	●	○	○	○	●

V 1	ECH42
V 2	EF41
V 3	EBC41
V 4	EI84
V 5	EZ40
EM80	

C 1	2.000	pf
C 2	50	»
C 3	100	»
C 4	100.000	»
C 5	25.000	»
C 6	75	»
C 7	200	»
C 8	50	»
C 9	75	»
C 10	4.000	»
C 11	300	»
C 12	200	»
C 13	200	»
C 14	200	»
C 15	50.000	»
C 16	10.000	»
C 17	200	»
C 18	200	»
C 19	200	»
C 20	5.000	»
C 21	50.000	»
C 22	200	»
C 23	10.000	»
C 24	1.000	»
C 25	25.000	»
C 26	250	»
C 27	10.000	»
C 28	2.000	»
C 29	100 Mf	»
C 30	5.000 pf	»
C 31	50+50 Mf	»
C 32	5.000 pf	»
C 33	5.000	»
C 34	2.000	»
R 1	150	Ω
R 2	47	KΩ
R 3	1	MΩ
R 4	47	Ω
R 5	33	KΩ
R 6	0.47	MΩ
R 7	0.47	MΩ
R 8	2.2	MΩ
R 9	47	KΩ
R 10	2.2	MΩ
R 11	47	KΩ
R 12	22	MΩ
R 13	0.1	MΩ
R 14	0.1	MΩ
R 15	120	KΩ
R 16	82	KΩ
R 17	22	KΩ
R 18	0.22	MΩ
R 19	0.22	MΩ
R 20	47	KΩ
R 21	0.1	MΩ
R 22	130	Ω
R 23	1000	Ω

FIMI S.A. - PHONOLA - Mod. 5573. Onde medie da 183 a 575 metri. Onde corte da 27,3 a 80 metri e da 15,8 a 28 metri. Media frequenza 470 kc/s. Consumo 50 watt. Potenza indistorta 5 watt. montaggio cordina come per il mod. 5532 F. Disposizione dei compensatori A. F. e bobine come per il mod. 5576.