



ZF: 125

MARCONI 237



I.F.T. 1



I.F.T. 2

SPARE PART LIST AND ELECTRICAL VALUES.

Ref. No.	Description.	Part No.	Ref. No.	Description.	Part No.
L 1	Tuning coil—		C 13	Fixed condenser—	
L 3	M.W. aerial	11980n	C 14	2,000 M.M.F.	15719c
L 2	L.W. aerial	11984c	C 15	5 M.F.	7581A
L 4	L.W.H.F. grid		C 16	4 "	15763n
L 5	M.W. 1st det. grid		C 17	6 "	
L 7	M.W. oscillator	11980b	C 18	1 M.F.	7581A
L 9	M.W. reaction		C 19	4 "	
L 6	L.W. 1st det. grid		C 20	2,000 M.M.F.	15719c
L 8	L.W. oscillator	11984A	C 21	4 M.F.	15764u
L 10	L.W. reaction			1 "	8349A
L 11	Tuning coil			Fixed resistance—	
L 12			R 1	5,000 ohms	5787f
TC 1	Trimming condenser	7597d	R 2	25,000 "	5787n
TC 2	70-140 M.M.F.		R 3	320 "	5787c
L 13	Tuning coil		R 4	2,000 "	5787A
L 14			R 5	320 "	5787x
TC 3	Trimming condenser	7597e	R 6	25,000 "	5786c
TC 4	70-140 M.M.F.		R 7	200,000 "	5787d
L 15	H.F. choke	11984A	R 8	100,000 "	5786u
TC 5	Trimming condenser, 5-70 M.M.F.	11737c	R 9	2—(3,000 ohms each)	
VC 1			R 10	8,000 ohms	13525A
VC 2	Ganged condenser, 450 M.M.F. and trimmers	10198A	R 11	1,000 "	5787k
VC 3			R 12	5,000 "	5787e
VC 4			R 13	50,000 "	5786A
CK 2	L.F. Choke	12045c	R 15	50,000 "	5787p
T 1	Interval transformer	4518f	R 16	800 "	13525n
T 2	Mains transformer	7572A	R 17	100,000 "	5787q
VR 1	Volume control—		R 18	25,000 "	5786c
VR 2	20,000 ohms	6000	R 19	3,000 "	13525c
VR 3	Potentiometer 20 ohms	10201u	S 1	Wave change switch	12540c
VR 4	Tone control, 600,000 ohms	4000r	S 2		
C 2	Fixed condenser—		LP	Lamp, 6-volt	1575A
C 3	1 M.F.	7581A	V 1	VMS4 valve	
C 4	300 M.M.F.	15719d	V 2	MH4—38MB valve	
C 5	50 "	15719A	V 3	MS4—11 MB valve	
C 6	1,700 "	15719t	V 4	VMS4 valve	
C 7	300 "	15719p	V 5	MH4—38MB valve	
C 8	1 M.F.		V 6	PN4—60 valve	
C 9	5 "		V 7	U12 valve	
C 10	1 "				
C 11	5 "	7581A			
C 12	1 "				