



3A4

3A4

POWER AMPLIFIER PENTODE

MINIATURE TYPE

Filament	Coated	
Filament Arrangement	<u>Series *</u>	<u>Parallel **</u>
Voltage	2.8	1.4
Current	0.1	0.2
Direct Interelectrode Capacitances: °		d-c volts amp.
Grid to Plate	0.34 max.	μμf
Input	4.8	μμf
Output	4.2	μμf
Maximum Overall Length		2-1/8"
Maximum Seated Height		1-7/8"
Maximum Diameter		3/4"
Bulb		T-5-1/2
Base ▲		Miniature Button 7-Pin
Pin 1 - Fil. (- series)		Pin 5 { Fil. Mid-Tap (- parallel)
Pin 2 - Plate		Pin 6 - Plate
Pin 3 - Screen		Pin 7 - Filament +
Pin 4 - Grid		Stock No. 9914
RCA Socket		Any
Mounting Position	BOTTOM VIEW (7BB)	



Maximum Ratings Are Design-Center Values

A-F POWER AMPLIFIER

Plate Voltage	150 max.	volts
Screen Voltage	90 max.	volts
Plate Dissipation	2.0 max.	watts
Screen Dissipation	0.4 max.	watt
Total Zero-Sig. Cathode Current ■	18 max.	ma.

Typical Operation and Characteristics-Class A₁ Amplifier: ●

Filament Arrangement	<u>Parallel **</u>	
Plate Voltage	135	150
Screen Voltage	90	90
Grid Voltage	-7.5	-8.4
Peak A-F Grid Voltage	7.5	8.4
Zero-Sig. Plate Current	14.8	13.3
Max.-Sig. Plate Current	14.9	14.1
Zero-Sig. Screen Current	2.6	2.2
Max.-Sig. Screen Current	3.5	3.5
Plate Resistance	9000	10000
Transconductance	1900	1900
Load Resistance	8000	8000
Total Harmonic Distortion	5	6
Max.-Sig. Power Output	600	700

R-F POWER AMPLIFIER

D-C Plate Voltage	150 max.	volts
D-C Screen Voltage	135 max.	volts
D-C Grid Voltage	-30 max.	volts
D-C Plate Current	20 max.	ma.
D-C Grid Current	0.25 max.	ma.
Total D-C Cathode Current ■	25 max.	ma.
Plate Input	3 max.	watts
Screen Input	0.9 max.	watt
Plate Dissipation	2 max.	watts

*, **, °, ▲, ■, ●: See next page.

← Indicates a change.

DEC. 15, 1944

RCA VICTOR DIVISION

RADIO CORPORATION OF AMERICA, HARRISON, NEW JERSEY

DATA



POWER AMPLIFIER PENTODE

(continued from preceding page)

→ Typical Operation at 10 Mc with

Parallel Filament Arrangement:**

D-C Plate Voltage	150	volts
D-C Screen Voltage	135	volts
Grid Resistor	0.2	megohm
D-C Plate Current	18.3	ma.
D-C Screen Current	6.5	ma.
D-C Grid Current	0.13	ma.
Power Output (approx.)	1.2	watts

* Filament voltage applied across the two sections in series between pins No.1 and No.7. Grid voltage is referred to pin No.1.

** Filament voltage applied across the two sections in parallel between pin No.5 and pins No.1 and No.7 connected together. Grid voltage is referred to pin No.5.

○ with no external shield.

■ For series-filament operation. A shunting resistor must be connected across the section between pins No.1 and No.5 to by-pass excess cathode current in this section. The value of the shunting resistor should be adjusted to make the voltage across the shunted section equal to the voltage across the section between pins No.5 and No.7. When other tubes in series-filament arrangement contribute to the filament current of the 3A4, an additional shunting resistor may be required between pins No.1 and No.7.

● Typical operating values for the 3A4 with filament sections in series will be approximately the same as those shown for parallel-filament operation.

▲ The center hole in sockets designed for this base provides for the possibility that this tube type may be manufactured with the exhaust-tube tip at the base end. For this reason, it is recommended that in equipment employing this tube type, no material be permitted to obstruct the socket hole.

← Indicates a change.



3A4

3A4

AVERAGE PLATE CHARACTERISTICS

