



5AZ4

5AZ4

## FULL-WAVE VACUUM RECTIFIER

### GENERAL DATA

#### Electrical:

Filament, Coated:

Voltage. . . . . 5 . . . . . ac or dc volts

Current. . . . . 2 . . . . . amp

#### Mechanical:

Mounting Position. . . . . Vertical, or Horizontal with pins  
2 and 8 in horizontal plane

Maximum Overall Length . . . . . 3-5/32"

Maximum Seated Length. . . . . 2-5/8"

Maximum Diameter . . . . . 1-3/16"

Bulb . . . . . T-9

Base . . . . . Lock-in 8-Pin

Basing Designation for BOTTOM VIEW . . . . . 5T

Pin 1 - No


Connection

Pin 2 - Filament

Pin 3 - No

Connection

Pin 4 - Plate



Pin 5 - No

Connection

Pin 6 - Plate

Pin 7 - No

Connection

Pin 8 - Filament

Plug - Base Shell

### FULL-WAVE RECTIFIER

#### Maximum Ratings, Design-Center Values:

PEAK INVERSE PLATE VOLTAGE . . . . . 1400 max. volts

PEAK PLATE CURRENT . . . . . 375 max. ma

DC OUTPUT CURRENT. . . . . 125 max. ma

#### Typical Operation:

|                                   | Capacitor-<br>Input to<br>Filter | Choke-<br>Input to<br>Filter |         |
|-----------------------------------|----------------------------------|------------------------------|---------|
| AC Plate-to-Plate Supply          |                                  |                              |         |
| Voltage (RMS). . . . .            | 700                              | 1000                         | volts   |
| Filter Input Capacitor . . . . .  | 4                                | -                            | μf      |
| Min. Total Effective Plate-Supply |                                  |                              |         |
| Impedance per Plate*. . . . .     | 50                               | -                            | ohms    |
| Min. Filter Input Choke . . . . . | -                                | 5                            | henries |
| DC Output Current. . . . .        | 125                              | 125                          | ma      |

\* When the input capacitor of the filter exceeds 40 μf, it may be necessary to increase the plate-supply impedance in order to limit the peak current to the rated value.

MAY 20, 1949

TUBE DEPARTMENT  
RADIO CORPORATION OF AMERICA, HARRISON, NEW JERSEY

DATA