



## Current Equipment Type



## TYPE EZ80/6V4

MINIATURE  
FULL-WAVE  
RECTIFIER

Heater Voltage ... ... ... ... ... ... 6.3 volts  
Heater Current ... ... ... ... ... ... 0.6 amp.

## RATINGS

Peak Inverse Voltage ... ... ... ... ... 980 volts max.  
Peak Current (each anode) ... ... ... ... 270 mA max.  
Hot Switching Transient Anode Current ... ... ... ... 900 mA max.  
Peak Heater-Cathode potential ... ... ... ... 500 volts max.

## CHARACTERISTICS AS FULL-WAVE RECTIFIER

## CONDENSER INPUT

R.M.S. Input per Anode ...	... 250	275	300	350 volts
Supply Impedance per Anode ...	125	175	215	300 ohms min.
Reservoir Condenser ...	... 50	50	50	50 $\mu$ F max.
Rectified Current ...	... 90	90	90	90 mA max.

