


Refer to type 12FX5.	<b>19FX5</b>
Refer to chart at end of section.	<b>19GQ7</b>
Refer to chart at end of section.	<b>19HR6</b>
Refer to chart at end of section.	<b>19HS6</b>
Refer to chart at end of section.	<b>19HV8</b>
Refer to chart at end of section.	<b>19J6</b>
Refer to chart at end of section.	<b>19JN8</b>
Refer to type 6JN8.	<b>19JN8/19CL8A</b>
Refer to chart at end of section.	<b>19KG8</b>
For replacement use type 18GD6A.	<b>19MR9</b>
For replacement use type 18FW6A.	<b>19MR19</b>
Refer to chart at end of section.	<b>19Q9</b>
Refer to type 6X8A.	<b>19X8</b>
Refer to chart at end of section.	<b>20</b>
Refer to type 16AQ3/XY88.	<b>20AQ3/LY88</b>
Refer to chart at end of section.	<b>20EQ7</b>
Refer to chart at end of section.	<b>20EZ7</b>
Refer to type 6LF6/6LX6.	<b>20LF6</b>
Refer to chart at end of section.	<b>21EX6</b>
Refer to type 6GY5.	<b>21GY5</b>
Refer to chart at end of section.	<b>21HB5</b>



12BJ

**BEAM POWER TUBE**

**21HB5A**

Duodecax type used as horizontal-deflection amplifier in television receivers. **Outlines section**, 15B; requires duodecax 12-contact socket. For maximum ratings, refer to type 6HB5. **Heater:** volts (ac/dc), 21; amperes, 0.45; warm-up time (average), 11 seconds; maximum heater-cathode volts,  $\pm 200$  peak, 100 average.

**Class A<sub>1</sub> Amplifier**

**CHARACTERISTICS**

	Pentode Connection			Triode* Connection	
Plate Voltage	5000	50	130	130	volts
Grid-No.2 (Screen-Grid) Voltage	130	130	130	130	volts
Grid-No.1 (Control-Grid) Voltage	—	0	—20	—20	volts
Amplification Factor	—	—	—	4.8	
Plate Resistance (Approx.)	—	—	9900	—	ohms
Transconductance	—	—	9000	—	$\mu$ mhos

Plate Current .....	—	450*	46	—	mA
Grid-No.2 Current .....	—	29*	1.8	—	mA
Grid-No.1 Voltage (Approx.) for plate current of 1 mA .....	-64	—	-32	—	volts

\* Grid-No.2 tied to plate

\* This value can be measured by a method involving a recurrent waveform such that the maximum ratings of the tube will not be exceeded.


**21HJ5** Refer to chart at end of section.

**21JS6A** For replacement use type 23JS6A.

**21JV6** Refer to chart at end of section.

## 21JZ6 BEAM POWER TUBE

Duodecar type used as horizontal-deflection amplifier in television receivers. Outlines section, 39A; requires duodecar 12-contact socket. Heater: volts (ac/dc), 21; amperes, 0.45; average warm-up time, 11 seconds; maximum heater-cathode volts,  $\pm 200$  peak, 100 average.



### Class A<sub>1</sub> Amplifier

CHARACTERISTICS	Triode <sup>a</sup> Connection		Pentode Connection		
	13J	5000	50	130	
Plate Voltage .....	—	5000	50	130	volts
Grid No.3 (Suppressor Grid) .....	—	—	Connected to cathode at socket		
Grid-No.2 (Screen-Grid) Voltage .....	—	130	130	130	volts
Grid-No.1 (Control-Grid) Voltage .....	-20	—	0	-20	volts
Amplification Factor .....	4.8	—	—	—	
Plate Resistance (Approx.) .....	—	—	—	9900	ohms
Transconductance .....	—	—	—	9000	$\mu$ mhos
Plate Current .....	—	—	450	46	mA
Grid-No.2 Current .....	—	—	29	1.8	mA
Grid-No.1 Voltage (Approx.) for plate current of 1.0 mA .....	—	-64	—	-32	volts

<sup>a</sup> Grid No.2 connected to plate.

### Horizontal-Deflection Amplifier

For operation in a 525-line, 30-frame system

#### MAXIMUM RATINGS (Design-Maximum Values)

Plate Supply Voltage .....	770	volts
Peak Positive-Pulse Plate Voltage# .....	6500	volts
Peak Negative-Pulse Plate Voltage .....	1500	volts
DC Grid-No.3 Voltage, Positive-bias value .....	70	volts
Grid-No.2 Voltage .....	220	volts
DC Grid-No.1 Voltage, Negative-bias value .....	55	volts
Peak Negative-Pulse Grid-No.1 Voltage .....	330	volts
Peak Cathode Current .....	800	mA
Average Cathode Current .....	230	mA
Plate Dissipation* .....	18	watts
Grid-No.2 Input .....	3.5	watts
Bulb Temperature (At hottest point) .....	220	$^{\circ}$ C

#### MAXIMUM CIRCUIT VALUE

Grid-No.1-Circuit Resistance .....	1	megohm
------------------------------------	---	--------

\* A bias resistor or other means is required to protect the tube in absence of excitation.

# Pulse duration must not exceed 15% of a horizontal scanning cycle (10 microseconds).