

SHARP-CUTOFF TRIODE 2HM5, 3HM5, 4HM5 AND 6HM5

The 2HM5, 3HM5, 4HM5 and 6HM5 are sharp-cutoff, seven-pin miniature triode types designed particularly for service in V.H.F. television tuners as grounded cathode r-f amplifiers. These types are electrically and mechanically similar to the 2HA5, 3HA5, 4HA5 and 6HA5 except for bulb length.

The 2HM5, 3HM5 and 4HM5 have been designed for use in receivers which employ series connected heaters, especially in television receivers where the picture-tube heater is in series with other heaters. When each is employed in this type of circuit with other tubes similarly designed having the same heater current rating, heater voltage surges across individual tubes are minimized inasmuch as heater warm-up characteristic is controlled.

ELECTRICAL:

Heater Characteristics:	2HM5	3HM5	4HM5	6HM5	
Voltage ac or dc	2.4	2.9	4.0	6.3	Volts
Current	0.60	0.45	0.30	0.185	Amps
Warm-up Time (Note 1)	11	11	11	—	Seconds
Direct Interelectrode Capacitance: (Shielded) (Note 2)					
Grid to Plate	—	—	0.34 max.	—	μmf
Input	—	—	4.5	—	μmf
Output	—	—	3.0	—	μmf
Heater to Cathode	—	—	2.5	—	μmf

MECHANICAL:

Cathode	Coated Unipotential
Bulb	T-5-1/2
Base	Miniature 7-Pin (JEDEC E7-1)
Outline	5-2
Basing	7GM
Mounting Position	Any

RATINGS:

Design Maximum Values

Plate Voltage	200 max.	Volts
Plate Dissipation	2.2 max.	Watts
Grid Voltage:		
Negative Value	50 max.	Volts
Cathode Current	20 max.	Ma.
Grid Circuit Resistance (Self Bias)	1.0 max.	Megohm

Heater Ratings:

Allowable Heater Voltage	2HM5	3HM5	4HM5	6HM5	
Maximum	—	—	—	6.9 max.	Volts
Minimum	—	—	—	5.7 min.	Volts

Allowable Heater Current:

Maximum	640	480	320	— max.	Ma.
Minimum	560	420	280	— min.	Ma.

Heater-Cathode Voltage:

Heater Negative with Respect to Cathode DC	100	100	100 max.	Volts
Heater Positive with Respect to Cathode DC	100	100	100 max.	Volts

CHARACTERISTICS & TYPICAL OPERATION:

Plate Voltage	120	135	Volts
Grid Voltage	—0	—1	Volts
Grid Resistance	0.1	0	Megohm
Transconductance	18,000	14,500	μmhos
Grid Cutoff Bias	See Note 6	See Note 3	
Plate Current	15.0	12.5	Ma.
Amplification Factor	82	78	—
Hot Input Resistance (Note 4)	—	1000	Ohms
Hot Input Capacitance (Note 4)	—	8.5	μmf
Noise Figure (Note 5)	4.0	4.2	db

NOTES

1. Heater Warm-up Time is defined as the time required for the voltage across the heater to reach 80% of its rated value after applying four times rated heater voltage to a circuit consisting of the tube heater in series with a resistance equal to three times rated heater voltage divided by rated heater current.
2. With JEDEC shield No. 316 connected to Pin 1—cathode
3. Grid Volts for $g_m = 150 \mu\text{mhos}$: -5.7
Grid Volts for $g_m = 1500 \mu\text{mhos}$: -2.7
4. Measured at 200 Mc. with plate at signal ground. $E_{c1} = -1.5$ Volt.
5. In a 200 Mc. noise-matched, optimized, neutralized, grounded-cathode triode amplifier stage.
6. Grid volts for $g_m = 150 \mu\text{mhos}$: -5.1

