



**UHF
GROUNDED GRID TRIODE**

BRIEF DATA

A uhf triode for use in grounded grid circuits as a low noise amplifier, small power amplifier or frequency multiplier at frequencies up to 1250 MHz. The A2521 is a commercial version of the CV2453, except for the heater current rating.

HEATER

Heater voltage	6.3	V
Heater current (approx) - A2521	0.3	A
Heater current (approx) - CV2453	0.37	A

MAXIMUM RATINGS

DC anode voltage	250	V
Peak anode voltage	1000	V
Anode dissipation	2.5	W
DC grid current	6	mA
DC cathode current	25	mA
Peak cathode current (pulse duration $< 2 \mu s$)	700	mA
Negative dc grid voltage	20	V
Peak heater-cathode voltage	100	V
Bulb temperature	200	°C

CAPACITANCES (Measured on a cold unscreened valve)

Cathode plus heater to grid	3.5	pF
Anode to grid	1.6	pF
Cathode plus heater to anode	0.06	pF

CHARACTERISTICS

DC anode voltage	130	V
DC anode current	16	mA
Negative dc grid voltage (approx)	1	V
Mutual conductance (approx)	15	mA/V
Amplification factor	60	—

OPERATING DATA

CLASS A GROUNDED GRID AMPLIFIER

Typical Operation

Frequency	1250	900	400	200	MHz
V_b	180	180	180	180	V
R_a	3.3	3.3	3.3	3.3	k Ω
R_k	68	68	68	68	Ω
I_a	16	16	16	16	mA
* Δf (to 3 dB)	20	50	6	4	MHz
†Power gain	9	10	17	14.5	dB
†‡Noise factor	11.1	9.5	6.7	4.6	dB

*Bandwidth and power gain may be adjusted by altering the coupling between the anode circuit and the output line.

†With input circuit adjusted for minimum noise factor.

‡Using a gas discharge noise source.

CLASS C GROUNDED GRID UHF POWER AMPLIFIER AND FREQUENCY MULTIPLIER

Maximum Permissible Conditions

DC anode voltage	250	V
Anode dissipation	2.5	W
Peak anode current	100	mA
DC grid current	6	mA
Positive dc cathode to grid voltage	20	V

Typical Operation as Amplifier

Frequency	400	900	MHz
DC anode voltage	250	150	V
Anode dissipation	2	2.4	W
*DC anode current	18	20	mA
DC grid current	4.5	2.5	mA
Positive dc cathode to grid voltage	10.5	5.0	V
Driving power	0.3	0.45	W
Load power (approx)	2.6	0.9	W

*Set by adjustment of cathode resistance.

Typical Operation as Frequency Multiplier

Frequency-in	200	133.3	450	300	416.6	MHz
Frequency-out	400	400	900	900	1250	MHz
V_a	200	200	140	90	130	V
P_a	2.4	2.5	2.4	2.5	2.4	W
$*I_a$	20	15	20	20	18.5	mA
I_g	3.5	1.5	3.5	3.0	1.5	mA
$+V_{k-g}$	20	20	15	10	10.5	V
P_{dr}	0.6	0.55	0.6	1.2	0.22	W
P_L (approx)	1.8	0.75	0.7	0.3	0.05	W

*Set by adjustment of R_k .

INSTALLATION


The valve may be mounted in any position.

If a screening can is used it should be blackened inside and out.

Free air circulation around the bulb or the screening can is desirable.

A detailed Application Report is available upon request.

BASE CONNECTIONS AND VALVE DIMENSIONS



Base: B9A
 Bulb: Tubular
 Max. overall length: 56 mm
 Max. seated length: 49 mm
 Max. diameter: 22.2 mm

View from underside of base.

Whilst M-OV has taken care to ensure the accuracy of the information contained herein it accepts no responsibility for the consequences of any use thereof and also reserves the right to change the specification of goods without notice.

M-OV accepts no liability beyond that set out in its standard conditions of sale in respect of infringement of third party patents arising from the use of tubes or other devices in accordance with information contained herein.

