



Continental
Admiral

CAPACITORS						RESISTORS					
No.	MFD'S	VOLTS	No.	MFD'S	VOLTS	No.	OHMS	WATTS	No.	OHMS	WATTS
C1	.05	200	C11	.0001	MICA	R1	50,000	1/2	R11	50,000	1/2
C2	.25	200	C12	.004±5%	MICA	R2	200	1/2	R12	250,000	1/2
C3	.05	400	C13	300-600MFD	PADDER	R3	250	1/2	R13	500,000	1/2
C4	.00025	MICA	C14	.01	400	R4	20,000	1/2	R14	100,000	1/2
C5	.01	400	C15	10.0	350	R5	1,000	1/2	R15	400,000	1/2
C6	.005	600	C16	10.0	350	R6	2MEG	1/2	R16	300	1/2
C7	.00025	MICA	C17	.05	400	R7	500,000	VOL. CON.			
C8	.01	400	C18	GIMMICK		R8	3,000	1/2			
C9	.005	600	C19	.0001	MICA	R9	5MEG	1/2			
C10	.005	600				R10	500,000	TONE CON.			

I.F. - 455 K.C.

BAND SWITCHES SHOWN IN BROADCAST
POSITION
BOTTOM VIEW OF TUBE SOCKETS SHOWN
GANG CONDENSER CAPACITY 443MFD'S.

SCHEMATIC DIAGRAM MODEL 7C