



ARVIN HOME RADIO - CHASSIS RE-98

35Z5GT

RESISTORS				CONDENSERS				COILS & TRANSFORMERS				MISCELLANEOUS UNITS			
R	OHM	W	PART NO	C	CAPACITY	VOLT	PART NO	T	DESCRIPTION	PART NO		SYMBOL	DESCRIPTION	PART NO	
9	1MEG	1/4	17-2080	222	2	400	17-4317	1	ANTENNA LOOP ASSY	00-17298		SPK	SPEAKER 5 INCH E.M.	17-17251	
222	10MEG	1/4	17-4377	192	00025	600	17-4273	2	OSCILLATOR COIL	00-17299		P	LINE CORD & PLUG ASSY	17-17303	
174	20K	1/4	17-14281	91	.01	400	17-44272	3	FIRST IF COIL	00-17300		L	DIAL LIGHT - MAZDA C 7 7WATT5	17-18701	
27	2MEG	1/4	17-4798	193	.05	200	17-44274	4	SECOND IF COIL	00-17301		SW	VOLUME CONTROL & SW	17-17299	
150	5MEG	1/4	17-4242	221	.002	400	17-14388	5	OUTPUT TRANS	00-17302					
8	500K	1/4	17-2070	398	.05	400	17-14382								
183	150	1/4	17-14318	195	.05	400	17-14276								
213	10K	1/4	17-14389	278	100000	400	17-14404								
23	250K	1/4	17-3011		TWO GANG		17-446								
233	1MEG	1/4	17-17291	2	VARIABLE										
				281A	40MFD	50									
				281B	20MFD	50	17-14417								
				281C	20MFD	25									

IF PEAK 455 K C
BALANCE 1400 K C - CHECK AT 600 K C.

NOBLITT-SPARKS INDUSTRIES, INC
COLUMBUS, INDIANA