

RESISTORS				CONDENSERS				TRANSFORMERS			MISCELLANEOUS UNITS		
R	OHM	W	PART NO.	C	CAPACITY	VOLT	PART NO.	T	TYPE	PART NO.	SYMBOL	DESCRIPTION	PART NO.
9	1M	1/4	17-2080	1	TWO-GANG		17-18005	1	ANTENNA COIL	00-15997	L	DIAL LIGHT BULB	17-13904
10	30	1/4	17-14117	2	VARIABLE		17-18005	2	OSCILLATOR COIL	00-15997	PI	SPEAKER PLUG	
108	50K	1/4	17-14171	5	.05	200	17-14015	3	FIRST I.F. COIL	00-15998	P2	AC LINE CORD & PLUG ASSEMBLY	17-1579E
111	20K	1/2	17-14178	6	.002	600	17-2083	4	SECOND I.F. COIL	00-15999	S1	SPEAKER SOCKET	17-13248
113	250K	1/4	17-14178	7	.0001	800	17-2084	5	OUTPUT TRANS.	00-15998	SPK	SPEAKER (SEE MODEL)	
130	100	1	17-14219	27	DOUBLE PAD.		17-13077	6	POWER TRANS.	00-15995	SW1	AC LINE SWITCH	17-18009
151	.5M	VC	17-18008	48	.00025	600	17-4207				SW2	BAND SWITCH	17-18007
152	100K	VC	17-18009	59	.01	400	17-14615						
153	30K	VC	17-14243	96	.05	800	17-14121						
154	1.5M	1/4	17-14244	104	.01	200	17-4208						
156	.35	1/4	17-14248	122	.01	400	17-2189						
				33	.00005	800	17-14047						

I.F. PEAK 455 K.C.
 BROADCAST BALANCE AT 1500 K.C.
 PAD AT 600 K.C.
 SHORTWAVE BALANCE AT 15 M.C.
 CHECK AT 7 M.C.
 NOBLITT-SPARKS INDUSTRIES, INC.
 COLUMBUS, INDIANA

ARVIN RADIO CHASSIS RE 27

