


MODEL --- # 10

TUBES MAY BE METAL OR GT TYPE

**CROSLLEY**



The material presented on this page has been prepared by and is printed through the courtesy of THE CROSLLEY CORP.

Power Consumption @ 117.5 Volts Line—Approximately 43 Watts.  
 D. C. Drop Across Speaker Field—29 Volts.  
 Maximum Power Output Approximately 2.0 Watts.

**SOCKET VOLTAGES TAKEN @ 117.5 VOLT LINE (A. C.)**

Tube	Function	SOCKET PIN NUMBER							
		No. 1	No. 2	No. 3	No. 4	No. 5	No. 6	No. 7	No. 8
6SK7	R. F. Amplifier	GND.	H	3.0	GRID	3.0	92	H	91
6J7	Detector	GND.	H	20	8	2.0	—	H	2.0
25L6	Output	GND.	H	82	91	GRID	N.C.	H	5.8
25Z6	Rectifier	H	A.C.	120	A.C.	A.C.	H	H	120
W-46416	Ballast Resistor —165 Ohms (Cold)	Between No. 3 and No. 7 Pins with No. 7 and No. 8 Pins Tied Together.							