

MODEL 55U



NOTES: 1. I.F.-403 N.C.
2. NUMBERS SHOWN RELATIVE TO PARTS ARE OUR PART NUMBERS.

**BOTTOM VIEW
SHOWING TRIMMERS**

BOTTOM VIEW OF CHASSIS.

PEAK IF trimmers at 465 KC. BROADCAST BAND - Dial and generator to 1720 KC, adjust oscillator trimmer to peak, then dial and generator to 1400 KC, peak antenna trimmer. Dial and generator to 600 KC, pad oscillator circuit to peak, while rocking variable condenser. LONG WAVE BAND - Dial and generator to 390 KC, peak oscillator trimmer. Dial and generator to 350 KC, peak antenna trimmer. ad the oscillator circuit at 150 KC. while rocking variable condenser.

CONVENTIONAL ALIGNMENT -
(see special section)

VOLTAGE TABLE

NOTE: LINE VOLTAGE 115 VOLTS A.C. OR D.C.
HEATER VOLTAGES MEASURED DIRECTLY ACROSS
SOCKET TERMINALS.

