

# SELECTOR

- C1 VARIABLE CONDENSERS
- C2 EQUALIZING CONDENSERS
- L1 TUNING COILS
- L2 CATHODE COIL
- L3 R.F. CHOKE COIL
- L4 FIRST PLATE COIL
- L5 COUPLING COIL

# AMPLIFIER

- L6 FIRST R.F. TRANSFORMER
- L7 SECOND R.F. TRANSFORMER
- L8 THIRD R.F. TRANSFORMER
- L9 FOURTH R.F. TRANSFORMER
- L10 GRID COIL
- L11 DETECTOR PLATE CHOKE

SPARTON—Model  
Line Voltage 120—Set on 120-130 Volt Tap—Volume  
Control Position Max  
#250 or 585 types tubes.

TUBE	TYPE	POSITION	MEASURED PLUG IN SOCKET OF SET									
			A	B	C	D	E	F	G	H	I	J
1	484	1st RF	3	150	2.9	150	4.5	7.5	13	5.5	—	—
2	484	2nd RF	3	150	2.9	150	4.5	7.5	13	5.5	—	—
3	484	3rd RF	3	150	2.9	150	4.5	7.5	13	5.5	—	—
4	484	4th RF	3	150	2.9	150	4.5	7.5	13	5.5	—	—
5	484	5th RF	3	150	2.9	150	4.5	7.5	13	5.5	—	—
6	484	Det.	3	150	2.9	150	4.5	7.5	13	5.5	—	—
7	250	1st A	7.5	350	7.25	350	70	40	45	5	—	—
8	250	2nd A	7.5	350	7.25	350	70	40	45	5	—	—
9	251	Rect.	7.5	—	—	—	—	—	—	—	—	—
10	251	Rect.	7.5	—	—	—	—	—	—	—	—	—

\*Models 740 and 750—1 Additional 484 Tube in Selector

SPARKS WITHINGTON CO.

MODEL 564,570,  
740,750 AC

