



NOTE (1) PHONO MOTOR PLUG IS ON RADIO -  
PHONO COMBINATION MODELS ONLY

PHONO MOTOR PLUG  
NOTE 1

### Short Wave Reception

With a good antenna connected to it this receiver is able to pick up foreign and domestic short wave programs International broadcasts may be heard in the following bands

49 meter	60 — 62 Mc
31 meter	9.5 — 9.7 Mc
25 meter	11.7 — 11.9 Mc
19 meter	15.1 — 15.35 Mc
16 meter	17.75 — 17.85 Mc

Amateur radio stations may be heard on the 20 meter band from 14.0 to 14.4 Mc

### Tube Complement:

- 1 type 14Q7 Oscillator-Converter
- 1 type 14A7 IF Amplifier
- 1 type 14B6 Det AVC and Amplifier
- 2 type 35A5 Power Amp
- 1 type 35Y4 Rectifier

IF PEAK 455 KC

radio receiver designed to operate on

1 105-125 volts AC 60 cycles

2 105-125 volts DC \*

Power drawn is 50 watts