



FOR TEGOM

MODEL RCU

JAG. NO.	PART NO.	DESCRIPTION	DIAG. NO.	PART NO.	DESCRIPTION
C1	N-1345	.05 MFD 200 V	20% R8	N-4068	33 OHM 1.0W 20%
C2	N-9257	.03 MFD 200 V	-10%+10% R9	N-4061	47 MEGOHM .5W 20%
C3	N-1374	100MFD. MICA 500V.	20% R10	N-4896	2500 OHM .5W 10%
C4	N-4894	.005 MFD 600 V	-15%+40% R11	N-4899	220,000 OHM .5W 10%
C5	N-2063	3 MFD 600 V	-45%+40% R12	N-3029	22,000 OHM .5W 5%
C6	N-1367	6 MFD 150MV ELECTROLYTIC	20% R13	N-4470	12 MEGOHM .5W 10%
C7	N-4890	.0005 MFD 600 V	-25%+60% R14	N-4897	8,200 OHM .5W 10%
C8	N-1344	.01 MFD 400 V	20% R15	N-4067	180 OHM .5W 10%
C9	N-1376	.02 MFD 400 V	-20% R16	N-4027	470,000 OHM .5W 20%
C10	N-1351	.1 MFD 400 V	-10%+20% R17	N-4900	1200 OHM 1.0W 10%
C11	N-1372	.1 MFD 400 V	20% R18	N-4068	33 OHM 1.0W 20%
C12	N-3658	40 MFD 150 V ELECTROLYTIC	20% 1	N-4912	LOOP COIL
C13	N-1345	.05 MFD 200 V	20% 2	N-4810	OSCILLATOR COIL
C14	N-3658	40 MFD 150 V ELECTROLYTIC	20% 3	N-4872	15K 1 F. COIL
C15	N-1346	.05 MFD 400 V	20% 4	N-4873	2MD 1 F. COIL
R1	N-4025	22,000 OHM .5W	20% R1	N-4932	50N
R2	N-4026	220,000 OHM .5W	20% R2	N-4875	TONE SWITCH
R3	N-4052	33 MEGOHM 5W	20% R3	N-4875	OUTPUT TRANSFORMER
R4	N-4889	0.5 MEGOHM VOLUME CONTROL	20% R4	N-4869	5 PM DYNAMIC SPEAKER
R5	N-4061	47 MEGOHM .5W	20% R5	N-4907	2 GANG CONDENSER
R6	N-1778	100,000 OHM .5W	20% R6		
R7	N-4895	100,000 OHM .5W	10% R7		

[illegible]

J.F.-455 K.G.

6 TUBE A.C.-D.C.

SUPERHERO THERODYNE

SINGLE BAND

DRAWN *L. S.*

APPROVED *[Signature]*

DATE-9-27-1948