



STROMBERG-CARLSON NO. 920 RADIO RECEIVERS

Also Model 1020

Model	Input Power Frequency
920-H	50-60 Cycles
920-HB	25-60 Cycles
920-L	50-60 Cycles
920-LB	25-60 Cycles
920-PF	60 Cycle
920-PFB	25 Cycle
920-PG	60 Cycle
920-PGB	25 Cycle

I.F. 455 KC.

		TERMINALS OF SOCKETS							
Tube	Circuit	1	2	3	4	5	6	7	8
6SK7	R. F. Amp.	0	0.5	0	0	0	+85	0	+178
6SA7	Osc. and Mod.	0	0	+240	+85	0	0	0.5	0
6SF7	I. F. Amp. Demod. and A. V. C.	0	0	0	+95	0	+240	0	0.5
6SC7	Audio Amp. and Inverter	0	+65	0	0	+65	4*	0	0.5
6V6GT	Output	0	0	+235	+240	0	0	0.5	13*
6V6GT	Output	0	0.5	+235	+240	0	0	0	13*
5Y3G	Rectifier	0	+380	—	380	—	380	—	+380

*Read on lowest possible scale of voltmeter