



VOLTAGE CHART

R1	BE1301	25M ohm- $\frac{1}{2}$ w.
R2	BE1301	25M ohm- $\frac{1}{2}$ w.
R3	BE13019	1 megohm- $\frac{1}{2}$ w.
R4	BE130239	250 ohm- $\frac{1}{2}$ w.
R5	BE130218	5M ohm- $\frac{1}{2}$ w.
R6		1 megohm-in tuning indicator cable
R7	BE10662	12,500 ohm-3 w.
R8	BE13019	1 megohm- $\frac{1}{2}$ w.
R9	BE130232	25M ohm- $\frac{1}{2}$ w.
R10	BE130174	50 ohm- $\frac{1}{2}$ w.
R11	BE130220	300 ohm-1 w.
R12	BE1303	500M ohm- $\frac{1}{2}$ w.
R13	BE1303	500M ohm- $\frac{1}{2}$ w.
R14	BE130103	100M ohm- $\frac{1}{2}$ w.
R15	BE130218	5M ohm- $\frac{1}{2}$ w.
R16	BE130103	100M ohm- $\frac{1}{2}$ w.
R17	BE13019	.1 megohm- $\frac{1}{2}$ w.
R18	BE1303	500M ohm- $\frac{1}{2}$ w.
R19	BE13070	500 ohm- $\frac{1}{2}$ w.
R20	BE101267	2.8 megohm volume control
R21	BE13011	250M ohm- $\frac{1}{2}$ w.
R22	BE1303	500M ohm- $\frac{1}{2}$ w.
R23	BE130352	150M ohm- $\frac{1}{2}$ w.
R24	BE130351	80M ohm- $\frac{1}{2}$ w.
R25	BE1307	40M ohm- $\frac{1}{2}$ w.
R26	BE13012	50M ohm- $\frac{1}{2}$ w.
R27	BE1304	3 megohm- $\frac{1}{2}$ w.
R28	BE139191	1.5 megohm- $\frac{1}{2}$ w.
R29	BE130257	5 megohm- $\frac{1}{2}$ w.

C14	BE119109	15.0 x 450 w. v.
—OR—		
C14	BE119109B	15.0 x 450 w. v.
C15	BE119109	15.0 x 450 w. v.
—OR—		
C15	BE119109B	15.0 x 450 w. v.
C16	BE124144	B.C. oscillator trimmer
C17	BE10071	.004 x 600 v.
C18	BE129167	.0002 silver mica
C19	BE129165	.00005 mica
C20	BE124145	9 mc. osc. trimmer
C21	BE10013	.05 x 400 v.
C22	BE1009	.05 x 200 v.
C23	BE10026	.02 x 400 v.
C24	BE10020	.1 x 200 v.
C25	BE12951	.000125 mica
C26	BE1002	.003 x 300
C27	BE10026	.02 x 400 v.
C28	BE12921	.0002 mica
C29	BE10019	.006 x 600 v.
C30	BE100139	.0015 x 200 v.
C31	BE129165	.00005 mica
C32	BE129165	.00005 mica
C33	BE10061	.02 x 600 v. bakelite
C34	BE10061	.02 x 600 v. bakelite

C12, C14 and C15 are in same unit
C31 and C32 are in same unit

C1	BE1292	.0005 mica
C2	BE10047	.002 x 600 v.—10%
C3	BE124143	B.C. antenna trimmer
C4	BE124143	9 mc. antenna trimmer
C5	BE1292	.0005 mica
C6	BE10020	.1 x 200 v. tubular
C7	BE129168	.00001 mica
C8	BE124138	9 mc. R.F. trimmer
C9	BE124139	B.C. R.F. trimmer
C10	BE10074	.1 x 400 v.
C11	BE10074	.1 x 400 v.
C12	BE119109	10.0 x 350 w. v.
—OR—		
C12	BE119109B	10.0 x 350 w. v.
C13	BE1292	.0005 mica

JUNE 1941