

PHILCO TRANSITONE HOME RADIO MODELS PT-43 AND PT-55

Schem.
No.

Description

- 1 Loop Antenna Assembly
- 2 Tuning Condenser
- 3 Tubular Condenser (.05 mf., 200 v.)
- 4 Tubular Condenser (.25 mf., 400 v.)
- 5 Resistor (47,000 ohms, 1/4 watt) ..
- 6 Mica Condenser (110 mmf.)
- 7 Oscillator Transformer
- 8 Tubular Condenser (.05 mf., 200 v.)
- 9 1st I. F. Transformer
- 10 2nd I. F. Transformer
- 11 Resistor (2.2 megs., 1/4 watt)
- 12 Mica Condenser (250 mmf.)
- 13 Resistor (27,000 ohms, 1/2 watt) ..
- 14 Volume Control (500,000 ohms) ..
- 15 Tubular Condenser (.01 mf., 200 v.)
- 16 Resistor (4.7 megs., 1/4 watt)
- 17 Resistor (220,000 ohms, 1/4 watt)
- 18 Tubular Condenser (.01 mf., 400 v.)
- 19 Mica Condenser (250 mmf.)
- 20 Resistor (470,000 ohms, 1/4 watt)
- 21 Resistor (130 ohms, 1/2 watt)
- 22 Tubular Condenser (.04 mf., 400 v.)
- 23 Output Transformer,
.....Part of Speaker
- 24 Speaker
- 25 Tubular Condenser (.04 mf., 400 v.)
- 26 Electrolytic Condenser
(20-20 mf., 150 v.)
- 27 Field Coil,Part of Speaker
- 28 Pilot Lamp
- 29 Line Resistor

