



Models 41-260 and 41-265 are seven (7) tube alternating current (A. C.) operated superheterodyne radios incorporating electric push button in addition to manual tuning — and the new Philco built-in American and overseas loop aerial system. These models are also designed to receive the sound of a television program tuned in by special type Philco Television Radios.

In general, these models are similar with the exception of the tuning ranges and cabinet design. Model 41-260 has two (2) tuning ranges covering 540 to 1720 K. C. and 9.0 to 12.0 M. C. Model 41-265 consists of three (3) tuning ranges covering 540 to 1720 K. C., 2.0 to 7.0 M. C. and 9.0 to 12 M. C.

1	Ant. Section of Tuning Cond.	455 K. C.	Tuning Cond. Closed	Vol. Max. Range Switch "Brdest"	35A, 29A, 22A, 22B
2	Loop to Radio Loop See Sig. Gen. Above	1720 K. C.	1720 K. C.	Vol. Max. Range Switch "Brdest"	6A
3	Loop to Radio Loop See Sig. Gen. Above	1500 K. C.	1500 K. C.	Vol. Max. Range Switch "Brdest"	14
4	Loop to Radio Loop See Sig. Gen. Above	580 K. C.	580 K. C.	Vol. Max. Range Switch "Brdest"	14A
5	Loop to Radio Loop See Sig. Gen. Above	6 M. C.	6 M. C.	Range Switch Police	6
6'	Loop to Radio Loop See Sig. Gen. Above	12 M. C.	12 M. C.	Range Switch S. W.	6B, 15