

D2584, D2585

	POSITION OF VARIABLE	SIGNAL GENERATOR			TRIMMER ADJUSTMENTS (in order shown)
		FREQUENCY	DUMMY ANTENNA	CONNECTION TO RECEIVER	
IF	ROTOR FULL OPEN (Plates out of mesh)	455 kc.	.1 mfd.	Stator of RF section of var. condenser	Top and Bottom Slugs of IF Can T1 and T2
	ROTOR FULL OPEN (Plates out of mesh)	1650 kc.		Stator of RF section of var. condenser	Oscillator Trimmer T3
RF	1500 kc.	1500 kc.			RF Trimmer T4
	600 kc.	600		Fashion loop of several turns of wire and radiate sig. into loop of receiver adj. for max. output	Check Point